Pedestrian Blind Bell

☒Custom voice   ☒sound adjustable

Wait

Wait

Our Pedestrian blind bell is intended to use for providing the pedestrian safety in road traffic especially visually impaired people.

They are produced with capacitive sensor, which is produced as an alternative to mechanical pedestri- an buttons. When your hand is close enough to sensor, Our Pedestrian blind bell will detect this and transmit this information to intersection controller device. In addition to this; pedestrians are warned by the screen on the button in order to pass or wait. The touch button works sensitively and is not affected by foreign objects.

Our Pedestrian blind bell can be used in all pedestrian crossings especially in front of the schools, hospitals, bicycle crossings and so on.

The body of Our Pedestrian blind bell manufactured from ABS+PC mate- rial which make it resistance to any damage. More than one sound can be loaded into the device. Sounds installed in the device can be played with separate trigger .The operating range of the device is -20 / +60 degrees. The device can be operated with two different sources, AC 240V and DC 12V. Touch button take its power from the traffic light that is connected to. The maximum power consumption of pedestrian button about 2 watts and the blind clock push button power consumption about 3 watts. Body size of the device is 173.5 x 81.1 x 62.7 mm. There are connection entries which makes it easy to mount on the pole.

There is a capacitive microphone on the device. Therefore the voice level Pedestrian blind bell is automatic / Acoustic Characteristic (according to environment dB level).

Six key advantages

Pedestrian blind clock

NON-CONTACT TOUCH BUTTON

2.4G NETWORK TECHNOLOGY

VOICE PROMPTS LOUD

DAY &NIGHT VOLUME AUTOMATICALLY

32-BIT MCU AMBIENT DYNAMIC VOLUME

IP65 WATERPROOF

high strength shell

Outlook small, novel, compact, waterproof design, easy to install, ABS+PC material, high strength and anti-aging.

Wait

Automatically adjust the volume

Optional dynamic volume adjustment function, the blind clock can automatically adjust the volume according to the surrounding environment of the intersection, which is more intelligent.

MIC hole

Voice

Blind clock voice prompts loud, Volume can be adjusted, day and night volume automatically switch, At the same time, the sound source can be customized.

60DB

Wait

30DB

Wait

PC-side configuration software

The wireless blind clock button is equipped with a PC-side configuration software. By connecting the network cable, you can configure the button output mapping on the PC and adjust the voice volume of the blind clock..Blind clock button selection specifications.

PC-side configuration software

The wireless blind clock button is equipped with a PC-side configuration software. By connecting the network cable, you can configure the button output mapping on the PC and adjust the voice volume of the blind clock.. Blind clock button selection specifications

PedestriaButton Setting

Slave	Ped	OutPut	MaxVol	MinVol	SwitchV	Config
	☑ Ped-1	1	14	9	2,800	
	☑ Ped-2	1	14	9	2,800	
	☑ Ped-3	2	14	9	2,800	
	☑ Ped-4	2	14	9	2,800	Batch Query
	☑ Ped-5	3	14	9	2,800	
	☑ Ped-6	3	14	9	2,800	
	☑ Ped-7	4	14	9	2,800	
Ped	☑ Ped-8	4	14	9	2,800	
Button	☑ Ped-9	5	14	9	2,800	Batch Save
	☑ Ped-10	5	14	9	2,800	
	☑ Ped-11	6	14	9	2,800	
	☑ Ped-12	6	14	9	2,800	
	☑ Ped-13	7	14	9	2,800	Config WireLess
	☑ Ped-14	7	14	9	2,800	
	☑ Ped-15	8	14	9	2,800	
	☑ Ped-16	8	14	9	2,800	
Master	OB	WireLess Channel:		9		

IP65 waterproof level

The self-opening mold has good sealing effect, can adapt to outdoor work, and the waterproof level can

Wait

Custom voice

With led lights and language reminders, voice、 graphics can be custom-ized;

CUSTOM VOICE
OEM.ODM

Wait

Wait

Wait

Wait

?
Next
Follow US

Chinese prompt tone

English prompt tone

Spanish beep

animal sound or other

Appearance introduction

Photosensitive Light guide column

Automatic day and night sound switching

Wait

Text and light prompt area

Red light, text support OEM

Touch Sensing area

Can only be pressed under red light and flash for 10 seconds

Mounting hole

Speaker sound hole

Outlet hole

Mounting hole

MIC hole

According to the surrounding environment volume
Automatically adjust the blind clock volume

Pedestrian Blind Clock

SPECIFICATIONS

Model	PTB-20BS-V12
CONSUMPTION	<3W
WORKING VOLTAGE	100-240VAC
VOICE SPEAKER POWER	8Ω2W
VOICE DISTRIBUTION	30-90DB
DIMENSIONS AND MATERIALS	173.5x81.1 x62.7mm Material: ABS+PC
PROTECTION LEVEL BLIND BELL BUTTON	IP 65
AUDIO FILE	Default "Tick-tack" pedestrian button tone, voice can be customized
AUTOMATIC ADJUSTMENT	The volume is automatically adjusted according to the working environment of the device.

Product Size

62.7

81.1

173.5

81.1

62.7

173.5

173.5

81.1

Loja
Pedroso

A QUALIDADE QUE VOCÊ PROCURA ESTÁ AQUI

(49) 3278.4014

100 M

MANTE
CIDADE

TRA