

# Pro Convert HDMI Plus Technical Specifications

Copyright (c) 2011–2025 [Nanjing Magewell Electronics Co., Ltd.](#) All rights reserved.

Specifications are based on current hardware, firmware and software revisions, and are subject to change without notice.

HDMI, the HDMI logo and High-Definition Multimedia interface are trademarks or registered trademarks of HDMI Licensing LLC. NDI® is trademark or registered trademark of Vizrt NDI AB.

Revised on 10/11/2025

## Input & Loop through Features

- Max input & loop through signal:
  - 4096x2160 30fps 4:4:4:2:2
  - 4096x2160 60fps 4:2:0
- Input video at any format by custom EDID of input port
- Video formats: RGB, YUV BT.601/709/2020
- 8-channel HDMI-embedded audio
- HDMI interfaces: HDMI 1.4, DVI-D

## NDI® Encoding Features

- Encoding NDI High Bandwidth real-time stream at up to 2048x2160 120fps 4:2:2 8-bit
- Output the same resolution as input or any custom resolution. Typical outputs include:
  - 2048x1080p/1920x1080p 23.98/24/25/29.97/30/50/59.94/60
  - 1280x720p 23.98/24/25/29.97/30/50/59.94/60/100/119.88/120
  - 1920x1080i 25/29.97/30/50/59.94/60
  - 720x480p/720x480i 59.94/60/119.88/120
  - 720x576p/720x576i 50/100
- Output frame rate same as the original, 1/2, 1/3 or 1/4 of input frame rate
- Encoding 8-channel NDI-embedded audio
- Support NDI 6.2

## Configuration Management

- Register with Control Hub
- Remote control via WebUI and Control Hub
- Provide comprehensive information regarding the device and input signals in real-time
- Allow to configure how an input is processed and encoded, including deinterlacing, EDID, up/down scaling, frame rate, aspect ratio, as well as the network connection
- Update firmware
- Support USB RNDIS/ECM
- Support IE/Edge/Firefox/Chrome/Safari/Opera web browsers
- Provide HTTP APIs

## On-board Control Buttons

- 16 Position Rotary DIP Switch: set board-index from 0 to F

## PTZ Control

- Control PTZ cameras using protocols of VISCA, Visca UDP, Visca UDP2rs232, PELCO-P and PELCO-D via NDI
- Mini-DIN-8 jack (shared with Tally light)

## Network Interfaces

- 10/100/1000Mbps Ethernet
- IEEE 802.3af PoE

## USB Interface

- USB2.0 Type B
  - 5V/2.1A power supply
  - USB RNDIS/ECM

## Supported Products

- NDI Studio Monitor
- OBS
- vMix
- Any other NDI-enabled product

## LED Indicators

- Status LEDs indicate:
  - Power supply: on/off
  - Tally: preview/program
  - Input signal: locked/unlocked
  - Loop through signal: device connected and signal detected/undetected

## Form Factor

- 117.5mm (L) x 66.7mm (W) x 23.4mm (H)

## Accessories

- USB 2.0 A to B cable
- 5V/2.1A power adaptor
- Mini-DIN 8 breakout cable
- Tally light
- L-bracket

## Screw Mounting Hole

- ¼–20 threaded hole

## Power Consumption

- 5V max current: ~1.5A
- Max power consumption: ~8W

## Working Environment

- Operating temperature: 0 to 45 deg C
- Storage temperature: –20 to 70 deg C
- Relative humidity: 5% to 90% non-condensing