

VIS-FS100-A

Automatic feedback suppressor



VIS-FS100-A feedback suppressor uses a powerful signal processor and a fully automatic adaptive algorithm, which is easy to use. In addition to supporting 4-line / microphone input, it is also equipped with an AUDIOLINK digital audio cascade interface and supports 5 channel automatic mixer.

Features

- Fully automatic high-speed howling suppression algorithm, no need to debug, ready to use
- Eliminate feedback
- Automatically adapt to the acoustic environment
- Up to 12DB additional gain to effectively prevent feedback
- Equalized line or microphone input to provide phantom power
- With AUDIOLINK digital cascade input and output interface
- Four microphone inputs and digital interface AUDIOLINK inputs with automatic mixer

Function

- The adaptive filter can switch between "Fast" mode and "Precise" mode. Fast mode is suitable for situations where the microphone position changes frequently. Adaptive filters converge at a slower rate, suppressing more reverberation components. Depending on the acoustic environment and the selected operating mode, an additional gain of up to 12DB can be obtained before acoustic feedback occurs.
- The feedback suppressor also has a built-in automatic mixer to achieve four microphone inputs. In many cases, such as on a podium, pulpit, or conference table, the use of the above two microphones can better capture the voice of a moving speaker, which often increases the risk of acoustic feedback. In view of this problem, the automatic mixer in the feedback suppressor will automatically reduce the gain of the microphone with a weak signal input, while increasing the gain of another microphone with a strong signal input. In this way, it can track the speaker on the move, producing the best sound clarity. At the same time, since the total amount of gain remains constant, a maximum volume is maintained without generating acoustic feedback.
- When the feedback suppressor is configured with two AUDIOLINK cascade interfaces, it is connected to the CLEACON series conference controller through the AUDIOLINK interface, and the conference controller outputs audio to the feedback suppressor for mixing output, and can be cascaded to the next feedback suppressor or Other devices with AUDIOLINK interface.

- Even if the feedback suppressor is switched to the "bypass" mode, the automatic mixer function still works.

Controls and indicators

- Switch
- Bypass button with yellow LED
- Activate ACTIVE button with yellow LED
- Calibration button. Start quick calibration cycle
- 4-channel microphone / line input status indicator
- Overload (at 0DBFS), red LED
- Enable Auto Mix, yellow LED
- Calibration, yellow LED

Specification

Electrical characteristics

Power supply voltage230VAC / 115VAC, $\pm 10\%$, 50 / 60Hz
15W

Maximum starting power1.5A (230VAC) / 3A (115VAC)

Sampling rate..... 32KHZ

Frequency response.....125HZ-15KHZ

<1% at 1KHZ distortion

Gain0dB line in, 12dB / 0dB / -12dB (Low / Med / High) microphone input

Gain adjustment range..... Mute ~ 20dB

S / N ratio.....> 90DB

Signal delay<11 ms

Decoupler frequency variation..... up to 5HZ shielding noise

Line / microphone input

Maximum input level..... 6dBv

Output resistance..... <100 ohm

CMRR.....> 25DB (50HZ-20KHZ)

24V phantom power (microphone only, switchable)

10dBv maximum output level

conventional

Relative temperature <95%

Weight 3 kg

Operating temperature range from 10 ° C to 55 ° C

Storage temperature range 40 ° C to 70 ° C

Relative humidity <95%

Item Model for Order

VIS-FS100-A Five-channel Fully Automatic Feedback Suppressor

VIS-FS100 Four-channel full-automatic feedback suppressor