

Microwave Antennas

Product Specification





Copyright

© Ericsson AB 2019. All rights reserved. No part of this document may be reproduced in any form without the written permission of the copyright owner.

Disclaimer

The contents of this document are subject to revision without notice due to continued progress in methodology, design and manufacturing. Ericsson shall have no liability for any error or damage of any kind resulting from the use of this document.



Contents

1	Introduction.....	4
1.1	Portfolio Overview.....	4
1.2	Polarization	4
1.3	Performance	5
1.4	Integration.....	5
1.5	Kit Form	5
1.6	Modular antennas	6
1.7	Dual band antennas.....	6
1.8	MINI-LINK 6366 Compatibility	7
1.9	4+0 and 2+2 Compatibility	8
2	Product Name and Number.....	9
2.1	Product Name.....	9
2.2	Product Numbers.....	10
3	Electrical Data.....	22
3.1	Frequency Band	22
3.2	Gain.....	23
3.3	Half Power Beamwidth (HPBW).....	27
3.4	Cross-Polar Discrimination (XPD).....	29
3.5	Return Loss and VSWR.....	29
3.6	Front to Back Ratio (F/B)	30
3.7	Inter Port Isolation (IPI)	31
3.8	Radiation Pattern Envelope (RPE)	31
3.9	Compliance with International Standards	32
4	Mechanical Data.....	40
4.1	Dimensions	40
4.2	Weight	116
4.3	RF Interfaces	118
4.4	Pressurization	118
4.5	Material and Treatment.....	119
5	Environmental Data	123
5.1	Compliance with International Standards	123
5.2	Wind Velocity	123
5.3	Wind Loading, Force and Torque	125
5.4	Endurance	127
6	Mounting Data.....	128
6.1	Mounting Kit.....	128
6.2	Alignment.....	129
6.3	Installation Instruction	130
7	Packing Data	131
7.1	Dimensions	131
7.2	Weight	133
7.3	Compliance with International Standards	134
8	Document Revision Records	135



1 Introduction

1.1 Portfolio Overview

The microwave antenna portfolio ranges from 0.1 m to 3.7 m and from 4 GHz to 80 GHz.

Size [m]	Frequency [GHz]															
	4	5	6	7/8	10/11	13	15	18	23	24/26	28	32	38	42	60	80
0.1											X	X	X	X	X	X
0.2										X	X	X	X	X		X
0.3						X	X	X	X	X	X	X	X	X		X
0.6				X	X	X	X	X	X	X	X	X	X	X		X
0.9			X	X	X	X	X	X	X	X	X	X	X			
1.2		X	X	X	X	X	X	X	X	X						
1.8	X	X	X	X	X	X	X	X	X							
2.4	X	X	X	X	X	X	X									
3.0	X	X	X	X	X	X										
3.7	X	X	X	X												

Depending on frequency and antenna size different versions are available:

- Reflector antennas and flat panel antennas
- High performance and super high-performance antennas
- Single polarized and dual polarized antennas
- Dual band antennas, combining two frequency bands in one antenna
- Integrated antennas and antennas for separate installation

The antennas are used for both short haul (SH) and long haul (LH) systems.

Please see section 2 for a complete list of all different antennas available for the different systems.

1.2 Polarization

Single polarized antennas radiate in one polarization, vertical or horizontal polarization. The polarization is adjustable and is set at site during the installation.

Dual polarized antennas radiate in two polarizations simultaneously, vertical and horizontal polarization. The antenna has two ports, one for each polarization.



1.3 Performance

1.3.1 Radiation Pattern Envelope (RPE)

High performance antennas fulfil ETSI RPE class 3 (0.1 m 60 GHz class 2).

Super high-performance antennas fulfil ETSI RPE class 4, with only a few exceptions fulfilling class 3. The antennas have got an integrated radome, which protects the antenna from its physical environment (rain, snow, dirt, wind etc). The antennas are suitable for networks with a very high interference potential.

1.3.2 Return Loss

The system requirement on antenna return loss is:

Short haul	5-80 GHz	14 dB
Long haul	4-8 GHz	18 dB
Long haul	10-13 GHz	14 dB

1.4 Integration

The integrated antennas are installed with the radio unit without using any flexible waveguides, i.e. the radio is fitted directly to the rear of the antenna. The radio unit can easily be dismounted without affecting the antenna alignment.

All antennas (including the integrated antennas), except 80 GHz, can be installed separately from the radio unit using a flexible and/or elliptical waveguide. The antennas are equipped with a standardised waveguide interface (see section 4.3.2). The 2.4-3.7 m antennas are always installed separately from the radio unit.

The 0.1 m 60 GHz antenna is integrated in MINI-LINK 6351 and cannot be separated from the radio.

1.5 Kit Form

To reduce transportation and storage volume and cost the antennas are delivered as a kit, which must be assembled at site before the installation. The 2.4-3.7 m antennas are delivered with the reflector split in two pieces.



1.6

Modular antennas

Part of the antenna portfolio has got fixed radio interfaces (traditional way) and part of the portfolio has got a modular approach. Antennas with fixed interfaces have product numbers UKY 2** **/**** and modular antennas have product numbers BFZ 622 **/*****. Modular antennas are available for sizes 0.3-1.8 m.

Modular antennas are upgradeable from single to dual polarization and from one radio type to another by replacing the Interface module.

It is not possible to change the frequency band of the antenna by replacing the interface, since also other parts in the antenna are frequency dependent.

For detailed information regarding the Interface module, see 1301-URS 199 01+.

The Interface module must be from the same supplier as the antenna. Interface module A can only be used with an ANT A antenna and the Interface module B can only be used with an ANT B antenna.

1.7

Dual band antennas

Dual band antennas combine two frequency bands in the same antenna, a traditional band (e.g. 15, 18, 23 GHz) and E-band (80 GHz).

Single polarized (HP/HP) dual band antennas radiate in one polarization both for the traditional band and for the E-band. The polarization for the traditional band and the polarization for the E-band can be set in vertical or horizontal polarization independent of each other.

Dual polarized (HPX/HP) dual band antennas radiate in two polarizations (vertical and horizontal) simultaneously for the traditional band and in one polarization for the E-band. The polarization for the E-band can be set in vertical or horizontal.



Figure 1 ANT2/2 B 0.6 HP/HP equipped with MINI-LINK 6352 and RAU2.



1.8

MINI-LINK 6366 Compatibility

The outdoor modem unit MINI-LINK 6366/1 and MINI-LINK 6366/4 can be installed integrated with the ANT3 HP and ANT3 HPX antennas or installed close to the antenna on a pole or a wall.

The MINI-LINK 6366/1 and MINI-LINK 6366/4 can be installed according to Table 1, this for ANT A, ANT B and ANT C.




Figure 2 ANT3 A HPX equipped with MINI-LINK 6363 and MINI-LINK 6366/4.

Table 1 MINI-LINK 6366/1 and MINI-LINK 6366/4 compatibility

Size & Type ANT A ANT B ANT C [m]	Integrated installation on antenna	Integrated installation on antenna	Separate installation on Pole/Wall
	Configuration	Configuration	Configuration
1+0, 1+1, 2+0	4+0	1+0, 1+1, 2+0, 4+0	
No	No		Yes
Yes	No		Yes
Yes ¹	No		Yes
No	No		Yes

¹ Limited Antenna side strut angle and access inside MINI-LINK 6366/1 require additional handling when installed.



1.9

4+0 and 2+2 Compatibility

The ANT3 dual polarized antennas (HPX/SHPX) can be used in integrated installation for the configuration 4+0 and 2x(1+1), this adding two IPS3 to the installation (same frequency as the antenna).

It is also possible for all dual polarized antennas (except 80 GHz) to install 4+0 and 2x(1+1) separated from the antenna, using two IPS2 and two Sep Kit RAU2 when using RAU2 or two IPS3 and two SepKit3 when using MINI-LINK 6363.

IPS2 or IPS3 Sym is used for the configuration 4+0 and 2x(1+1) working standby.
IPS2 or IPS3 Asym is used for the configuration 2x(1+1) hot standby

The antennas that can be used in integrated installation for 4+0 and 2x(1+1) are presented in Table 2. ANT3 C antennas requires that a stabilizing side strut is installed, Ant Side Strut C 4+0, NTB 101 0557/4.




Figure 3 Dual polarized antenna equipped with two IPS3 and four MINI-LINK 6363

Table 2 ANT A HPX/SHPX, ANT B HPX and ANT C HPX compatibility for 4+0 and 2x(1+1)

Size [m]	Integrated installation ANT3 A HPX ANT3 A SHPX Configuration 4+0, 2x(1+1)	Integrated installation ANT3 B HPX Configuration 4+0, 2x(1+1)	Integrated installation ANT3 C HPX Configuration 4+0, 2x(1+1)	Separate installation ANT A HPX ANT A SHPX ANT B HPX ANT C HPX Configuration 4+0, 2x(1+1)
0.3-0.9 HPX	Yes	Yes	Yes ²	Yes ³
0.3-0.6 SHPX	Yes			Yes
0.9 SHPX	No			Yes
1.2-1.8 HPX	No	No	No	Yes
2.4-3.7 HPX	No	No		Yes

² Ant Side Strut C 4+0, NTB 101 0557/4 is required

³ Except 80 GHz



2

Product Name and Number

2.1

Product Name

The antenna product name is structured in the following way:

Xa b c d e

X=	ANT FPA	Reflector Antenna Flat Panel Antenna
a =	0 2 3 2/2	Antenna for separate installation Integrated antenna for RAU2, PT 2020, PT 6020, MINI-LINK 6352 and Fronthaul 6392 Integrated antenna for MINI-LINK 6363 Integrated antenna for RAU2, PT 2020 in the traditional bands and MINI-LINK 6352 for the E-band.
b =	A B C	Supplier A; CommScope Supplier B; RFS Supplier C; Ericsson
c =		Antenna size (in meters)
d =		Frequency band (in GHz)
e =	HP HPX SHP SHPX HP/HP HPX/HP	High performance, single polarized High performance, dual polarized Super high performance, single polarized Super high performance, dual polarized High performance in both the traditional frequency and the E-band High performance, dual polarized in the traditional frequency bands and high performance, single polarized in the E-band



2.2 Product Numbers

2.2.1 HP and HPX

Orderable product	System		
Product Name	Product Number		
ANT0 A 1.8 4 HPX	UKY 220 75/DC12	-	LH
ANT0 A 2.4 4 HPX	UKY 220 76/DC12	-	LH
ANT0 A 3.0 4 HPX	UKY 220 77/DC12	-	LH
ANT0 A 3.7 4 HPX	UKY 220 78/DC12	-	LH
ANT0 B 1.8 4 HPX	UKY 230 60/DC12	-	LH
ANT0 B 2.4 4 HPX	UKY 230 61/DC12	-	LH
ANT0 B 3.0 4 HPX	UKY 230 62/DC12	-	LH
ANT0 B 3.7 4 HPX	UKY 230 63/DC12	-	LH
ANT0 A 1.8 5 HPX	UKY 220 79/DC12	SH	LH
ANT0 A 2.4 5 HPX	UKY 220 80/DC12	SH	LH
ANT0 A 3.0 5 HPX	UKY 220 81/DC12	SH	LH
ANT0 A 3.7 5 HPX	UKY 220 82/DC12	SH	LH
ANT0 B 1.8 5 HPX	UKY 230 64/DC12	SH	LH
ANT0 B 2.4 5 HPX	UKY 230 65/DC12	SH	LH
ANT0 B 3.0 5 HPX	UKY 230 66/DC12	SH	LH
ANT0 B 3.7 5 HPX	UKY 230 67/DC12	SH	LH
ANT0 A 1.2 6 HPX	BFZ 622 34/0D01H	(SH)	LH
ANT0 A 1.8 6 HPX	BFZ 622 35/0D01H	(SH)	LH
ANT0 A 2.4 6 HPX	UKY 220 13/DC12	SH	LH
ANT0 A 3.0 6 HPX	UKY 220 14/DC12	SH	LH
ANT0 A 3.7 6 HPX	UKY 220 15/DC12	SH	LH
ANT2 A 0.9 6 HP	BFZ 622 33/2S01H	SH	-
ANT2 A 0.9 6 HPX	BFZ 622 33/2D01H	SH	-
ANT2 A 1.2 6 HP	BFZ 622 34/2S01H	SH	LH
ANT2 A 1.2 6 HPX	BFZ 622 34/2D01H	SH	(LH)
ANT2 A 1.8 6 HP	BFZ 622 35/2S01H	SH	LH
ANT2 A 1.8 6 HPX	BFZ 622 35/2D01H	SH	(LH)
ANT3 A 0.9 6 HP	BFZ 622 33/3S01H	SH	-
ANT3 A 0.9 6 HPX	BFZ 622 33/3D01H	SH	-
ANT3 A 1.2 6 HP	BFZ 622 34/3S01H	SH	LH
ANT3 A 1.2 6 HPX	BFZ 622 34/3D01H	SH	(LH)
ANT3 A 1.8 6 HP	BFZ 622 35/3S01H	SH	LH
ANT3 A 1.8 6 HPX	BFZ 622 35/3D01H	SH	(LH)
ANT0 B 1.2 6 HPX	BFZ 622 54/0D01H	(SH)	LH
ANT0 B 1.8 6 HPX	BFZ 622 55/0D01H	(SH)	LH
ANT0 B 2.4 6L HPX	UKY 230 68/DC12	SH	LH
ANT0 B 2.4 6U HPX	UKY 230 69/DC12	SH	LH
ANT0 B 3.0 6L HPX	UKY 230 70/DC12	SH	LH
ANT0 B 3.0 6U HPX	UKY 230 71/DC12	SH	LH
ANT0 B 3.7 6L HPX	UKY 230 72/DC12	SH	LH
ANT0 B 3.7 6U HPX	UKY 230 73/DC12	SH	LH
ANT3 B 0.9 6 HP	BFZ 622 53/3S01H	SH	-



ANT3 B 0.9 6 HPX	BFZ 622 53/3D01H	SH	-
ANT3 B 1.2 6 HP	BFZ 622 54/3S01H	SH	LH
ANT3 B 1.2 6 HPX	BFZ 622 54/3D01H	SH	(LH)
ANT3 B 1.8 6 HP	BFZ 622 55/3S01H	SH	LH
ANT3 B 1.8 6 HPX	BFZ 622 55/3D01H	SH	(LH)
ANT3 C 0.9 6 HP	BFZ 622 73/3S01H	SH	-
ANT3 C 0.9 6 HPX	BFZ 622 73/3D01H	SH	-
ANT3 C 1.2 6 HP	BFZ 622 74/3S01H	SH	LH
ANT3 C 1.2 6 HPX	BFZ 622 74/3D01H	SH	(LH)
ANT3 C 1.8 6 HP	BFZ 622 75/3S01H	SH	LH
ANT3 C 1.8 6 HPX	BFZ 622 75/3D01H	SH	(LH)
ANT0 A 1.2 7/8 HPX	BFZ 622 34/0D02H	(SH)	LH
ANT0 A 1.8 7/8 HPX	BFZ 622 35/0D02H	(SH)	LH
ANT0 A 2.4 7/8 HP	UKY 220 01/SC12	SH	LH
ANT0 A 2.4 7/8 HPX	UKY 220 01/DC12	SH	LH
ANT0 A 3.0 7/8 HP	UKY 220 04/SC12	SH	LH
ANT0 A 3.0 7/8 HPX	UKY 220 04/DC12	SH	LH
ANT0 A 3.7 7/8 HPX	UKY 220 06/DC12	SH	LH
ANT2 A 0.6 7/8 HP	BFZ 622 32/2S02H	SH	-
ANT2 A 0.6 7/8 HPX	BFZ 622 32/2D02H	SH	-
ANT2 A 0.9 7/8 HP	BFZ 622 33/2S02H	SH	-
ANT2 A 0.9 7/8 HPX	BFZ 622 33/2D02H	SH	-
ANT2 A 1.2 7/8 HP	BFZ 622 34/2S02H	SH	LH
ANT2 A 1.2 7/8 HPX	BFZ 622 34/2D02H	SH	(LH)
ANT2 A 1.8 7/8 HP	BFZ 622 35/2S02H	SH	LH
ANT2 A 1.8 7/8 HPX	BFZ 622 35/2D02H	SH	(LH)
ANT3 A 0.6 7/8 HP	BFZ 622 32/3S02H	SH	-
ANT3 A 0.6 7/8 HPX	BFZ 622 32/3D02H	SH	-
ANT3 A 0.9 7/8 HP	BFZ 622 33/3S02H	SH	-
ANT3 A 0.9 7/8 HPX	BFZ 622 33/3D02H	SH	-
ANT3 A 1.2 7/8 HP	BFZ 622 34/3S02H	SH	LH
ANT3 A 1.2 7/8 HPX	BFZ 622 34/3D02H	SH	(LH)
ANT3 A 1.8 7/8 HP	BFZ 622 35/3S02H	SH	LH
ANT3 A 1.8 7/8 HPX	BFZ 622 35/3D02H	SH	(LH)
ANT0 B 1.2 7/8 HPX	BFZ 622 54/0D02H	(SH)	LH
ANT0 B 1.8 7/8 HPX	BFZ 622 55/0D02H	(SH)	LH
ANT0 B 2.4 7/8 HPX	UKY 230 74/DC12	SH	LH
ANT0 B 3.0 7/8 HPX	UKY 230 75/DC12	SH	LH
ANT0 B 3.7 7/8 HPX	UKY 230 76/DC12	SH	LH
ANT3 B 0.6 7/8 HP	BFZ 622 52/3S02H	SH	-
ANT3 B 0.6 7/8 HPX	BFZ 622 52/3D02H	SH	-
ANT3 B 0.9 7/8 HP	BFZ 622 53/3S02H	SH	-
ANT3 B 0.9 7/8 HPX	BFZ 622 53/3D02H	SH	-
ANT3 B 1.2 7/8 HP	BFZ 622 54/3S02H	SH	LH
ANT3 B 1.2 7/8 HPX	BFZ 622 54/3D02H	SH	(LH)
ANT3 B 1.8 7/8 HP	BFZ 622 55/3S02H	SH	LH
ANT3 B 1.8 7/8 HPX	BFZ 622 55/3D02H	SH	(LH)
ANT3 C 0.6 7/8 HP	BFZ 622 72/3S02H	SH	-
ANT3 C 0.6 7/8 HPX	BFZ 622 72/3D02H	SH	-
ANT3 C 0.9 7/8 HP	BFZ 622 73/3S02H	SH	-
ANT3 C 0.9 7/8 HPX	BFZ 622 73/3D02H	SH	-
ANT3 C 1.2 7/8 HP	BFZ 622 74/3S02H	SH	LH
ANT3 C 1.2 7/8 HPX	BFZ 622 74/3D02H	SH	(LH)



ANT3 C 1.8 7/8 HP	BFZ 622 75/3S02H	SH	LH
ANT3 C 1.8 7/8 HPX	BFZ 622 75/3D02H	SH	(LH)
ANT0 A 1.2 10/11 HPX	BFZ 622 34/0D03H	(SH)	LH
ANT0 A 1.8 10/11 HPX	BFZ 622 35/0D03H	(SH)	LH
ANT0 A 2.4 10/11 HPX	UKY 220 19/DC12	SH	LH
ANT0 A 3.0 10/11 HPX	UKY 220 20/DC12	SH	LH
ANT2 A 0.6 10/11 HP	BFZ 622 32/2S03H	SH	LH
ANT2 A 0.6 10/11 HPX	BFZ 622 32/2D03H	SH	LH
ANT2 A 0.9 10/11 HP	BFZ 622 33/2S03H	SH	LH
ANT2 A 0.9 10/11 HPX	BFZ 622 33/2D03H	SH	LH
ANT2 A 1.2 10/11 HP	BFZ 622 34/2S03H	SH	LH
ANT2 A 1.2 10/11 HPX	BFZ 622 34/2D03H	SH	(LH)
ANT2 A 1.8 10/11 HP	BFZ 622 35/2S03H	SH	LH
ANT2 A 1.8 10/11 HPX	BFZ 622 35/2D03H	SH	(LH)
ANT3 A 0.6 10/11 HP	BFZ 622 32/3S03H	SH	LH
ANT3 A 0.6 10/11 HPX	BFZ 622 32/3D03H	SH	LH
ANT3 A 0.9 10/11 HP	BFZ 622 33/3S03H	SH	LH
ANT3 A 0.9 10/11 HPX	BFZ 622 33/3D03H	SH	LH
ANT3 A 1.2 10/11 HP	BFZ 622 34/3S03H	SH	LH
ANT3 A 1.2 10/11 HPX	BFZ 622 34/3D03H	SH	(LH)
ANT3 A 1.8 10/11 HP	BFZ 622 35/3S03H	SH	LH
ANT3 A 1.8 10/11 HPX	BFZ 622 35/3D03H	SH	(LH)
ANT0 B 1.2 10/11 HPX	BFZ 622 54/0D03H	(SH)	LH
ANT0 B 1.8 10/11 HPX	BFZ 622 55/0D03H	(SH)	LH
ANT0 B 2.4 10 HPX	UKY 230 77/DC12	SH	LH
ANT0 B 2.4 11 HPX	UKY 230 78/DC12	SH	LH
ANT0 B 3.0 10 HPX	UKY 230 79/DC12	SH	LH
ANT0 B 3.0 11 HPX	UKY 230 80/DC12	SH	LH
ANT3 B 0.6 10/11 HP	BFZ 622 52/3S03H	SH	LH
ANT3 B 0.6 10/11 HPX	BFZ 622 52/3D03H	SH	LH
ANT3 B 0.9 10/11 HP	BFZ 622 53/3S03H	SH	LH
ANT3 B 0.9 10/11 HPX	BFZ 622 53/3D03H	SH	LH
ANT3 B 1.2 10/11 HP	BFZ 622 54/3S03H	SH	LH
ANT3 B 1.2 10/11 HPX	BFZ 622 54/3D03H	SH	(LH)
ANT3 B 1.8 10/11 HP	BFZ 622 55/3S03H	SH	LH
ANT3 B 1.8 10/11 HPX	BFZ 622 55/3D03H	SH	(LH)
ANT3 C 0.6 10/11 HP	BFZ 622 72/3S03H	SH	LH
ANT3 C 0.6 10/11 HPX	BFZ 622 72/3D03H	SH	LH
ANT3 C 0.9 10/11 HP	BFZ 622 73/3S03H	SH	LH
ANT3 C 0.9 10/11 HPX	BFZ 622 73/3D03H	SH	LH
ANT3 C 1.2 10/11 HP	BFZ 622 74/3S03H	SH	LH
ANT3 C 1.2 10/11 HPX	BFZ 622 74/3D03H	SH	(LH)
ANT3 C 1.8 10/11 HP	BFZ 622 75/3S03H	SH	LH
ANT3 C 1.8 10/11 HPX	BFZ 622 75/3D03H	SH	(LH)
ANT0 A 1.2 13 HPX	BFZ 622 34/0D04H	(SH)	LH
ANT0 A 1.8 13 HPX	BFZ 622 35/0D04H	(SH)	LH
ANT0 A 2.4 13 HPX	UKY 220 02/DC12	SH	LH
ANT0 A 3.0 13 HPX	UKY 220 05/DC12	SH	LH
ANT2 A 0.3 13 HP	BFZ 622 31/2S04H	SH	LH
ANT2 A 0.3 13 HPX	BFZ 622 31/2D04H	SH	LH
ANT2 A 0.6 13 HP	BFZ 622 32/2S04H	SH	LH
ANT2 A 0.6 13 HPX	BFZ 622 32/2D04H	SH	LH
ANT2 A 0.9 13 HP	BFZ 622 33/2S04H	SH	LH



ANT2 A 0.9 13 HPX	BFZ 622 33/2D04H	SH	LH
ANT2 A 1.2 13 HP	BFZ 622 34/2S04H	SH	LH
ANT2 A 1.2 13 HPX	BFZ 622 34/2D04H	SH	(LH)
ANT2 A 1.8 13 HP	BFZ 622 35/2S04H	SH	LH
ANT2 A 1.8 13 HPX	BFZ 622 35/2D04H	SH	(LH)
ANT3 A 0.3 13 HP	BFZ 622 31/3S04H	SH	LH
ANT3 A 0.3 13 HPX	BFZ 622 31/3D04H	SH	LH
ANT3 A 0.6 13 HP	BFZ 622 32/3S04H	SH	LH
ANT3 A 0.6 13 HPX	BFZ 622 32/3D04H	SH	LH
ANT3 A 0.9 13 HP	BFZ 622 33/3S04H	SH	LH
ANT3 A 0.9 13 HPX	BFZ 622 33/3D04H	SH	LH
ANT3 A 1.2 13 HP	BFZ 622 34/3S04H	SH	LH
ANT3 A 1.2 13 HPX	BFZ 622 34/3D04H	SH	(LH)
ANT3 A 1.8 13 HP	BFZ 622 35/3S04H	SH	LH
ANT3 A 1.8 13 HPX	BFZ 622 35/3D04H	SH	(LH)
ANT0 B 1.2 13 HPX	BFZ 622 54/0D04H	(SH)	LH
ANT0 B 1.8 13 HPX	BFZ 622 55/0D04H	(SH)	LH
ANT0 B 2.4 13 HPX	UKY 230 81/DC12	SH	LH
ANT0 B 3.0 13 HPX	UKY 230 82/DC12	SH	LH
ANT3 B 0.3 13 HP	BFZ 622 51/3S04H	SH	LH
ANT3 B 0.3 13 HPX	BFZ 622 51/3D04H	SH	LH
ANT3 B 0.6 13 HP	BFZ 622 52/3S04H	SH	LH
ANT3 B 0.6 13 HPX	BFZ 622 52/3D04H	SH	LH
ANT3 B 0.9 13 HP	BFZ 622 53/3S04H	SH	LH
ANT3 B 0.9 13 HPX	BFZ 622 53/3D04H	SH	LH
ANT3 B 1.2 13 HP	BFZ 622 54/3S04H	SH	LH
ANT3 B 1.2 13 HPX	BFZ 622 54/3D04H	SH	(LH)
ANT3 B 1.8 13 HP	BFZ 622 55/3S04H	SH	LH
ANT3 B 1.8 13 HPX	BFZ 622 55/3D04H	SH	(LH)
ANT3 C 0.3 13 HP	BFZ 622 71/3S04H	SH	LH
ANT3 C 0.3 13 HPX	BFZ 622 71/3D04H	SH	LH
ANT3 C 0.6 13 HP	BFZ 622 72/3S04H	SH	LH
ANT3 C 0.6 13 HPX	BFZ 622 72/3D04H	SH	LH
ANT3 C 0.9 13 HP	BFZ 622 73/3S04H	SH	LH
ANT3 C 0.9 13 HPX	BFZ 622 73/3D04H	SH	LH
ANT3 C 1.2 13 HP	BFZ 622 74/3S04H	SH	LH
ANT3 C 1.2 13 HPX	BFZ 622 74/3D04H	SH	(LH)
ANT3 C 1.8 13 HP	BFZ 622 75/3S04H	SH	LH
ANT3 C 1.8 13 HPX	BFZ 622 75/3D04H	SH	(LH)
ANT0 A 2.4 15 HPX	UKY 220 03/DC12	SH	-
ANT2 A 0.3 15 HP	BFZ 622 31/2S05H	SH	-
ANT2 A 0.3 15 HPX	BFZ 622 31/2D05H	SH	-
ANT2 A 0.6 15 HP	BFZ 622 32/2S05H	SH	-
ANT2 A 0.6 15 HPX	BFZ 622 32/2D05H	SH	-
ANT2 A 0.9 15 HP	BFZ 622 33/2S05H	SH	-
ANT2 A 0.9 15 HPX	BFZ 622 33/2D05H	SH	-
ANT2 A 1.2 15 HP	BFZ 622 34/2S05H	SH	-
ANT2 A 1.2 15 HPX	BFZ 622 34/2D05H	SH	-
ANT2 A 1.8 15 HP	BFZ 622 35/2S05H	SH	-
ANT2 A 1.8 15 HPX	BFZ 622 35/2D05H	SH	-
ANT3 A 0.3 15 HP	BFZ 622 31/3S05H	SH	-
ANT3 A 0.3 15 HPX	BFZ 622 31/3D05H	SH	-
ANT3 A 0.6 15 HP	BFZ 622 32/3S05H	SH	-



ANT3 A 0.6 15 HPX	BFZ 622 32/3D05H	SH	-
ANT3 A 0.9 15 HP	BFZ 622 33/3S05H	SH	-
ANT3 A 0.9 15 HPX	BFZ 622 33/3D05H	SH	-
ANT3 A 1.2 15 HP	BFZ 622 34/3S05H	SH	-
ANT3 A 1.2 15 HPX	BFZ 622 34/3D05H	SH	-
ANT3 A 1.8 15 HP	BFZ 622 35/3S05H	SH	-
ANT3 A 1.8 15 HPX	BFZ 622 35/3D05H	SH	-
ANT0 B 2.4 15 HPX	UKY 230 83/DC12	SH	-
ANT3 B 0.3 15 HP	BFZ 622 51/3S05H	SH	-
ANT3 B 0.3 15 HPX	BFZ 622 51/3D05H	SH	-
ANT3 B 0.6 15 HP	BFZ 622 52/3S05H	SH	-
ANT3 B 0.6 15 HPX	BFZ 622 52/3D05H	SH	-
ANT3 B 0.9 15 HP	BFZ 622 53/3S05H	SH	-
ANT3 B 0.9 15 HPX	BFZ 622 53/3D05H	SH	-
ANT3 B 1.2 15 HP	BFZ 622 54/3S05H	SH	-
ANT3 B 1.2 15 HPX	BFZ 622 54/3D05H	SH	-
ANT3 B 1.8 15 HP	BFZ 622 55/3S05H	SH	-
ANT3 B 1.8 15 HPX	BFZ 622 55/3D05H	SH	-
ANT3 C 0.3 15 HP	BFZ 622 71/3S05H	SH	-
ANT3 C 0.3 15 HPX	BFZ 622 71/3D05H	SH	-
ANT3 C 0.6 15 HP	BFZ 622 72/3S05H	SH	-
ANT3 C 0.6 15 HPX	BFZ 622 72/3D05H	SH	-
ANT3 C 0.9 15 HP	BFZ 622 73/3S05H	SH	-
ANT3 C 0.9 15 HPX	BFZ 622 73/3D05H	SH	-
ANT3 C 1.2 15 HP	BFZ 622 74/3S05H	SH	-
ANT3 C 1.2 15 HPX	BFZ 622 74/3D05H	SH	-
ANT3 C 1.8 15 HP	BFZ 622 75/3S05H	SH	-
ANT3 C 1.8 15 HPX	BFZ 622 75/3D05H	SH	-
ANT2 A 0.3 18 HP	BFZ 622 31/2S06H	SH	-
ANT2 A 0.3 18 HPX	BFZ 622 31/2D06H	SH	-
ANT2 A 0.6 18 HP	BFZ 622 32/2S06H	SH	-
ANT2 A 0.6 18 HPX	BFZ 622 32/2D06H	SH	-
ANT2 A 0.9 18 HP	BFZ 622 33/2S06H	SH	-
ANT2 A 0.9 18 HPX	BFZ 622 33/2D06H	SH	-
ANT2 A 1.2 18 HP	BFZ 622 34/2S06H	SH	-
ANT2 A 1.2 18 HPX	BFZ 622 34/2D06H	SH	-
ANT2 A 1.8 18 HP	BFZ 622 35/2S06H	SH	-
ANT2 A 1.8 18 HPX	BFZ 622 35/2D06H	SH	-
ANT3 A 0.3 18 HP	BFZ 622 31/3S06H	SH	-
ANT3 A 0.3 18 HPX	BFZ 622 31/3D06H	SH	-
ANT3 A 0.6 18 HP	BFZ 622 32/3S06H	SH	-
ANT3 A 0.6 18 HPX	BFZ 622 32/3D06H	SH	-
ANT3 A 0.9 18 HP	BFZ 622 33/3S06H	SH	-
ANT3 A 0.9 18 HPX	BFZ 622 33/3D06H	SH	-
ANT3 A 1.2 18 HP	BFZ 622 34/3S06H	SH	-
ANT3 A 1.2 18 HPX	BFZ 622 34/3D06H	SH	-
ANT3 A 1.8 18 HP	BFZ 622 35/3S06H	SH	-
ANT3 A 1.8 18 HPX	BFZ 622 35/3D06H	SH	-
ANT3 B 0.3 18 HP	BFZ 622 51/3S06H	SH	-
ANT3 B 0.3 18 HPX	BFZ 622 51/3D06H	SH	-
ANT3 B 0.6 18 HP	BFZ 622 52/3S06H	SH	-
ANT3 B 0.6 18 HPX	BFZ 622 52/3D06H	SH	-
ANT3 B 0.9 18 HP	BFZ 622 53/3S06H	SH	-



ANT3 B 0.9 18 HPX	BFZ 622 53/3D06H	SH	-
ANT3 B 1.2 18 HP	BFZ 622 54/3S06H	SH	-
ANT3 B 1.2 18 HPX	BFZ 622 54/3D06H	SH	-
ANT3 B 1.8 18 HP	BFZ 622 55/3S06H	SH	-
ANT3 B 1.8 18 HPX	BFZ 622 55/3D06H	SH	-
ANT3 C 0.3 18 HP	BFZ 622 71/3S06H	SH	-
ANT3 C 0.3 18 HPX	BFZ 622 71/3D06H	SH	-
ANT3 C 0.6 18 HP	BFZ 622 72/3S06H	SH	-
ANT3 C 0.6 18 HPX	BFZ 622 72/3D06H	SH	-
ANT3 C 0.9 18 HP	BFZ 622 73/3S06H	SH	-
ANT3 C 0.9 18 HPX	BFZ 622 73/3D06H	SH	-
ANT3 C 1.2 18 HP	BFZ 622 74/3S06H	SH	-
ANT3 C 1.2 18 HPX	BFZ 622 74/3D06H	SH	-
ANT3 C 1.8 18 HP	BFZ 622 75/3S06H	SH	-
ANT3 C 1.8 18 HPX	BFZ 622 75/3D06H	SH	-
ANT2 A 0.2 23 HP	UKY 220 90/SC15	SH	-
ANT2 A 0.3 23 HP	BFZ 622 31/2S07H	SH	-
ANT2 A 0.3 23 HPX	BFZ 622 31/2D07H	SH	-
ANT2 A 0.6 23 HP	BFZ 622 32/2S07H	SH	-
ANT2 A 0.6 23 HPX	BFZ 622 32/2D07H	SH	-
ANT2 A 0.9 23 HP	BFZ 622 33/2S07H	SH	-
ANT2 A 0.9 23 HPX	BFZ 622 33/2D07H	SH	-
ANT2 A 1.2 23 HP	BFZ 622 34/2S07H	SH	-
ANT2 A 1.2 23 HPX	BFZ 622 34/2D07H	SH	-
ANT2 A 1.8 23 HP	BFZ 622 35/2S07H	SH	-
ANT2 A 1.8 23 HPX	BFZ 622 35/2D07H	SH	-
ANT3 A 0.3 23 HP	BFZ 622 31/3S07H	SH	-
ANT3 A 0.3 23 HPX	BFZ 622 31/3D07H	SH	-
ANT3 A 0.6 23 HP	BFZ 622 32/3S07H	SH	-
ANT3 A 0.6 23 HPX	BFZ 622 32/3D07H	SH	-
ANT3 A 0.9 23 HP	BFZ 622 33/3S07H	SH	-
ANT3 A 0.9 23 HPX	BFZ 622 33/3D07H	SH	-
ANT3 A 1.2 23 HP	BFZ 622 34/3S07H	SH	-
ANT3 A 1.2 23 HPX	BFZ 622 34/3D07H	SH	-
ANT3 A 1.8 23 HP	BFZ 622 35/3S07H	SH	-
ANT3 A 1.8 23 HPX	BFZ 622 35/3D07H	SH	-
ANT3 B 0.3 23 HP	BFZ 622 51/3S07H	SH	-
ANT3 B 0.3 23 HPX	BFZ 622 51/3D07H	SH	-
ANT3 B 0.6 23 HP	BFZ 622 52/3S07H	SH	-
ANT3 B 0.6 23 HPX	BFZ 622 52/3D07H	SH	-
ANT3 B 0.9 23 HP	BFZ 622 53/3S07H	SH	-
ANT3 B 0.9 23 HPX	BFZ 622 53/3D07H	SH	-
ANT3 B 1.2 23 HP	BFZ 622 54/3S07H	SH	-
ANT3 B 1.2 23 HPX	BFZ 622 54/3D07H	SH	-
ANT3 B 1.8 23 HP	BFZ 622 55/3S07H	SH	-
ANT3 B 1.8 23 HPX	BFZ 622 55/3D07H	SH	-
ANT3 C 0.3 23 HP	BFZ 622 71/3S07H	SH	-
ANT3 C 0.3 23 HPX	BFZ 622 71/3D07H	SH	-
ANT3 C 0.6 23 HP	BFZ 622 72/3S07H	SH	-
ANT3 C 0.6 23 HPX	BFZ 622 72/3D07H	SH	-
ANT3 C 0.9 23 HP	BFZ 622 73/3S07H	SH	-
ANT3 C 0.9 23 HPX	BFZ 622 73/3D07H	SH	-
ANT3 C 1.2 23 HP	BFZ 622 74/3S07H	SH	-



ANT3 C 1.2 23 HPX	BFZ 622 74/3D07H	SH	-
ANT3 C 1.8 23 HP	BFZ 622 75/3S07H	SH	-
ANT3 C 1.8 23 HPX	BFZ 622 75/3D07H	SH	-
ANT2 A 0.2 24/26 HP	UKY 220 91/SC15	SH	-
ANT2 A 0.3 24/26 HP	BFZ 622 31/2S08H	SH	-
ANT2 A 0.3 24/26 HPX	BFZ 622 31/2D08H	SH	-
ANT2 A 0.6 24/26 HP	BFZ 622 32/2S08H	SH	-
ANT2 A 0.6 24/26 HPX	BFZ 622 32/2D08H	SH	-
ANT2 A 0.9 24/26 HP	BFZ 622 33/2S08H	SH	-
ANT2 A 0.9 24/26 HPX	BFZ 622 33/2D08H	SH	-
ANT2 A 1.2 24/26 HP	BFZ 622 34/2S08H	SH	-
ANT2 A 1.2 24/26 HPX	BFZ 622 34/2D08H	SH	-
ANT3 A 0.3 24/26 HP	BFZ 622 31/3S08H	SH	-
ANT3 A 0.3 24/26 HPX	BFZ 622 31/3D08H	SH	-
ANT3 A 0.6 24/26 HP	BFZ 622 32/3S08H	SH	-
ANT3 A 0.6 24/26 HPX	BFZ 622 32/3D08H	SH	-
ANT3 A 0.9 24/26 HP	BFZ 622 33/3S08H	SH	-
ANT3 A 0.9 24/26 HPX	BFZ 622 33/3D08H	SH	-
ANT3 A 1.2 24/26 HP	BFZ 622 34/3S08H	SH	-
ANT3 A 1.2 24/26 HPX	BFZ 622 34/3D08H	SH	-
ANT3 B 0.3 24/26 HP	BFZ 622 51/3S08H	SH	-
ANT3 B 0.3 24/26 HPX	BFZ 622 51/3D08H	SH	-
ANT3 B 0.6 24/26 HP	BFZ 622 52/3S08H	SH	-
ANT3 B 0.6 24/26 HPX	BFZ 622 52/3D08H	SH	-
ANT3 B 0.9 24/26 HP	BFZ 622 53/3S08H	SH	-
ANT3 B 0.9 24/26 HPX	BFZ 622 53/3D08H	SH	-
ANT3 B 1.2 24/26 HP	BFZ 622 54/3S08H	SH	-
ANT3 B 1.2 24/26 HPX	BFZ 622 54/3D08H	SH	-
ANT3 C 0.3 24/26 HP	BFZ 622 71/3S08H	SH	-
ANT3 C 0.3 24/26 HPX	BFZ 622 71/3D08H	SH	-
ANT3 C 0.6 24/26 HP	BFZ 622 72/3S08H	SH	-
ANT3 C 0.6 24/26 HPX	BFZ 622 72/3D08H	SH	-
ANT3 C 0.9 24/26 HP	BFZ 622 73/3S08H	SH	-
ANT3 C 0.9 24/26 HPX	BFZ 622 73/3D08H	SH	-
ANT3 C 1.2 24/26 HP	BFZ 622 74/3S08H	SH	-
ANT3 C 1.2 24/26 HPX	BFZ 622 74/3D08H	SH	-
ANT2 A 0.2 28 HP	UKY 220 92/SC15	SH	-
ANT2 A 0.3 28 HP	BFZ 622 31/2S09H	SH	-
ANT2 A 0.3 28 HPX	BFZ 622 31/2D09H	SH	-
ANT2 A 0.6 28 HP	BFZ 622 32/2S09H	SH	-
ANT2 A 0.6 28 HPX	BFZ 622 32/2D09H	SH	-
ANT2 A 0.9 28 HP	BFZ 622 33/2S09H	SH	-
ANT2 A 0.9 28 HPX	BFZ 622 33/2D09H	SH	-
ANT3 A 0.3 28 HP	BFZ 622 31/3S09H	SH	-
ANT3 A 0.3 28 HPX	BFZ 622 31/3D09H	SH	-
ANT3 A 0.6 28 HP	BFZ 622 32/3S09H	SH	-
ANT3 A 0.6 28 HPX	BFZ 622 32/3D09H	SH	-
ANT3 A 0.9 28 HP	BFZ 622 33/3S09H	SH	-
ANT3 A 0.9 28 HPX	BFZ 622 33/3D09H	SH	-
ANT3 B 0.3 28 HP	BFZ 622 51/3S09H	SH	-
ANT3 B 0.3 28 HPX	BFZ 622 51/3D09H	SH	-
ANT3 B 0.6 28 HP	BFZ 622 52/3S09H	SH	-
ANT3 B 0.6 28 HPX	BFZ 622 52/3D09H	SH	-



ANT3 B 0.9 28 HP	BFZ 622 53/3S09H	SH	-
ANT3 B 0.9 28 HPX	BFZ 622 53/3D09H	SH	-
ANT3 C 0.3 28 HP	BFZ 622 71/3S09H	SH	-
ANT3 C 0.3 28 HPX	BFZ 622 71/3D09H	SH	-
ANT3 C 0.6 28 HP	BFZ 622 72/3S09H	SH	-
ANT3 C 0.6 28 HPX	BFZ 622 72/3D09H	SH	-
ANT3 C 0.9 28 HP	BFZ 622 73/3S09H	SH	-
ANT3 C 0.9 28 HPX	BFZ 622 73/3D09H	SH	-
ANT2 A 0.2 32 HP	UKY 220 93/SC15	SH	-
ANT2 A 0.3 32 HP	BFZ 622 31/2S10H	SH	-
ANT2 A 0.3 32 HPX	BFZ 622 31/2D10H	SH	-
ANT2 A 0.6 32 HP	BFZ 622 32/2S10H	SH	-
ANT2 A 0.6 32 HPX	BFZ 622 32/2D10H	SH	-
ANT2 A 0.9 32 HP	BFZ 622 33/2S10H	SH	-
ANT2 A 0.9 32 HPX	BFZ 622 33/2D10H	SH	-
ANT3 A 0.3 32 HP	BFZ 622 31/3S10H	SH	-
ANT3 A 0.3 32 HPX	BFZ 622 31/3D10H	SH	-
ANT3 A 0.6 32 HP	BFZ 622 32/3S10H	SH	-
ANT3 A 0.6 32 HPX	BFZ 622 32/3D10H	SH	-
ANT3 A 0.9 32 HP	BFZ 622 33/3S10H	SH	-
ANT3 A 0.9 32 HPX	BFZ 622 33/3D10H	SH	-
ANT3 B 0.3 32 HP	BFZ 622 51/3S10H	SH	-
ANT3 B 0.3 32 HPX	BFZ 622 51/3D10H	SH	-
ANT3 B 0.6 32 HP	BFZ 622 52/3S10H	SH	-
ANT3 B 0.6 32 HPX	BFZ 622 52/3D10H	SH	-
ANT3 B 0.9 32 HP	BFZ 622 53/3S10H	SH	-
ANT3 B 0.9 32 HPX	BFZ 622 53/3D10H	SH	-
ANT3 C 0.3 32 HP	BFZ 622 71/3S10H	SH	-
ANT3 C 0.3 32 HPX	BFZ 622 71/3D10H	SH	-
ANT3 C 0.6 32 HP	BFZ 622 72/3S10H	SH	-
ANT3 C 0.6 32 HPX	BFZ 622 72/3D10H	SH	-
ANT3 C 0.9 32 HP	BFZ 622 73/3S10H	SH	-
ANT3 C 0.9 32 HPX	BFZ 622 73/3D10H	SH	-
ANT2 A 0.2 38 HP	UKY 220 94/SC15	SH	-
ANT2 A 0.3 38 HP	BFZ 622 31/2S11H	SH	-
ANT2 A 0.3 38 HPX	BFZ 622 31/2D11H	SH	-
ANT2 A 0.6 38 HP	BFZ 622 32/2S11H	SH	-
ANT2 A 0.6 38 HPX	BFZ 622 32/2D11H	SH	-
ANT2 A 0.9 38 HP	BFZ 622 33/2S11H	SH	-
ANT2 A 0.9 38 HPX	BFZ 622 33/2D11H	SH	-
ANT3 A 0.3 38 HP	BFZ 622 31/3S11H	SH	-
ANT3 A 0.3 38 HPX	BFZ 622 31/3D11H	SH	-
ANT3 A 0.6 38 HP	BFZ 622 32/3S11H	SH	-
ANT3 A 0.6 38 HPX	BFZ 622 32/3D11H	SH	-
ANT3 A 0.9 38 HP	BFZ 622 33/3S11H	SH	-
ANT3 A 0.9 38 HPX	BFZ 622 33/3D11H	SH	-
ANT3 B 0.3 38 HP	BFZ 622 51/3S11H	SH	-
ANT3 B 0.3 38 HPX	BFZ 622 51/3D11H	SH	-
ANT3 B 0.6 38 HP	BFZ 622 52/3S11H	SH	-
ANT3 B 0.6 38 HPX	BFZ 622 52/3D11H	SH	-
ANT3 B 0.9 38 HP	BFZ 622 53/3S11H	SH	-
ANT3 B 0.9 38 HPX	BFZ 622 53/3D11H	SH	-



ANT3 C 0.3 38 HP	BFZ 622 71/3S11H	SH	-
ANT3 C 0.3 38 HPX	BFZ 622 71/3D11H	SH	-
ANT3 C 0.6 38 HP	BFZ 622 72/3S11H	SH	-
ANT3 C 0.6 38 HPX	BFZ 622 72/3D11H	SH	-
ANT3 C 0.9 38 HP	BFZ 622 73/3S11H	SH	-
ANT3 C 0.9 38 HPX	BFZ 622 73/3D11H	SH	-
ANT2 A 0.2 42 HP	UKY 220 95/SC15	SH	-
ANT2 A 0.3 42 HP	BFZ 622 31/2S12H	SH	-
ANT2 A 0.3 42 HPX	BFZ 622 31/2D12H	SH	-
ANT2 A 0.6 42 HP	BFZ 622 32/2S12H	SH	-
ANT2 A 0.6 42 HPX	BFZ 622 32/2D12H	SH	-
ANT3 A 0.3 42 HP	BFZ 622 31/3S12H	SH	-
ANT3 A 0.3 42 HPX	BFZ 622 31/3D12H	SH	-
ANT3 A 0.6 42 HP	BFZ 622 32/3S12H	SH	-
ANT3 A 0.6 42 HPX	BFZ 622 32/3D12H	SH	-
ANT3 B 0.3 42 HP	BFZ 622 51/3S12H	SH	-
ANT3 B 0.3 42 HPX	BFZ 622 51/3D12H	SH	-
ANT3 B 0.6 42 HP	BFZ 622 52/3S12H	SH	-
ANT3 B 0.6 42 HPX	BFZ 622 52/3D12H	SH	-
ANT3 C 0.3 42 HP	BFZ 622 71/3S12H	SH	-
ANT3 C 0.3 42 HPX	BFZ 622 71/3D12H	SH	-
ANT3 C 0.6 42 HP	BFZ 622 72/3S12H	SH	-
ANT3 C 0.6 42 HPX	BFZ 622 72/3D12H	SH	-
ANT 0.1 60 HP	UKY 230 31/SC10	SH	-
ANT2 A 0.1 80 HP	UKY 230 39/2S14H	SH	-
ANT2 A 0.2 80 HP	UKY 220 96/SC15	SH	-
ANT2 A 0.3 80 HP	BFZ 622 31/2S14H	SH	-
ANT2 A 0.3 80 HPX	BFZ 622 31/2D14H	SH	-
ANT2 A 0.6 80 HP	BFZ 622 32/2S14H	SH	-
ANT2 A 0.6 80 HPX	BFZ 622 32/2D14H	SH	-
ANT3 A 0.3 80 HP	BFZ 622 31/3S14H	SH	-
ANT3 A 0.3 80 HPX	BFZ 622 31/3D14H	SH	-
ANT3 A 0.6 80 HP	BFZ 622 32/3S14H	SH	-
ANT3 A 0.6 80 HPX	BFZ 622 32/3D14H	SH	-
ANT2 B 0.3 80 HP	BFZ 622 51/2S14H	SH	-
ANT2 B 0.3 80 HPX	BFZ 622 51/2D14H	SH	-
ANT2 B 0.6 80 HP	BFZ 622 52/2S14H	SH	-
ANT2 B 0.6 80 HPX	BFZ 622 52/2D14H	SH	-
ANT3 B 0.3 80 HP	BFZ 622 51/3S14H	SH	-
ANT3 B 0.3 80 HPX	BFZ 622 51/3D14H	SH	-
ANT3 B 0.6 80 HP	BFZ 622 52/3S14H	SH	-
ANT3 B 0.6 80 HPX	BFZ 622 52/3D14H	SH	-
ANT2 C 0.3 80 HP	BFZ 622 71/2S14H	SH	-
ANT2 C 0.3 80 HPX	BFZ 622 71/2D14H	SH	-
ANT3 C 0.3 80 HP	BFZ 622 71/3S14H	SH	-
ANT3 C 0.3 80 HPX	BFZ 622 71/3D14H	SH	-
ANT2 C 0.6 80 HP	BFZ 622 72/2S14H	SH	-
ANT2 C 0.6 80 HPX	BFZ 622 72/2D14H	SH	-
ANT3 C 0.6 80 HP	BFZ 622 72/3S14H	SH	-
ANT3 C 0.6 80 HPX	BFZ 622 72/3D14H	SH	-



2.2.2

SHP and SHPX

Orderable product		System	
Product Name	Product Number		
ANT2 A 0.9 6 SHP	BFZ 622 33/2S01S	SH	-
ANT2 A 0.9 6 SHPX	BFZ 622 33/2D01S	SH	-
ANT3 A 0.9 6 SHP	BFZ 622 33/3S01S	SH	-
ANT3 A 0.9 6 SHPX	BFZ 622 33/3D01S	SH	-
ANT2 A 0.9 10/11 SHP	BFZ 622 33/2S03S	SH	LH
ANT2 A 0.9 10/11 SHPX	BFZ 622 33/2D03S	SH	LH
ANT3 A 0.9 10/11 SHP	BFZ 622 33/3S03S	SH	LH
ANT3 A 0.9 10/11 SHPX	BFZ 622 33/3D03S	SH	LH
ANT2 A 0.6 13 SHP	BFZ 622 32/2S04S	SH	LH
ANT2 A 0.6 13 SHPX	BFZ 622 32/2D04S	SH	LH
ANT2 A 0.9 13 SHP	BFZ 622 33/2S04S	SH	LH
ANT2 A 0.9 13 SHPX	BFZ 622 33/2D04S	SH	LH
ANT3 A 0.6 13 SHP	BFZ 622 32/3S04S	SH	LH
ANT3 A 0.6 13 SHPX	BFZ 622 32/3D04S	SH	LH
ANT3 A 0.9 13 SHP	BFZ 622 33/3S04S	SH	LH
ANT3 A 0.9 13 SHPX	BFZ 622 33/3D04S	SH	LH
ANT2 A 0.6 15 SHP	BFZ 622 32/2S05S	SH	-
ANT2 A 0.6 15 SHPX	BFZ 622 32/2D05S	SH	-
ANT2 A 0.9 15 SHP	BFZ 622 33/2S05S	SH	-
ANT2 A 0.9 15 SHPX	BFZ 622 33/2D05S	SH	-
ANT3 A 0.6 15 SHP	BFZ 622 32/3S05S	SH	-
ANT3 A 0.6 15 SHPX	BFZ 622 32/3D05S	SH	-
ANT3 A 0.9 15 SHP	BFZ 622 33/3S05S	SH	-
ANT3 A 0.9 15 SHPX	BFZ 622 33/3D05S	SH	-
ANT2 A 0.6 18 SHP	BFZ 622 32/2S06S	SH	-
ANT2 A 0.6 18 SHPX	BFZ 622 32/2D06S	SH	-
ANT2 A 0.9 18 SHP	BFZ 622 33/2S06S	SH	-
ANT2 A 0.9 18 SHPX	BFZ 622 33/2D06S	SH	-
ANT3 A 0.6 18 SHP	BFZ 622 32/3S06S	SH	-
ANT3 A 0.6 18 SHPX	BFZ 622 32/3D06S	SH	-
ANT3 A 0.9 18 SHP	BFZ 622 33/3S06S	SH	-
ANT3 A 0.9 18 SHPX	BFZ 622 33/3D06S	SH	-
ANT2 A 0.3 23 SHP	BFZ 622 31/2S07S	SH	-
ANT2 A 0.3 23 SHPX	BFZ 622 31/2D07S	SH	-
ANT2 A 0.6 23 SHP	BFZ 622 32/2S07S	SH	-
ANT2 A 0.6 23 SHPX	BFZ 622 32/2D07S	SH	-
ANT2 A 0.9 23 SHP	BFZ 622 33/2S07S	SH	-
ANT2 A 0.9 23 SHPX	BFZ 622 33/2D07S	SH	-
ANT3 A 0.3 23 SHP	BFZ 622 31/3S07S	SH	-
ANT3 A 0.3 23 SHPX	BFZ 622 31/3D07S	SH	-
ANT3 A 0.6 23 SHP	BFZ 622 32/3S07S	SH	-
ANT3 A 0.6 23 SHPX	BFZ 622 32/3D07S	SH	-
ANT3 A 0.9 23 SHP	BFZ 622 33/3S07S	SH	-
ANT3 A 0.9 23 SHPX	BFZ 622 33/3D07S	SH	-
ANT2 A 0.3 24/26 SHP	BFZ 622 31/2S08S	SH	-
ANT2 A 0.3 24/26 SHPX	BFZ 622 31/2D08S	SH	-
ANT2 A 0.6 24/26 SHP	BFZ 622 32/2S08S	SH	-



ANT2 A 0.6 24/26 SHPX	BFZ 622 32/2D08S	SH	-
ANT2 A 0.9 24/26 SHP	BFZ 622 33/2S08S	SH	-
ANT2 A 0.9 24/26 SHPX	BFZ 622 33/2D08S	SH	-
ANT3 A 0.3 24/26 SHP	BFZ 622 31/3S08S	SH	-
ANT3 A 0.3 24/26 SHPX	BFZ 622 31/3D08S	SH	-
ANT3 A 0.6 24/26 SHP	BFZ 622 32/3S08S	SH	-
ANT3 A 0.6 24/26 SHPX	BFZ 622 32/3D08S	SH	-
ANT3 A 0.9 24/26 SHP	BFZ 622 33/3S08S	SH	-
ANT3 A 0.9 24/26 SHPX	BFZ 622 33/3D08S	SH	-
ANT2 A 0.3 28 SHP	BFZ 622 31/2S09S	SH	-
ANT2 A 0.3 28 SHPX	BFZ 622 31/2D09S	SH	-
ANT2 A 0.6 28 SHP	BFZ 622 32/2S09S	SH	-
ANT2 A 0.6 28 SHPX	BFZ 622 32/2D09S	SH	-
FPA3 A 0.1 28 SHP	UKY 230 50/3S09S	SH	-
ANT3 A 0.3 28 SHP	BFZ 622 31/3S09S	SH	-
ANT3 A 0.3 28 SHPX	BFZ 622 31/3D09S	SH	-
ANT3 A 0.6 28 SHP	BFZ 622 32/3S09S	SH	-
ANT3 A 0.6 28 SHPX	BFZ 622 32/3D09S	SH	-
ANT2 A 0.3 32 SHP	BFZ 622 31/2S10S	SH	-
ANT2 A 0.3 32 SHPX	BFZ 622 31/2D10S	SH	-
ANT2 A 0.6 32 SHP	BFZ 622 32/2S10S	SH	-
ANT2 A 0.6 32 SHPX	BFZ 622 32/2D10S	SH	-
FPA3 A 0.1 32 SHP	UKY 230 50/3S10S	SH	-
ANT3 A 0.3 32 SHP	BFZ 622 31/3S10S	SH	-
ANT3 A 0.3 32 SHPX	BFZ 622 31/3D10S	SH	-
ANT3 A 0.6 32 SHP	BFZ 622 32/3S10S	SH	-
ANT3 A 0.6 32 SHPX	BFZ 622 32/3D10S	SH	-
ANT2 A 0.3 38 SHP	BFZ 622 31/2S11S	SH	-
ANT2 A 0.3 38 SHPX	BFZ 622 31/2D11S	SH	-
ANT2 A 0.6 38 SHP	BFZ 622 32/2S11S	SH	-
ANT2 A 0.6 38 SHPX	BFZ 622 32/2D11S	SH	-
FPA3 A 0.1 38 SHP	UKY 230 50/3S11S	SH	-
ANT3 A 0.3 38 SHP	BFZ 622 31/3S11S	SH	-
ANT3 A 0.3 38 SHPX	BFZ 622 31/3D11S	SH	-
ANT3 A 0.6 38 SHP	BFZ 622 32/3S11S	SH	-
ANT3 A 0.6 38 SHPX	BFZ 622 32/3D11S	SH	-
ANT2 A 0.3 42 SHP	BFZ 622 31/2S12S	SH	-
ANT2 A 0.3 42 SHPX	BFZ 622 31/2D12S	SH	-
ANT2 A 0.6 42 SHP	BFZ 622 32/2S12S	SH	-
ANT2 A 0.6 42 SHPX	BFZ 622 32/2D12S	SH	-
FPA3 A 0.1 42 SHP	UKY 230 50/3S12S	SH	-
ANT3 A 0.3 42 SHP	BFZ 622 31/3S12S	SH	-
ANT3 A 0.3 42 SHPX	BFZ 622 31/3D12S	SH	-
ANT3 A 0.6 42 SHP	BFZ 622 32/3S12S	SH	-
ANT3 A 0.6 42 SHPX	BFZ 622 32/3D12S	SH	-



2.2.3

Dual band antenna, HP/HP and HPX/HP

Orderable product		System	
Product Name	Product Number		
ANT2/2 B 0.6 18/80 HP/HP	BFZ 622 52/AS26H	SH	-
ANT2/2 B 0.6 23/80 HP/HP	BFZ 622 52/AS27H	SH	-



3 Electrical Data

3.1 Frequency Band

4 GHz	3.6-4.2 GHz
5 GHz	4.4-5 GHz
6 GHz	5.925-7.125 GHz (6L: 5.925-6.425 GHz, 6U: 6.425-7.125 GHz)
7/8 GHz	7.1-8.5 GHz
10/11 GHz	10-11.7 GHz (10: 10-10.7 GHz, 11: 10.7-11.7 GHz)
13 GHz	12.75-13.25 GHz
15 GHz	14.4-15.35 GHz
18 GHz	17.7-19.7 GHz
23 GHz	21.2-23.6 GHz
24/26 GHz	24.25-26.5 GHz
28 GHz	27.5-29.5 GHz
32 GHz	31-33.4 GHz
38 GHz	37-40 GHz
42 GHz	40.5-43.5 GHz
60 GHz	57-64 GHz
80 GHz	71-76 + 81-86 GHz



3.2 Gain

3.2.1 ANT A, HP and HPX

Size [m]	4	Frequency [GHz]														80 ⁴
		5	6	7/8	10/11	13	15	18	23	24/26	28	32	38	42	60	
0.1																38.0 38.7 39.5
0.2								32.3 32.8 33.3	33.5 33.8 34.4	34.3 34.8 35.2	35.9 36.1 36.3	37.3 37.5 37.7	37.8 38.2 38.5			42.0 43.5 44.0
0.3					30.8 30.9 31.0	32.5 32.7 32.9	34.0 34.6 35.2	35.0 35.6 36.2	36.3 36.9 37.5	37.6 38.1 38.6	38.7 38.9 39.1	39.7 40.3 40.9	40.4 40.8 41.1			46.0 46.5 47.0
0.6			29.6 31.1 32.2	33.7 34.5 35.2	35.8 36.0 36.2	36.8 37.1 37.5	38.6 39.0 39.4	40.2 40.7 41.2	41.5 42.0 42.5	42.5 42.8 43.2	43.3 43.6 44.0	44.6 45.2 45.8	45.7 46.0 46.3			50.0 50.5 51.0
0.9		32.3 33.3 34.3	34.8 35.5 35.8	37.2 38.4 39.0	39.9 40.0 40.1	40.8 41.1 41.4	42.4 43.2 43.4	44.5 44.8 45.0	45.6 45.8 46.2	46.6 47.0 47.2	47.5 48.0 48.2	49.0 49.4 49.6				
1.2		34.0 35.0 36.0	36.8 37.3 37.7	40.2 40.7 41.0	41.9 42.0 42.1	42.8 43.0 43.1	44.2 44.7 45.1	46.0 46.7 47.0	47.0 47.4 47.8							
1.8	33.8 34.8 35.3	35.7 36.3 36.8	38.5 39.3 40.1	40.1 40.8 41.5	43.2 44.0 44.8	45.1 45.3 45.5	46.4 46.7 47.0	47.5 48.0 48.5	48.7 49.2 49.7							
2.4	36.1 37.3 38.0	38.0 38.8 39.3	40.8 41.6 42.4	42.5 42.9 43.3	45.4 46.0 46.6	47.4 47.6 47.7	48.5 48.8 49.1									
3.0	38.3 38.9 39.4	40.0 40.6 41.1	42.7 43.5 44.2	44.2 45.0 45.8	47.5 47.9 48.6	49.2 49.4 49.5										
3.7	40.3 40.9 41.4	41.7 42.2 42.8	44.5 45.4 46.2	46.0 46.9 47.6												

Nominal gain (in dB_i) at low-, mid- and high-band, including losses in the antenna interface module. Tolerance: ±1 dB. HPX/SHPX antennas can have a lower gain compared to HP/SHP antennas, see footnote.

⁴ The 80 GHz HPX antenna has got 0.8 dB lower gain than HP antenna.



3.2.2 ANT B, HP and HPX

Size [m]	Frequency [GHz]														
	4	5	6 6L/6U	7/8	10/11	13	15	18	23	24/26 ⁵	28 ⁶	32 ⁷	38 ⁸	42 ⁹	80 ¹⁰
0.3						30.8	32.1	34.0	35.5	36.7	38.2	39.2	40.2	40.8	43.1
						30.9	32.3	34.7	36.0	37.3	38.4	39.5	40.5	41.2	44.6
						31.1	32.4	34.9	36.2	37.5	38.8	39.7	40.9	41.5	45.7
0.6				30.5	33.8	35.8	36.8	38.7	40.8	41.7	42.8	43.8	44.8	45.5	50.0
				31.7	34.5	36.0	37.2	39.2	41.1	42.3	43.0	44.2	45.4	45.8	50.9
				32.3	35.2	36.2	37.5	39.7	41.5	42.5	43.2	44.4	45.8	46.1	51.9
0.9			32.0	34.7	37.6	39.9	40.6	42.8	44.1	45.6	46.6	47.0	48.9		
			33.2	35.6	38.3	40.0	41.0	43.3	44.8	46.1	47.0	47.4	49.2		
			33.9	35.8	39.0	40.1	41.3	43.8	45.0	46.5	47.2	47.8	49.7		
1.2			35.2	36.2	39.4	41.7	42.7	44.2	45.5	46.8					
			35.7	36.9	39.9	41.9	42.9	44.7	46.1	47.2					
			36.6	37.6	40.3	42.1	43.1	45.2	46.6	47.6					
1.8			37.8	40.1	42.7	45.1	45.9	47.2	49.0						
			39.3	40.6	43.4	45.4	46.2	47.8	49.5						
			39.4	41.1	43.9	45.7	46.5	48.4	50.0						
2.4	36.5	38.2	40.9/41.8	42.4	45.4/45.9	47.4	48.3								
	37.2	38.8	41.3/42.2	43.1	45.8/46.2	47.5	48.5								
	37.8	39.6	41.7/42.7	43.9	45.9/46.7	47.7	48.8								
3.0	38.4	40.1	42.9/43.5	44.4	47.3/47.8	49.2									
	39.1	40.7	43.2/43.9	45.1	47.7/48.2	49.3									
	39.7	41.2	43.5/44.4	45.9	47.8/48.4	49.5									
3.7	40.0	41.7	44.6/45.1	46.0											
	40.7	42.3	44.8/45.6	46.7											
	41.3	42.8	45.2/46.0	47.5											

Nominal gain (in dBi) at low-, mid- and high-band, including losses in the antenna interface module. Tolerance: ± 1 dB. HPX/SHPX antennas can have a lower gain compared to HP/SHP antennas, see footnote.

⁵ The 24/26 GHz HPX/SHPX antenna has got 0.8 dB lower gain than HP/SHP antenna.

⁶ The 28 GHz HPX/SHPX antenna has got 0.8 dB lower gain than HP/SHP antenna.

⁷ The 32 GHz HPX/SHPX antenna has got 1.0 dB lower gain than HP/SHP antenna.

⁸ The 38 GHz HPX/SHPX antenna has got 1.0 dB lower gain than HP/SHP antenna.

⁹ The 42 GHz HPX/SHPX antenna has got 1.0 dB lower gain than HP/SHP antenna.

¹⁰ The 80 GHz HPX antennas has got 2.0 dB lower gain than HP antenna.



3.2.3 ANT C, HP and HPX

Size [m]	Frequency [GHz]														
	4	5	6	7/8	10/11	13	15	18	23	24/26 ¹¹	28 ¹²	32 ¹³	38 ¹⁴	42 ¹⁵	80 ¹⁶
0.3					30.8	31.6	33.6	34.7	36.2	37.6	38.4	39.6	40.4	45.0	
					30.9	32.1	34.2	35.3	36.6	38.1	38.8	40.1	40.8	46.0	
					31.0	32.6	34.5	35.9	37.1	38.3	39.1	40.5	41.1	47.0	
0.6				29.6	33.8	35.8	36.5	38.4	40.0	41.1	42.3	43.0	44.6	45.0	50.0
				31.1	34.5	36.0	36.8	38.9	40.5	41.6	42.6	43.4	45.2	45.3	50.5
				32.2	35.2	36.2	37.2	39.1	41.0	42.1	43.0	43.8	45.8	45.6	51.0
0.9			31.6	34.0	36.9	39.0	40.1	41.8	43.4	44.6	45.6	46.6	48.2		
			32.5	34.8	37.6	39.2	40.3	42.3	43.9	45.0	45.9	46.9	48.5		
			33.2	35.5	38.2	39.3	40.6	42.8	44.3	45.3	46.2	47.2	48.8		
1.2			35.0	36.8	40.0	41.9	42.7	44.2	46.0	47.0					
			35.6	37.3	40.5	42.0	42.9	44.7	46.7	47.4					
			36.2	37.7	41.0	42.1	43.1	45.1	47.0	47.8					
1.8			38.5	40.1	42.7	44.8	45.9	47.0	48.9						
			39.4	40.8	43.5	45.2	46.2	47.8	49.4						
			39.8	41.1	44.4	45.5	46.5	48.4	49.9						

Nominal gain (in dBi) at low-, mid- and high-band, including losses in the antenna interface module. Tolerance: ± 1 dB. HPX/SHPX antennas can have a lower gain compared to HP/SHP antennas, see footnote.

¹¹ The 24/26 GHz HPX/SHPX antenna has got 0.8 dB lower gain than HP/SHP antenna.

¹² The 28 GHz HPX/SHPX antenna has got 0.8 dB lower gain than HP/SHP antenna.

¹³ The 32 GHz HPX/SHPX antenna has got 1.0 dB lower gain than HP/SHP antenna.

¹⁴ The 38 GHz HPX/SHPX antenna has got 1.0 dB lower gain than HP/SHP antenna.

¹⁵ The 42 GHz HPX/SHPX antenna has got 1.0 dB lower gain than HP/SHP antenna.

¹⁶ The 80 GHz HPX antenna has got 1.5 dB lower gain than HP antenna.



3.2.4

ANT, HP and HPX

Size [m]	4	5	6	7/8	10/11	13	15	Frequency [GHz]						42	60	80
								18	23	24/26	28	32	38			
0.1														31.5		
														32.5		
														32.7		

Nominal gain (in dBi) at low-, mid- and high-band. Tolerance: ± 1 dB.

3.2.5

ANT A, SHP and SHPX

Size [m]	Frequency [GHz]															80
	4	5	6	7/8	10/11	13	15	18	23	24/26	28	32	38	42		
0.1											30.5	31.8	33.0	33.4		
											30.8	32.1	33.3	33.8		
											31.1	32.4	33.6	34.1		
0.3										35.2	36.4	37.7	38.5	39.9	40.8	
										35.6	36.8	38.0	38.7	40.1	41.1	
										36.0	37.3	38.3	38.9	40.3	41.4	
0.6						35.8	36.5	38.4	40.0	41.1	42.3	43.2	44.6	45.7		
						36.0	36.8	38.9	40.5	41.6	42.6	43.5	45.2	46.0		
						36.2	37.2	39.1	41.0	42.1	43.0	43.8	45.8	46.3		
0.9		32.3		37.2	39.9	41.3	42.7	44.5	45.6							
		33.6		38.4	40.0	41.7	43.5	44.8	45.8							
		34.5		39.0	40.1	42.1	43.7	45.0	46.2							

Nominal gain (in dBi) at low-, mid- and high-band. Tolerance: ± 1 dB.

3.2.6

Dual band antenna, HP/HP and HPX/HP

Size [m]	Type	Frequency [GHz]												15/80	18/80	23/80	37.8/46.7	38.8/48.3
0.6	HP/HP													38.2/48.5	39.6/49.3			
														38.7/49.0	39.9/49.8			

Nominal gain (in dBi) at low-, mid- and high-band. Tolerance: ± 1 dB.



3.3 Half Power Beamwidth (HPBW)

3.3.1 ANT A, HP and HPX

Size [m]	4	5	6	7/8	10/11	13	15	18	23	Frequency [GHz]		24/26	28	32	38	42	60	80
										24/26	28							
0.1																		1.8
0.2										4.0	3.5	3.3	2.7	2.3	2.0			1.1
0.3							4.7	4.1	3.2	3.0	2.5	2.2	1.8	1.6	1.5			0.8
0.6				4.7	3.3	2.7	2.5	2.1	1.7	1.5	1.3	1.1	0.9	0.8				0.5
0.9			3.7	3.0	2.0	1.7	1.5	1.1	1.0	0.9	0.8	0.7	0.6					
1.2			2.9	2.2	1.6	1.3	1.2	0.9	0.8	0.6								
1.8	3.1	2.6	1.8	1.3	1.0	0.9	0.8	0.7	0.5									
2.4	2.4	2.0	1.3	1.1	0.8	0.7	0.6											
3.0	1.9	1.5	1.1	1.0	0.7	0.6												
3.7	1.6	1.2	0.9	0.8														

Nominal HPBW (in degrees) in the azimuthal plane at mid-band.

3.3.2 ANT B, HP and HPX

Size [m]	4	5	6 6L/6U	7/8	10/11	13	15	18	23	Frequency [GHz]		24/26	28	32	38	42	60	80
										24/26	28							
0.3							4.5	4.1	3.2	2.7	2.3	2.2	1.9	1.5	1.3		0.8	
0.6				4.3	3.2	2.7	2.3	1.8	1.5	1.4	1.2	1.0	0.8	0.7			0.5	
0.9			3.0	2.6	2.0	1.6	1.5	1.1	1.0	0.8	0.8	0.7	0.6					
1.2			2.6	2.3	1.5	1.3	1.1	1.0	0.8	0.7								
1.8			1.7	1.5	1.0	0.9	0.8	0.7	0.5									
2.4	2.4	1.8	1.5/1.3	1.1	0.8/0.8	0.7	0.6											
3.0	1.8	1.5	1.2/1.0	0.9	0.7/0.7	0.6												
3.7	1.5	1.2	0.9/0.8	0.7														

Nominal HPBW (in degrees) in the azimuthal plane at mid-band.

3.3.3 ANT C, HP and HPX

Size [m]	4	5	6	7/8	10/11	13	15	18	23	Frequency [GHz]		24/26	28	32	38	42	60	80
										24/26	28							
0.3							4.7	4.1	3.3	2.7	2.3	2.2	1.8	1.6	1.5		0.7	
0.6				4.3	3.3	2.7	2.3	1.8	1.5	1.3	1.2	1.0	0.9	0.8			0.4	
0.9			3.4	3.0	2.1	1.8	1.6	1.2	1.0	0.9	0.8	0.7	0.6					
1.2			2.5	2.2	1.5	1.3	1.2	0.9	0.8	0.6								
1.8			1.7	1.5	1.1	0.9	0.8	0.7	0.5									

Nominal HPBW (in degrees) in the azimuthal plane at mid-band.



3.3.4

ANT, HP and HPX

Size [m]	Frequency [GHz]															
	4	5	6	7/8	10/11	13	15	18	23	24/26	28	32	38	42	60	80
0.1															3.9	

Nominal HPBW (in degrees) in the azimuthal plane at mid-band.

3.3.5

ANT A, SHP and SHPX

Size [m]	Frequency [GHz]																		
	4	5	6	7/8	10/11	13	15	18	23	24/26	28	32	38	42	80				
0.1															4.7	4.1	3.4	3.5	
0.3											2.9	2.4	2.2	1.9	1.7	1.5			
0.6							2.7	2.2	2.1	1.7	1.5	1.2	1.0	0.9	0.8				
0.9			3.3		2.0	1.6	1.5	1.1	1.0	0.8									

Nominal HPBW (in degrees) in the azimuthal plane at mid-band.

3.3.6

Dual band antenna

Size [m]	Frequency [GHz]					
	15/80	18/80	23/80			
0.6				1.9/0.5	1.5/0.5	

Nominal HPBW (in degrees) in the azimuthal plane at mid-band.



3.4 Cross-Polar Discrimination (XPD)

3.4.1 ANT, HP and HPX

Angular region	Type [GHz]				
	ANT A 4-13 ANT B 4-13 ANT C 6-13 FPA3 A 28-42	ANT A 15-42 ANT B 15-42 ANT C 15-42	ANT 0.1 60 ANT A 0.2 80 ANT A 0.6 80	ANT B 0.3 80 HP ANT B 0.6 80 HP ANT C 80	ANT B 0.3 80 HPX ANT B 0.6 80 HPX
In azimuth over an angle twice the half power beamwidth of the co-polarized main beam	30		30		27
Within the 1 dB co-polarized contour	30		27		25

Minimum XPD (in dB).

3.4.2 Dual band antenna, HP/HP and HPX/HP

Angular region	Type [GHz]			
	ANT2/2 B 0.6 HP/HP 18/23 GHz	ANT2/2 B 0.6 HP/HP 80 GHz		
In azimuth over an angle twice the half power beamwidth of the co-polarized main beam	30	27		
Within the 1 dB co-polarized contour	30	27		

Minimum XPD (in dB).

3.5 Return Loss and VSWR

Size / Type [m]	Integrated installation ANT2, ANT2/2, ANT3	Integrated installation ANT2, ANT2/2, ANT3	Separate installation ANT0, ANT2, ANT2/2, ANT3	
	Frequency [GHz] 6-8	Frequency [GHz] 10-80	Frequency [GHz] 4-8	Frequency [GHz] 10-42
0.1-0.9	14 / 1.50	14 / 1.50	14 / 1.50	14 / 1.50
1.2-1.8	18 / 1.29	14 / 1.50	18 / 1.29	14 / 1.50
2.4-3.7			18 / 1.29	14 / 1.50

Minimum return loss (in dB) / maximum VSWR.



3.6 Front to Back Ratio (F/B)

3.6.1 ANT A, HP and HPX

Size [m]	4	Frequency [GHz]														
		5	6	7/8	10/11	13	15	18	23	24/26	28	32	38	42	60	80
0.1																56
0.2									58	61	61	60	62	64		62
0.3						58	60	63	62	63	64	61	61	60		64
0.6			57	61	61	65	67	66	68	69	63	66	67			68
0.9		60	61	64	66	69	71	71	72	74	72	76				
1.2		61	63	66	68	71	73	74	75							
1.8	61	63	66	67	70	74	76	78	80							
2.4	70	66	70	71	72	72	80									
3.0	68	71	70	72	75	76										
3.7	71	74	72	75												

Minimum F/B (in dB).

3.6.2 ANT B, HP and HPX

Size [m]	4	5	Frequency [GHz]													
			6 6L/6U	7/8	10/11	13	15	18	23	24/26	28	32	38	42	60	80
0.3						57	60	62	61	63	64	63	65	64		63
0.6				58	61	62	65	68	66	68	70	70	70	65		68
0.9			60	62	64	66	69	71	71	73	74	70	74			
1.2			62	63	66	68	72	72	74	73						
1.8			65	67	70	72	74	76	75							
2.4	66	66	71/71	71	76/75	75	76									
3.0	67	68	74/74	73	78/77	76										
3.7	70	69	76/76	75												

Minimum F/B (in dB).

3.6.3 ANT C, HP and HPX

Size [m]	4	5	6	Frequency [GHz]												
				7/8	10/11	13	15	18	23	24/26	28	32	38	42	60	80
0.3						57	60	60	62	63	63	58	61	60		62
0.6				57	61	62	65	67	65	68	68	61	64	65		67
0.9			59	60	63	64	67	70	67	70	71	64	67			
1.2			62	63	67	68	71	73	74	75						
1.8			65	67	70	72	74	76	79							

Minimum F/B (in dB).



3.6.4

ANT, HP and HPX

Size [m]	4	5	6	7/8	10/11	13	15	18	23	Frequency [GHz]						
										24/26	28	32	38	42	60	80
0.1															51	

Minimum F/B (in dB).

3.6.5

ANT A, SHP and SHPX

Size [m]	4	5	6	7/8	10/11	13	15	18	23	Frequency [GHz]					
										24/26	28	32	38	42	80
0.1											57	51	51	51	
0.3									66	69	70	67	68	70	
0.6						67	68	70	71	74	76	71	72	71	
0.9			65		69	71	73	74	75	77					

Minimum F/B (in dB).

3.6.6

Dual band antenna, HP/HP and HPX/HP

Size [m]					Frequency [GHz]			
					15/80	18/80	23/80	
0.6						66/68	64/68	

Minimum F/B (in dB).

3.7

Inter Port Isolation (IPI)

Minimum 35 dB IPI (dual polarized antennas only).

3.8

Radiation Pattern Envelope (RPE)

3.8.1

General

The radiation pattern envelopes (RPEs) are typical and should be used for network planning. Guaranteed RPEs will not have any peaks exceeding the typical RPEs by more than 3 dB. In all cases peaks will not exceed the international standards listed in section 3.9.

The radiation pattern envelopes (RPEs) corresponding to the antenna versions in this document are specified in:

Microwave Antennas, Radiation Pattern Envelope: 2/1301-UKY 210 40+ Rev B



3.9 Compliance with International Standards

3.9.1 Europe, ETSI EN 302 217-4 V2.1.1 (2017-05)

3.9.1.1 General

<u>Ericsson</u>		<u>ETSI</u>
4-13 GHz	covered by	Range 1
15-18 GHz	covered by	Range 2
23 GHz	covered by	Range 3
24-28 GHz	covered by	Range 4
32-42 GHz	covered by	Range 5
60 GHz	covered by	Range 6
80 GHz	covered by	Range 7

3.9.1.2 ANT A, ANT B, ANT C and Dual band antenna, HP/HPX

Size [m]	Frequency [GHz]																		
	4	5	6	7/8	10/11	13	15	18	23	24/26	28	32	38	42	60	80	15/80	18/80	23/80
0.1															2	3			
0.2									3	3	3	3B	3B	3B			3		
0.3						3	3	3	3	3	3	3B	3B	3B		3			
0.6				3	3	3	3	3	3	3	3	3B	3B	3B		3	3/3	3/3	3/3
0.9		3	3	3	3	3	3	3	3	3	3	3B	3B						
1.2		3	3	3	3	3	3	3	3	3									
1.8	3	3	3	3	3	3	3	3	3										
2.4	3	3	3	3	3	3	3	3											
3.0	3	3	3	3	3	3													
3.7	3	3	3	3															

Compliance with RPE classes.

Antennas are compliant with XPD category 1 and 2 (defined for 4-42 GHz)

3.9.1.3 ANT A, SHP/SHPX

Size [m]	Frequency [GHz]																	
	4	5	6	7/8	10/11	13	15	18	23	24/26	28	32	38	42	80			
0.1															3 ⁴	3 ⁴	3 ⁴	3 ⁴
0.3													4	4	4	4	4	4
0.6							3 ¹⁷	4	4	4	4	4	4	4	4	4	4	4
0.9			3 ⁴		3 ⁴	4	4	4	4	4	4							

Compliance with RPE classes.

Antennas are compliant with XPD category 1 and 2 (defined for 4-42 GHz)

¹⁷ Significantly better than class 3.



3.9.2 USA, FCC 47 CFR Ch. I (10-1-17 Edition) § 101.115 and § 30.406

3.9.2.1 General

Ericsson	FCC
4 GHz	covers
6 GHz	covers
10/11 GHz	covers
18 GHz	covers
23 GHz	covers
24/26 GHz	covers
38 GHz	covers
80 GHz	covers
	3.7-4.2 GHz
	5.925-6.425 + 6.525-6.875 + 6.875-7.125 GHz
	10.55-10.68 + 10.7-11.7 GHz
	17.7-18.82 + 18.92-19.7 GHz
	21.2-23.6 GHz
	24.25-25.25 GHz
	38.6-40 GHz
	71-76 + 81-86 GHz

3.9.2.2 ANT A, HP/HPX

Size [m]	Frequency [GHz]															
	4	5	6	7/8	10/11 ¹⁸	13	15	18	23	24/26	28	32	38	42	60	80 ¹⁹
0.1																—
0.2										B2	—			—		—
0.3									B2	A	B			A		OK
0.6					A/B			A	A	A			A			OK
0.9		B2			A/A			A	A	A			A			
1.2		B2			A/A			A	A	A						
1.8	—	A			A/A			A	A							
2.4	B	A			A/A											
3.0	B	A			A/A											
3.7	A	A														

Compliance with antenna performance categories.

3.9.2.3 ANT B, ANT C and Dual band antenna, HP/HPX

Size [m]	Frequency [GHz]																
	4	5	6	7/8	10/11 ²⁰	13	15	18	23	24/26	28	32	38	42	60	80 ²¹	15&18&23/80 ²²
0.3								B2	A	B			A			OK	
0.6					A/B			A	A	A			A			OK	A/OK
0.9		B2			A/A			A	A	A			A				
1.2		B2			A/A			A	A	A							
1.8	—	A			A/A			A	A								
2.4	A	A			A/A												
3.0	A	A			A/A												
3.7	A	A															

Compliance with antenna performance categories

¹⁸ Category in FCC 10.55-10.68 GHz band / Category in FCC 10.7-11.7 GHz band.

¹⁹ Only one category, without any name, is defined in FCC 71-76 + 81-86 GHz band.

²⁰ Category in FCC 10.55-10.68 GHz band / Category in FCC 10.7-11.7 GHz band.

²¹ Only one category, without any name, is defined in FCC 71-76 + 81-86 GHz band.

²² Only one category, without any name, is defined in FCC 71-76 + 81-86 GHz band.



3.9.2.4

ANT A, SHP/SHPX

Size [m]	Frequency [GHz]														
	4	5	6	7/8	10/11 ⁵	13	15	18	23	24/26	28	32	38	42	80 ⁶
0.1														A	
0.3									A	–			A		
0.6								A	A	A			A		
0.9		B2		A/A			A	A	A						

Compliance with antenna performance categories.

3.9.3

Brazil, Anatel, Resolution No 609 (April 18, 2013)

3.9.3.1

General

Ericsson	Anatel
4-13 GHz	covered by 3-14 GHz
15-18 GHz	covered by 14-20 GHz
23 GHz	covered by 20-24 GHz
24-28 GHz	covered by 24-30 GHz
32-42 GHz	covered by 30-47 GHz
80 GHz	covered by 71-86 GHz

3.9.3.2

ANT A, ANT B, ANT C and Dual band antenna, HP/HPX

Size [m]	Frequency [GHz]																
	4	5	6	7/8	10/11	13	15	18	23	24/26	28	32	38	42	60	80	15&18&23/80
0.1																3	
0.2									3	3	3	2	2	2		3	
0.3					3	3	3	3	3	3	3	2	2	2		3	
0.6		3	3	3	3	3	3	3	3	3	3	2	2	2		3	3/3
0.9	3	3	3	3	3	3	3	3	3	3	3	2	2				
1.2		3	3	3	3	3	3	3	3	3							
1.8	3	3	3	3	3	3	3	3	3								
2.4	3	3	3	3	3	3	3	3									
3.0	3	3	3	3	3	3											
3.7	3	3	3	3													

Compliance with RPE classes.

All antennas are compliant with XPD class 2 (and 1).

3.9.3.3

ANT A, SHP/SHPX

Size [m]	Frequency [GHz]														
	4	5	6	7/8	10/11	13	15	18	23	24/26	28	32	38	42	80
0.1												3	3	3	3
0.3										3	3	3	3	3	3
0.6						3	3	3	3	3	3	3	3	3	3
0.9			3		3	3	3	3	3	3	3				



Compliance with RPE classes.

All antennas are compliant with XPD class 2 (and 1).

3.9.4 Australia, ACMA RALI FX 3 Appendix 11 (June 2016)

3.9.4.1 General

Ericsson		ACMA
4 GHz	covers	3.8 GHz
6 GHz	covers	6 + 6.7 GHz
7/8 GHz	covers	7.5 + 8 GHz
10/11 GHz	covers	10 + 11 GHz
13 GHz	covers	13 GHz
15 GHz	covers	15 GHz
18 GHz	covers	18 GHz
23 GHz	covers	22 GHz
38 GHz	covers	38 GHz

3.9.4.2 ANT A, HP/HPX

Size [m]	Frequency [GHz]															
	4	5	6 ²³	7/8 ²⁴	10/11 ²⁵	13	15	18	23	24/26	28	32	38	42	60	80
0.1																A
0.2									B					B		A
0.3						B	B	B	B				B		A	
0.6				B/-	B/B	B	A	A	A				A		A	
0.9			B/-	B/B	B/B	B	A	A	A				A			
1.2			B/-	B/B	A/B	B	A	A	A							
1.8	A		B/B	B/B	A/B	A	A	A	A							
2.4	A		B/B	A/B	A/B	A	A									
3.0	A		B/B	A/B	A/B	A										
3.7	A		B/B	A/A												

Compliance with antenna grades.

²³ Grade in ACMA 6 GHz band / Grade in ACMA 6.7 GHz band.

²⁴ Grade in ACMA 7.5 GHz band / Grade in ACMA 8 GHz band.

²⁵ Grade in ACMA 10 GHz band / Grade in ACMA 11 GHz band.



3.9.4.3 ANT B and Dual band antenna, HP/HPX

Size [m]	4	5	6 ²⁶	Frequency [GHz]													
				7/8 ²⁷	10/11 ²⁸	13	15	18	23	24/26	28	32	38	42	60	80	
0.3						B	C	B	B					B		A	
0.6				B/-	B/B	B	A	A	A				A			A	A/A
0.9			B/-	B/B	B/B	B	A	A	A				A				
1.2			B/-	B/B	A/B	B	A	A	A								
1.8	B		B/B	B/B	A/B	A	A	A	A								
2.4	A	-	B/B	A/B	A	A	A										
3.0	A	-	B/B	A/B	A	A											
3.7	A	-	A/A	A/A													

Compliance with antenna grades.

3.9.4.4 ANT C, HP/HPX

Size [m]	4	5	6 ²⁹	Frequency [GHz]												
				7/8 ³⁰	10/11 ³¹	13	15	18	23	24/26	28	32	38	42	60	80
0.3						B	B	B	B				B		A	
0.6				B/-	B/B	B	A	A	A				B		A	
0.9			B/-	B/B	B/B	B	A	A	A				A			
1.2			B/-	B/B	B/B	B	A	A	A							
1.8	B		B/B	B/B	B/B	A	A	A	A							

Compliance with antenna grades.

3.9.4.5 ANT A, SHP/SHPX

Size [m]	4	5	6 ⁶	Frequency [GHz]												
				7/8 ⁷	10/11 ⁸	13	15	18	23	24/26	28	32	38	42	80	
0.1														A		
0.3													A			
0.6							B	A	A					A		
0.9			B/B		A/B	A	A	A	A							

Compliance with antenna grades.

²⁶ Grade in ACMA 6 GHz band / Grade in ACMA 6.7 GHz band.

²⁷ Grade in ACMA 7.5 GHz band / Grade in ACMA 8 GHz band.

²⁸ Grade in ACMA 10 GHz band / Grade in ACMA 11 GHz band.

²⁹ Grade in ACMA 6 GHz band / Grade in ACMA 6.7 GHz band.

³⁰ Grade in ACMA 7.5 GHz band / Grade in ACMA 8 GHz band.

³¹ Grade in ACMA 10 GHz band / Grade in ACMA 11 GHz band.



3.9.5 Canada, ISED

3.9.5.1 General

<u>Ericsson</u>		<u>ISED</u>
4 GHz	covers	3.7-4.2 GHz SRSP-303.7, Issue 3, December 2006
6 GHz	covers	5.925-6.425 GHz SRSP-305.9, Issue 5, December 2006
		6.425-6.930 GHz SRSP-306.4, Issue 6, December 2006
7/8 GHz	covers	7.125-7.725 GHz SRSP-307.1, Issue 5, May 2006
		7.725-8.275 GHz SRSP-307.7, Issue 6, December 2006
10/11 GHz	covers	10.55-10.68 GHz SRSP-310.5, Issue 3, May 2012
		10.7-11.7 GHz SRSP-310.7, Issue 3, June 2012
15 GHz	covers	14.5-15.35 GHz SRSP-314.5, Issue 3, December 2010
18 GHz	covers	17.8-18.3 + 19.3-19.7 GHz SRSP-317.8, Issue 2, December 2006
23 GHz	covers	21.8-22.4 + 23.0-23.6 GHz SRSP-321.8, Issue 1, July 19, 1997
24/26 GHz	covers	24.25-24.45 + 25.05-25.25 GHz SRSP-324.25, Issue 1, January 1, 2000
		25.25-26.5 GHz SRSP-325.25, Issue 1, September 2013
28 GHz	covers	27.5-28.35 GHz SRSP-325.25, Issue 1, September 2013
38 GHz	covers	38.6-40.0 GHz SRSP-338.6, Issue 3, April 2008
80 GHz	covers	71-76 + 81-86 GHz SRSP-371.0, Issue 1, May 2017



3.9.5.2 ANT A, HP/HPX

Size [m]	Frequency [GHz]															
	4	5	6	7/8 ^{32 33}	10/11 ^{13 34}	13	15	18	23	24/26 ^{13 35 36}	28 ¹³	32	38 ¹³	42	60	80
0.2										—	OK/—	—		—		A
0.3						B	—	—	B	OK/OK	OK		OK		A	
0.6				—/—	—/—	B	C	A	A	OK/OK	OK		OK		A	
0.9			—	—/—	OK/—	B	C	A	A	OK/OK	OK		OK			
1.2			—	—/—	OK/B	B	C	A	A	OK/OK						
1.8	—	A	OK/B	OK/A	OK/A		C									
2.4	B	A	OK/A	OK/A												
3.0	B	A	OK/A	OK/A												
3.7	A	A	OK/A													

Compliance with antenna RPE.

3.9.5.3 ANT B and Dual band antenna, HP/HPX

Size [m]	Frequency [GHz]															
	4	5	6	7/8 ^{37 38}	10/11 ^{18 39}	13	15	18	23	24/26 ^{18 40 41}	28 ¹⁸	32	38 ¹⁸	42	60	80
0.3						—	—	B	OK/OK	OK		OK		—	A	
0.6				—/—	—/—	B	C	A	A	OK/OK	OK		OK		A	A/
0.9		—	—/—	OK/—	B	C	A	A	OK/OK	OK		OK				
1.2		—	—/—	OK/B	B	C	A	A	OK/OK							
1.8	—	A	OK/B	OK/A	B	C	A	A								
2.4	A	—	A	A	A	A	C									
3.0	A	—	A	A	A	A										
3.7	A	—	A	A												

Compliance with antenna RPE.

³² Only one RPE, without any name, is defined in SRSP-307.1, SRSP-310.5, SRSP-325.25 and SRSP-338.6.

³³ RPE in SRSP-307.1 / RPE in SRSP-307.7.

³⁴ RPE in SRSP-310.5 / RPE in SRSP-310.7.

³⁵ No traditional antenna requirements are defined in SRSP-324.25.

³⁶ RPE in SRSP-324.25 / RPE in SRSP-325.25.

³⁷ Only one RPE, without any name, is defined in SRSP-307.1, SRSP-310.5, SRSP-325.25 and SRSP-338.6.

³⁸ RPE in SRSP-307.1 / RPE in SRSP-307.7.

³⁹ RPE in SRSP-310.5 / RPE in SRSP-310.7.

⁴⁰ No traditional antenna requirements are defined in SRSP-324.25.

⁴¹ RPE in SRSP-324.25 / RPE in SRSP-325.25.



3.9.5.4 ANT C, HP/HPX

Size [m]	Frequency [GHz]															
	4	5	6	7/8 ^{42 43}	10/11 ^{13 44}	13	15	18	23	24/26 ^{13 45 46}	28 ¹³	32	38 ¹³	42	60	80
0.3						B	B	B	B	OK/OK	OK		OK	OK		A
0.6						B	C	A	A	OK/OK	OK		OK	OK		A
0.9		OK/B			OK/B	B	C	A	A	OK/OK	OK		OK			
1.2		OK/B	OK/OK	OK/B	B	C	A	A	OK/OK							
1.8		A	OK/B	OK/A	B	C	A	A								

Compliance with antenna RPE.

3.9.5.5 ANT A, SHP/SHPX

Size [m]	Frequency [GHz]															
	4	5	6	7/8 ^{13 14}	10/11 ^{13 15}	13	15	18	23	24/26 ^{13 16 17}	28 ¹³	32	38 ¹³	42	80	
0.1												OK		OK		
0.3									B	OK/OK	OK		OK			
0.6							C	A	B ⁴⁷	OK/OK	OK		OK			
0.9			—		OK/-		C	A	A	OK/OK						

⁴² Only one RPE, without any name, is defined in SRSP-307.1, SRSP-310.5, SRSP-325.25 and SRSP-338.6.

⁴³ RPE in SRSP-307.1 / RPE in SRSP-307.7.

⁴⁴ RPE in SRSP-310.5 / RPE in SRSP-310.7.

⁴⁵ No traditional antenna requirements are defined in SRSP-324.25.

⁴⁶ RPE in SRSP-324.25 / RPE in SRSP-325.25.

⁴⁷ Violates the "A" RPE at 2-5 degrees. Significantly better than "A" for all other angles.




4 Mechanical Data


4.1 Dimensions

4.1.1 ANT A, HP and HPX


4.1.1.1 ANT2 A 0.1 80 HP



Antenna.




Antenna, side, rear and front view.




Antenna, top view.

4.1.1.2


ANT2 A 0.2 HP



Antenna.




Antenna, side, front and rear view.




Antenna, top view.


4.1.1.3

ANT2 A 0.3 HP

Antenna 13-42 GHz and 80 GHz.




Antenna 13-42 GHz and 80 GHz, side and front view.




Antenna 13-42 GHz and 80 GHz, top view.

4.1.1.4


ANT2 A 0.3 HPX



Antenna 13-42 GHz and 80 GHz.




Antenna 13-42 GHz and 80 GHz, side and front view.




Antenna 13-42 GHz and 80 GHz, top view.




4.1.1.5

ANT3 A 0.3 HP

Antenna 13–42 GHz and 80 GHz.




Antenna 13-42 GHz and 80 GHz, side and front view.




Antenna 13-42 GHz and 80 GHz, top view.

4.1.1.6

ANT3 A 0.3 HPX




Antenna 13-42 GHz and 80 GHz.




[mm]

Antenna 13-42 GHz and 80 GHz, side and front view.




Antenna 13-42 GHz and 80 GHz, top view.

4.1.1.7


ANT2 A 0.6 HP

Antenna 7-42 GHz and 80 GHz.



[mm]

Antenna 7-42 GHz and 80 GHz, side and front view.




[mm]


Antenna 7-42 GHz and 80 GHz, top view.




4.1.1.8

ANT2 A 0.6 HPX

Antenna 7-42 GHz and 80 GHz.




Antenna 7-42 GHz and 80 GHz, side and front view.




Antenna 7-42 GHz and 80 GHz, top view.


4.1.1.9

ANT3 A 0.6 HP

Antenna 7-42 GHz and 80 GHz.




Antenna 7-42 GHz and 80 GHz, side and front view.




Antenna 7-42 GHz and 80 GHz, top view.

4.1.1.10


ANT3 A 0.6 HPX



Antenna 7-42 GHz and 80 GHz.




Antenna 7-42 GHz and 80 GHz, side and front view.




Antenna 7-42 GHz and 80 GHz, top view.

4.1.1.11


ANT2 A 0.9 HP



Antenna.




Antenna, side and front view.




Antenna, top and rear view.

4.1.1.12


ANT2 A 0.9 HPX



Antenna.




Antenna, side and front view.




Antenna, top and rear view.


4.1.1.13

ANT3 A 0.9 HP

Antenna




Antenna, side and front view.




Antenna, top and rear view.


4.1.1.14

ANT3 A 0.9 HPX

Antenna.




Antenna, side and front view.




Antenna, top and rear view.




4.1.1.15

ANT0 A 1.2 HPX

Antenna.




Antenna, side and front view.




Antenna, top view.




4.1.1.16

ANT2 A 1.2 HP

Antenna.




Antenna, side and front view.





Antenna, rear and top view.

4.1.1.17



ANT2 A 1.2 HPX

Antenna.



[mm]

Antenna, side and front view.




[mm]


Antenna, rear and top view.

4.1.1.18

ANT3 A 1.2 HP





Antenna.



[mm]

Antenna, side and front view.




[mm]


Antenna, rear and top view.

4.1.1.19



ANT3 A 1.2 HPX



Antenna.




Antenna, side and front view.




Antenna, rear and top view.



4.1.1.20

ANT0 A 1.8 HPX (4-5 GHz)

Antenna.




Antenna, side and front view.




Antenna, top view.



4.1.1.21

ANT0 A 1.8 HPX (6-13 GHz)

Antenna.




Antenna, side view.




Antenna, rear and top view.




4.1.1.22

ANT2 A 1.8 HP

Antenna.




Antenna, side view.




Antenna, rear and top view.



4.1.1.23

ANT2 A 1.8 HPX

Antenna.




Antenna, side view.




Antenna, rear and top view.

4.1.1.24


ANT3 A 1.8 HP



Antenna.




Antenna, side view.




Antenna, rear and top view.

4.1.1.25


ANT3 A 1.8 HPX



Antenna.




Antenna, side view.



Antenna, rear and top view.




4.1.1.26

ANT0 A 2.4 HP and ANT0 A 2.4 HPX



Antenna.

1710, 1941 (4 & 15 GHz)

1162, 1392 (4 & 15 GHz)



Antenna, side and front view.




Antenna, top view.




4.1.1.27


ANT0 A 3.0 HP and ANT0 A 3.0 HPX



Antenna.




Antenna, side and front view.




Antenna, top view.




4.1.1.28

ANT0 A 3.7 HPX

Antenna.




Antenna, side and front view.




Antenna, top view.

4.1.2 ANT B, HP and HPX


4.1.2.1 ANT2 B 0.3 HP



Antenna 80 GHz.



Antenna 80 Hz, rear and side view.




Antenna, top view.




4.1.2.2

ANT2 B 0.3 HPX




Antenna 80 GHz.



[mm]

Antenna 80 GHz, rear and side view.




[mm]


Antenna, top view.

4.1.2.3

ANT3 B 0.3 HP




Antenna 13-42 GHz and 80 GHz.



[mm]

Antenna 13-42 GHz and 80 Hz, rear and side view.




[mm]


Antenna, top view.

4.1.2.4

ANT3 B 0.3 HPX




Antenna 13-42 GHz and 80 GHz.



[mm]

Antenna 13-42 GHz and 80 GHz, rear and side view.




[mm]


Antenna, top view.

4.1.2.5

ANT2 B 0.6 HP




Antenna 80 GHz.



[mm]

Antenna 80 GHz, rear and side view.




[mm]


Antenna, top view.

4.1.2.6

ANT2 B 0.6 HPX




Antenna 80 GHz.



[mm]

Antenna 80 GHz, rear and side view.




[mm]


Antenna, top view.

4.1.2.7

ANT3 B 0.6 HP




Antenna.



[mm]

Antenna, rear and side view.




[mm]


Antenna, top view.

4.1.2.8

ANT3 B 0.6 HPX




Antenna.



[mm]

Antenna, rear and side view.




[mm]


Antenna, top view.

4.1.2.9

ANT3 B 0.9 HP




Antenna



[mm]

Antenna, rear and side view.




[mm]


Antenna, top view.

4.1.2.10


ANT3 B 0.9 HPX



Antenna




Antenna, rear and side view.





Antenna, top view.



4.1.2.11


ANT0 B 1.2 HPX

Antenna.



[mm]

Antenna, rear and side view.




Antenna, top view.



[mm]



4.1.2.12


ANT3 B 1.2 HP

Antenna.



[mm]

Antenna, rear and side view.




[mm]



Antenna, top view.



4.1.2.13


ANT3 B 1.2 HPX

Antenna.



[mm]

Antenna, rear and side view.




[mm]



Antenna, top view.

4.1.2.14

ANT0 B 1.8 HP (4-5 GHz)




Antenna.



[mm]


Antenna, rear and side view.




Antenna, top view.

4.1.2.15

ANT0 B 1.8 HPX (6-13 GHz)




Antenna.



[mm]

Antenna, rear and side view.




[mm]



Antenna, top view.

4.1.2.16


ANT3 B 1.8 HP



Antenna.




Antenna, rear and side view.




Antenna, top view.



4.1.2.17


ANT3 B 1.8 HPX

Antenna.



[mm]

Antenna, rear and side view.




Antenna, top view.



[mm]



4.1.2.18


ANT0 B 2.4 HPX

Antenna.



[mm]


Antenna, rear and side view.




Antenna, top view.



4.1.2.19


ANT0 B 3.0 HPX

Antenna.



[mm]

Antenna, rear and side view.




[mm]


Antenna, top view.




4.1.2.20

ANT0 B 3.7 HPX

Antenna.




Antenna, rear and side view.




Antenna, top view.

4.1.3 ANT C, HP and HPX

4.1.3.1 ANT2 C 0.3 80 HP




Antenna



[mm]

Antenna, rear and side view.




[mm]

Antenna, top view.




4.1.3.2

ANT2 C 0.3 80 HPX




Antenna



[mm]

Antenna, rear and side view.




[mm]


Antenna, top view.

4.1.3.3

ANT3 C 0.3 HP




Antenna.



[mm]

Antenna, rear and side view.




[mm]

Antenna, top view.




4.1.3.4

ANT3 C 0.3 HPX




Antenna 13-42 GHz and 80 GHz.



[mm]

Antenna, rear and side view.




[mm]


Antenna, top view.

4.1.3.5


ANT2 C 0.6 80 HP



Antenna.



Antenna, rear and side view.




Antenna, top view.


[mm]




4.1.3.6

ANT2 C 0.6 80 HPX

Antenna.




Antenna, rear and side view.





Antenna, top view.

4.1.3.7

ANT3 C 0.6 HP




Antenna.



[mm]

Antenna, rear and side view.




[mm]


Antenna, top view.

4.1.3.8

ANT3 C 0.6 HPX




Antenna.



[mm]

Antenna, rear and side view.




[mm]

Antenna, top view.




4.1.3.9


ANT3 C 0.9 HP



Antenna




Antenna, rear and side view.




Antenna, top view.



4.1.3.10


ANT3 C 0.9 HPX

Antenna.



[mm]

Antenna, rear and side view.




[mm]



Antenna, top view.

4.1.3.11

ANT3 C 1.2 HP




Antenna.



[mm]

Antenna, rear and side view.




[mm]



Antenna, top view.

4.1.3.12

ANT3 C 1.2 HPX




Antenna.



[mm]

Antenna, rear and side view.




[mm]



Antenna, top view.

4.1.3.13

ANT3 C 1.8 HP




Antenna.



[mm]

Antenna, rear and side view.




[mm]


Antenna, top view.

4.1.3.14

ANT3 C 1.8 HPX




Antenna.



[mm]

Antenna, rear and side view.




[mm]

Antenna, top view.




4.1.4 ANT A, SHP and SHPX

4.1.4.1 FPA3 A 0.1 SHP




Antenna.



[mm]

Antenna, side, rear and front view.




[mm]

Antenna, top view.




4.1.4.2


ANT2 A 0.3 SHP



Antenna.




Antenna, side and front view.




Antenna, top and rear view.




4.1.4.3

ANT2 A 0.3 SHPX

Antenna.




Antenna, side and front view.




Antenna, top and rear view.




4.1.4.4

ANT3 A 0.3 SHP

Antenna.



Antenna, top and side view.




Antenna, rear and front view.




4.1.4.5


ANT3 A 0.3 SHPX



Antenna.



Antenna, side and front view.




Antenna, top and rear view.



4.1.4.6

ANT2 A 0.6 SHP




Antenna, side and front view.


Antenna, top and rear view.

4.1.4.7


ANT2 A 0.6 SHPX



Antenna




Antenna, side and front view.




Antenna, top and rear view.

4.1.4.8



ANT3 A 0.6 SHP



Antenna



Antenna, side and rear view.




[mm]


Antenna, top and front view.

4.1.4.9


ANT3 A 0.6 SHPX



Antenna




Antenna, side and front view.




Antenna, top and rear view.

4.1.4.10


ANT2 A 0.9 SHP

Antenna



[mm]


Antenna, side and front view.




Antenna, rear view.



4.1.4.11


ANT2 A 0.9 SHPX

Antenna



[mm]

Antenna, side and front view.




Antenna, rear view.


[mm]

4.1.4.12


ANT3 A 0.9 SHP



Antenna




Antenna, side and front view.






Antenna, rear view.



4.1.4.13

ANT3 A 0.9 SHPX


Antenna






4.1.5 Dual band antenna

4.1.5.1 ANT2/2 B 0.6 HP/HP




Antenna.



[mm]

Antenna, rear and side view.



[mm]

Antenna, top view.



4.2 Weight

4.2.1 ANT A

Size [m]	ANT A									
	ANT0 HP/HPX	ANT2 HP	ANT2 HPX	ANT3 HP	ANT3 HPX	ANT2 SHP	ANT2 SHPX	ANT3/FPA3 SHP	ANT3 SHPX	
0.1		4.5							2.4	
0.2		5.7								
0.3	13-42	6.2	8.3	5.0	8.3	7.3	9.4	6.4	9	
0.3	80	6.8	7.8	5.5	8.6					
0.6		9.6	11	7.6	10	13.4	14.8	11.6	13.9	
0.9		18	20	17	19	32	33	30	33	
1.2	34	33	35	31	34					
1.8 4 GHz	90									
1.8 5 GHz	75									
1.8 6-23 GHz	94	90	93	90	94					
2.4 4&15 GHz	196									
2.4 5-13 GHz	187									
3.0	280									
3.7	343									

Total antenna weight (kg).

4.2.2 ANT B

Size [m]	Freq. [GHz]	ANT B				
		ANT0 HPX	ANT2 HP	ANT2 HPX	ANT3 HP	ANT3 HPX
0.3	13-42				5.0	8.5
0.3	80		6.3	10.0	6.3	10.0
0.6			7.0	10.5	7.0	10.5
0.9					16	20
1.2		37			35	39
1.8	4-5	110				
1.8	6-23	92			90	94
2.4		180				
3.0		290				
3.7		420				

Total antenna weight (kg).



4.2.3

ANT C

Size [m]	Freq. [GHz]	ANT C	
		ANT3 HP	ANT3 HPX
0.3		4.6	6.6
0.6		7.5	9.5
0.9	6-24/26	17.5	19.5
0.9	28-38	18.5	20.5
1.2		44	47
1.8		88	90

Total antenna weight (kg).

4.2.4

Dual band antenna

Size [m]	Dual band antenna	
	ANT2/2 B HP/HP	ANT2/2 B HPX/HP
0.6	16.4	

Total antenna weight (kg).



4.3 RF Interfaces

4.3.1 Integrated Installation

The integrated single polarized antennas have a polarization plate (waveguide matching section) matching the antenna waveguide port with the radio waveguide port.

4.3.2 Separate Installation

All antennas (including the integrated antennas) are equipped with a standardised waveguide interface:

Frequency [GHz]	Flange type [IEC]
4	154 IEC-PDR 40
5	154 IEC-PDR 48
6	154 IEC-UDR 70
7/8	154 IEC-UBR 84
10-13	154 IEC-UBR 120
15	154 IEC-UBR 140
18-23	154 IEC-UBR 220
24-28	154 IEC-UBR 260
32-38	154 IEC-UBR 320
42	Ericsson proprietary flange (waveguide R500)
80	Integrated installation only (waveguide R740)

4.4 Pressurization

Maximum 40 kPa antenna feed over pressure (continuous operation).



4.5 Material and Treatment

4.5.1 ANT A, HP and HPX

Type	Reflector & Shield	Radio Interface	Radome	Absorber	Mount	Feed	Screws & nuts
ANT2 A 0.1 80 HP	Aluminium	Aluminium	UV-resistant polycarbonate (PC) White, NCS S 1002-B	Carbon impregnated polyurethane foam	Aluminium extrusion	Surface treated aluminium	Stainless steel A2
ANT2 A 0.2 23-38 HP	Die-cast aluminium Polyester powder paint Light grey, NCS 2502-R	Die-cast aluminium Polyester powder paint, Light grey, NCS 2502-R	UV-resistant polycarbonate (PC) Light grey	Carbon impregnated polyurethane foam	Aluminium extrusion	Surface treated aluminium	Stainless steel A2
ANT2 A 0.2 42 HP	Die-cast aluminium Polyester powder paint Light grey, NCS 2502-R	Die-cast aluminium Polyester powder paint, Light grey, NCS 2502-R	UV-resistant acrylonitrile styrene acrylate (ASA) Light grey	Carbon impregnated polyurethane foam	Aluminium extrusion	Surface treated aluminium	Stainless steel A2
ANT2 A 0.2 80 HP	Die-cast aluminium Polyester powder paint White, RAL 9016	Die-cast aluminium Polyester powder paint. White, RAL 9016	UV-resistant polycarbonate (PC) Light grey	Carbon impregnated polyurethane foam	Aluminium extrusion	Surface treated aluminium	Stainless steel A2
ANT2 A 0.3 13-32 & 42 HP/HPX	Aluminium Polyester powder paint White, RAL 9016	HP: Zinc/Nickel plated steel. HPX: Die casted aluminium Polyester powder paint. Light grey, NCS 2502-R	UV-resistant polycarbonate (PC) and polystyrene (PS). Light grey	Carbon impregnated polyurethane foam	Aluminium extrusion	Surface treated aluminium	Stainless steel A2
ANT2 A 0.3 38 HP/HPX	Aluminium Polyester powder paint White, RAL 9016	HP: Zinc/Nickel plated steel. HPX: Die casted aluminium Polyester powder paint. Light grey, NCS 2502-R	UV-resistant polycarbonate (PC) Light grey	Carbon impregnated polyurethane foam	Aluminium extrusion	Surface treated aluminium	Stainless steel A2
ANT2 A 0.3 80 HP/HPX	Aluminium Polyester powder paint White, RAL 9016	HP: Zinc/Nickel plated steel. HPX: Die casted aluminium Light grey, NCS 2502-R	UV-resistant acrylonitrile styrene acrylate (ASA). Light grey	Carbon impregnated polyurethane foam	Aluminium extrusion	Surface treated aluminium	Stainless steel A2
ANT3 A 0.3 13-32 & 42 HP/HPX	Aluminium Polyester powder paint White, RAL 9016	HP: Zinc/Nickel plated steel. HPX: Die casted aluminium Polyester powder paint. White, RAL 9016	UV-resistant polycarbonate (PC) and polystyrene (PS). Light grey	Carbon impregnated polyurethane foam	Aluminium extrusion	Surface treated aluminium	Stainless steel A2
ANT3 A 0.3 38 HP/HPX	Aluminium Polyester powder paint White, RAL 9016	HP: Zinc/Nickel plated steel. HPX: Die casted aluminium Polyester powder paint. White, RAL 9016	UV-resistant polycarbonate (PC) Light grey	Carbon impregnated polyurethane foam	Aluminium extrusion	Surface treated aluminium	Stainless steel A2
ANT3 A 0.3 80 HP/HPX	Aluminium Polyester powder paint White, RAL 9016	HP: Zinc/Nickel plated steel. HPX: Die casted aluminium Polyester powder paint. White, RAL 9016	UV-resistant acrylonitrile styrene acrylate (ASA). Light grey	Carbon impregnated polyurethane foam	Aluminium extrusion	Surface treated aluminium	Stainless steel A2
ANT2 A 0.6 7-42 HP/HPX	Aluminium Polyester powder paint White, RAL 9016	HP: Zinc/Nickel plated steel. HPX: Die casted aluminium Polyester powder paint. Light grey, NCS 2502-R	UV-resistant polycarbonate (PC) and polystyrene (PS). Light grey		Aluminium extrusion	Surface treated aluminium	Stainless steel A2
ANT2 A 0.6 80 HP/HPX	Aluminium Polyester powder paint White, RAL 9016	HP: Zinc/Nickel plated steel. HPX: Die casted aluminium Light grey, NCS 2502-R	UV-resistant acrylonitrile styrene acrylate (ASA). Light grey		Aluminium extrusion	Surface treated aluminium	Stainless steel A2
ANT3 A 0.6 7-42 HP/HPX	Aluminium Polyester powder paint White, RAL 9016	HP: Zinc/Nickel plated steel. HPX: Die casted aluminium Polyester powder paint. White, RAL 9016	UV-resistant polycarbonate (PC) and polystyrene (PS). Light grey		Aluminium extrusion	Surface treated aluminium	Stainless steel A2
ANT3 A 0.6 80 HP/HPX	Aluminium Polyester powder paint White, RAL 9016	HP: Zinc/Nickel plated steel. HPX: Die casted aluminium Polyester powder paint. White, RAL 9016	UV-resistant acrylonitrile styrene acrylate (ASA). Light grey		Aluminium extrusion	Surface treated aluminium	Stainless steel A2
ANT2 A 0.9 HP/HPX	Aluminium Polyester powder paint White, RAL 9016	HP: Zinc/Nickel plated steel. HPX: Die casted aluminium Polyester powder paint. Light grey, NCS 2502-R	UV-resistant polycarbonate (PC) and polystyrene (PS). Light grey	Carbon impregnated polyurethane foam	Aluminium extrusion	Surface treated aluminium	Stainless steel A2, galvanized steel
ANT3 A 0.9 HP/HPX	Aluminium Polyester powder paint White, RAL 9016	HP: Zinc/Nickel plated steel. HPX: Die casted aluminium	UV-resistant polycarbonate (PC) and polystyrene	Carbon impregnated polyurethane foam	Aluminium extrusion	Surface treated aluminium	Stainless steel A2 & galvanized



		Polyester powder paint White, RAL 9016	(PS). Light grey				steel
ANT0 A 1.2 HPX	Aluminium Polyester powder paint White, RAL 9016	N/A	UV-resistant polyvinyl chloride (PVC) fabric and polycarbonate (PC) rim. Light grey	Carbon impregnated polyurethane foam	Aluminium extrusion	Surface treated aluminium	Stainless steel A2, galvanized steel
ANT2 A 1.2 HP/HPX	Aluminium Polyester powder paint White, RAL 9016	HP: Zinc/Nickel plated steel. HPX: Die casted aluminium Polyester powder paint. Light grey, NCS 2502-R	UV-resistant polyvinyl chloride (PVC) fabric and polycarbonate (PC) rim. Light grey	Carbon impregnated polyurethane foam	Aluminium extrusion	Surface treated aluminium	Stainless steel A2, galvanized steel
ANT3 A 1.2 HP/HPX	Aluminium Polyester powder paint White, RAL 9016	HP: Zinc/Nickel plated steel. HPX: Die casted aluminium Polyester powder paint White, RAL 9016	UV-resistant polyvinyl chloride (PVC) fabric and polycarbonate (PC) rim. Light grey	Carbon impregnated polyurethane foam	Aluminium extrusion	Surface treated aluminium	Stainless steel A2, galvanized steel
ANT0 A 1.8 4-5 HPX	Aluminium Polyester powder paint Colour grey, US Fed. Std. 595-26152	N/A	UV-resistant polyvinyl chloride (PVC) fabric and polycarbonate (PC) rim. Light grey	Carbon impregnated polyurethane foam	Galvanized steel	Surface treated aluminium	Stainless steel A2, galvanized steel
ANT0 A 1.8 6-13 HPX	Aluminium Polyester powder paint White, RAL 9016	N/A	UV-resistant polyvinyl chloride (PVC) fabric and polycarbonate (PC) rim. Light grey	Carbon impregnated polyurethane foam	Galvanized steel	Surface treated aluminium	Stainless steel A2, galvanized steel
ANT2 A 1.8 HP/HPX	Aluminium Polyester powder paint White, RAL 9016	HP: Zinc/Nickel plated steel. HPX: Die casted aluminium Polyester powder paint, Light grey, NCS 2502-R	UV-resistant polyvinyl chloride (PVC) fabric and polycarbonate (PC) rim. Light grey	Carbon impregnated polyurethane foam	Galvanized steel	Surface treated aluminium	Stainless steel A2, galvanized steel
ANT3 A 1.8 HP/HPX	Aluminium Polyester powder paint White, RAL 9016	HP: Zinc/Nickel plated steel. HPX: Die casted aluminium Polyester powder paint White, RAL 9016	UV-resistant polyvinyl chloride (PVC) fabric and polycarbonate (PC) rim. Light grey	Carbon impregnated polyurethane foam	Galvanized steel	Surface treated aluminium	Stainless steel A2, galvanized steel
ANT0 A 2.4 HP/HPX	Aluminium Polyester powder paint Colour grey, US Fed. Std. 595-26152	N/A	UV-resistant polyvinyl chloride (PVC) fabric and polycarbonate (PC) rim. Light grey	Carbon impregnated polyurethane foam	Galvanized steel	Nickel plated brass ports	Stainless steel A2, galvanized steel
ANT0 A 3.0-3.7 4-5 HPX	Spun aluminium with integral rim section and reinforced back structure. Colour grey, US Fed. Std. 595-26152	Rolled aluminium with mechanical UV stabilised absorber fixings. Colour grey, US Fed. Std. 595-26152	TEGLAR fabric. Planar spring tensioned. Colour white	Carbon impregnated polyurethane foam	Galvanized steel	Nickel plated brass ports	Magnigard 565 coated carbon steel, stainless steel and galvanized steel.
ANT0 A 3.0-3.7 6-8 HPX	Spun aluminium with integral rim section and reinforced back structure. Colour grey, US Fed. Std. 595-26152	Rolled aluminium with mechanical UV stabilised absorber fixings. Colour grey, US Fed. Std. 595-26152	UV-resistant polyvinyl chloride (PVC). Colour white	Carbon impregnated polyurethane foam	Galvanized steel	Surface treated aluminium and nickel plated brass ports	Magnigard 565 coated carbon steel, stainless steel and galvanized steel
ANT0 A 3.0-3.7 10-13 HPX	Spun aluminium with integral rim section and reinforced back structure. Colour grey, US Fed. Std. 595-26152	Rolled aluminium with mechanical UV stabilised absorber fixings. Colour grey, US Fed. Std. 595-26152	TEGLAR fabric. Planar spring tensioned. Colour white	Carbon impregnated polyurethane foam	Galvanized steel	Brass and nickel plated brass ports	Magnigard 565 coated carbon steel, stainless steel and galvanized steel



4.5.2

ANT B, HP/HPX and Dual band antenna

Type	Reflector & Shield	Radio Interface	Radome	Absorber	Mount	Feed	Screws & nuts
ANT3 B 0.3 HP/HPX	Aluminium Painted White, RAL 9010	HP: Galvanized plated steel. HPX: Die casted aluminium Polyester powder paint. White, RAL 9010	UV-resistant ABS White, RAL 9010		Aluminium extrusion	Aluminium	Stainless steel A2
ANT3 B 0.6 7-26 HP/HPX	Aluminium Polyester powder paint Painted White, RAL 9010	HP: Galvanized plated steel. HPX: Die casted aluminium Polyester powder paint. White, RAL 9010	UV-resistant HIPS White, RAL 9010		Aluminium extrusion	Aluminium	Stainless steel A2
ANT3 B 0.6 28-80 HP/HPX	Aluminium Polyester powder paint Painted White, RAL 9010	HP: Galvanized plated steel. HPX: Die casted aluminium Polyester powder paint. White, RAL 9010	UV-resistant polypropylene (PP) White, RAL 9010		Aluminium extrusion	Aluminium	Stainless steel A2
ANT3 B 0.9 HP/HPX	Aluminium Polyester powder paint Painted White, RAL 9010	HP: Galvanized plated steel. HPX: Die casted aluminium Polyester powder paint. White, RAL 9010	UV-resistant polypropylene (PP) White, RAL 9010		Aluminium extrusion	Aluminium	Stainless steel A2
ANT3 B 1.2 HP/HPX	Aluminium Polyester powder paint Painted White, RAL 9010	HP: Galvanized plated steel. HPX: Die casted aluminium Polyester powder paint. White, RAL 9010	UV-resistant expanded polyvinyl chloride (PVC) White, RAL 9010	Carbon impregnated polyurethane foam	Die casted aluminium	Aluminium	Stainless steel A2
ANT3 B 1.8 HP/HPX	Aluminium Polyester powder paint Painted White, RAL 9010	HP: Galvanized plated steel. HPX: Die casted aluminium Polyester powder paint. White, RAL 9010	UV-resistant expanded polyvinyl chloride (PVC) White, RAL 9010	Carbon impregnated polyurethane foam	Die casted aluminium	Aluminium	Stainless steel A2, galvanized steel
ANT0 B 2.4-3.7 HPX	Aluminium Polyester powder paint Painted White, RAL 9010	Aluminium, Polyester powder paint	UV-resistant polyvinyl chloride (PVC) fabric White, RAL 9010	Carbon impregnated polyurethane foam	Galvanized steel	Brass	Stainless steel A2, galvanized steel
ANT2/2 B 0.6 HP/HP	Aluminium Polyester powder paint Painted White, RAL 9010	Zinc coated Polyester powder paint. White, RAL 9010	Expanded polyvinyl chloride (PVC) White, RAL 9010	Carbon impregnated polyurethane foam	Aluminium extrusion	Aluminium	Stainless steel A2

4.5.3

ANT C, HP and HPX

Type	Reflector & Shield	Radio Interface	Radome	Absorber	Mount	Feed	Screws & nuts
ANT C 0.3 13-28 HP/HPX	Aluminium Painted White, RAL 9016	HP: Stainless steel HPX: Die casted aluminium Polyester powder paint. White, RAL 9016	UV-resistant polycarbonate (PC) and polystyrene (PS). White, RAL 9016		Aluminium	Aluminium	Stainless steel A2
ANT C 0.3 32-80 HP/HPX	Aluminium Painted White, RAL 9016	HP: Stainless steel HPX: Die casted aluminium Polyester powder paint. White, RAL 9016	UV-resistant acrylonitrile styrene acrylate (ASA) and acrylonitrile butadiene styrene (ABS) White, RAL 9016		Aluminium	Aluminium	Stainless steel A2
ANT C 0.6 7-28 HP/HPX	Aluminium Polyester powder paint Painted White, RAL 9016	HP: Stainless steel HPX: Die casted aluminium Polyester powder paint. White, RAL 9016	UV-resistant polycarbonate (PC) and polystyrene (PS). White, RAL 9016		Aluminium	Aluminium	Stainless steel A2
ANT C 0.6 32-80 HP/HPX	Aluminium Polyester powder paint Painted White, RAL 9016	HP: Stainless steel HPX: Die casted aluminium Polyester powder paint. White, RAL 9016	UV-resistant acrylonitrile styrene acrylate (ASA) and acrylonitrile butadiene styrene (ABS) White, RAL 9016		Aluminium	Aluminium	Stainless steel A2
ANT C 0.9 6-24/26 HP/HPX	Aluminium Polyester powder paint Painted White, RAL 9016	HP: Stainless steel HPX: Die casted aluminium Polyester powder paint. White, RAL 9016	UV-resistant polyvinyl chloride (PVC) fabric White, RAL 9003	Carbon impregnated polyurethane foam	Aluminium	Aluminium	Stainless steel A2, galvanized steel
ANT C 0.9 28-38	Aluminium	HP: Stainless steel	UV-resistant ABS	Carbon	Aluminium	Aluminium	Stainless



HP/HPX	Polyester powder paint Painted White, RAL 9016	HPX: Die casted aluminium Polyester powder paint. White, RAL 9016	and ASA. White, RAL 9016	impregnated polyurethane foam			steel A2, galvanized steel
ANT C 1.2 HP/HPX	Aluminium Polyester powder paint Painted White, RAL 9016	HP: Stainless steel HPX: Die casted aluminium Polyester powder paint. White, RAL 9016	UV-resistant polyvinyl chloride (PVC) fabric White, RAL 9003	Carbon impregnated polyurethane foam	Aluminium	Aluminium	Stainless steel A2, galvanized steel
ANT C 1.8 HP/HPX	Aluminium Polyester powder paint Painted White, RAL 9016	HP: Stainless steel HPX: Die casted aluminium Polyester powder paint. White, RAL 9016	UV-resistant polyvinyl chloride (PVC) fabric White, RAL 9003	Carbon impregnated polyurethane foam	Aluminium	Aluminium	Stainless steel A2, galvanized steel

4.5.4 ANT A, SHP and SHPX

Type	Reflector & Shield	Radio Interface	Radome	Absorber	Mount	Feed / Array	Screws & nuts
FPA3 A 0.1 SHP	N/A	Zinc/Nickel plated steel. Polyester powder paint. White, RAL 9016	UV-resistant polycarbonate (PC) White, NCS S 1002-B	Carbon impregnated polyurethane foam	Aluminium extrusion, Anodized	Surface treated aluminium	Stainless steel A2
ANT2 A 0.3 SHP/SHPX	Aluminium Polyester powder paint Light grey, NCS 2502-R	HP: Zinc/Nickel plated steel. HPX: Die casted aluminium Polyester powder paint, Light grey, NCS 2502-R	UV-resistant polycarbonate (PC) Light grey	Carbon impregnated polyurethane foam	Aluminium extrusion	Surface treated aluminium	Stainless steel A2, galvanized steel
ANT3 A 0.3 SHP/SHPX	Aluminium Polyester powder paint White, RAL 9016	HP: Zinc/Nickel plated steel. HPX: Die casted aluminium Polyester powder paint White, RAL 9016	UV-resistant polycarbonate (PC) Light grey	Carbon impregnated polyurethane foam	Aluminium extrusion	Surface treated aluminium	Stainless steel A2, galvanized steel
ANT2 A 0.6 SHP/SHPX	Aluminium Polyester powder paint Light grey, NCS 2502-R	HP: Zinc/Nickel plated steel. HPX: Die casted aluminium Polyester powder paint, Light grey, NCS 2502-R	UV-resistant acrylonitrile styrene acrylate (ASA). Light grey	Carbon impregnated polyurethane foam	Aluminium extrusion	Surface treated aluminium	Stainless steel A2 or galvanized steel
ANT3 A 0.6 SHP/SHPX	Aluminium Polyester powder paint White, RAL 9016	HP: Zinc/Nickel plated steel. HPX: Die casted aluminium Polyester powder paint White, RAL 9016	UV-resistant acrylonitrile styrene acrylate (ASA). Light grey	Carbon impregnated polyurethane foam	Aluminium extrusion	Surface treated aluminium	Stainless steel A2 or galvanized steel
ANT2 A 0.9 SHP/SHPX	Aluminium Polyester powder paint Light grey, NCS 2502-R	HP: Zinc/Nickel plated steel. HPX: Die casted aluminium Polyester powder paint, Light grey, NCS 2502-R	High impact polystyrene (HIPS) Light grey	Carbon impregnated polyurethane foam	Aluminium extrusion	Surface treated aluminium	Stainless steel A2 or galvanized steel
ANT3 A 0.9 SHP/SHPX	Aluminium Polyester powder paint White, RAL 9016	HP: Zinc/Nickel plated steel. HPX: Die casted aluminium Polyester powder paint White, RAL 9016	High impact polystyrene (HIPS) Light grey and polystyrene (PS). Light grey	Carbon impregnated polyurethane foam	Aluminium extrusion	Surface treated aluminium	Stainless steel A2 or galvanized steel



5

Environmental Data

5.1

Compliance with International Standards

Storage

ETSI EN 300 019-2-1 v2.1.2 (class 1.2)

Transportation

ETSI EN 300 019-2-2 v2.1.2 (class 2.3)

Stationary use at non-weather protected locations

ETSI EN 300 019-2-4 v2.2.2 (class 4.1E, IEC class 4M5)

5.2

Wind Velocity

5.2.1

ANT A, HP/HPX and SHP/SHPX

Size [m]	Frequency [GHz]	Operational [m/s]	Survival [m/s]
0.1		50	70
0.2-0.3		50	70
0.6	7-42	50	70
0.6	80	40	70
0.9	6-26	50	70
0.9	28-38	40	70
1.2-1.8		50	70
2.4-3.7		50	56

Operational: Maximum deflection 0.3*HPBW

Survival: No damage to the antenna. Realignment might be needed.

5.2.2

ANT B and Dual band antenna, HP/HPX

Size [m]	Frequency [GHz]	Operational [m/s]	Survival [m/s]
0.3		50	70
0.6		50	70
0.9	6-15	50	70
0.9	18-23	45	70
0.9	24-32	40	70
0.9	38	35	70
1.2		50	70
1.8	4-5	50	56
1.8	6-23	50	70
2.4-3.7		50	56



Operational: Maximum deflection 0.3*HPBW
Survival: No damage to the antenna. Realignment might be needed.



5.2.3

ANT C, HP/HPX

Size [m]	Frequency [GHz]	Installed on tube diameter	Operational [m/s]	Survival [m/s]
0.3			50	70
0.6	7-42		50	70
0.6	80	40-50	30	60
0.6	80	50-120	50	70
0.9	6-18		50	70
0.9	23-38		40	70
1.2			50	70
1.8			50	70

Operational: Maximum deflection 0.3*HPBW

Survival: No damage to the antenna. Realignment might be needed.

5.3

Wind Loading, Force and Torque

5.3.1

ANT A, HP and HPX

Size [m]	Frequency [GHz]	Operational 40 m/s		Operational 50 m/s		Survival 56 m/s		Survival 70 m/s	
		F [N]	M [Nm]	F [N]	M [Nm]	F [N]	M [Nm]	F [N]	M [Nm]
0.1				129	35			253	70
0.2				160	44			313	85
0.3				227	73			446	144
0.6	7-42			660	205			1290	395
0.6	80	421	117					1290	357
0.9	6-26			1481	601			2903	1179
0.9	28-38	948	385					2903	1179
1.2				2519	1022			4937	2004
1.8	4			5378	3852			10655	7561
1.8	5			5378	3138			10655	7561
1.8	6-23			5444	2425			10655	6004
2.4	4-5			9059	4700	10600	7650		
2.4	6-13			9059	3935	10600	6520		
3.0				14155	6928	17632	8630		
3.7				20383	11345	25390	14132		

Maximum force and torque due to wind from the most critical direction.



5.3.2

ANT B, HP and HPX

Size [m]	Frequency [GHz]	Operational 50 m/s		Operational 70 m/s		Survival 70 m/s		Survival 89 m/s	
		F [N]	M [Nm]	F [N]	M [Nm]	F [N]	M [Nm]	F [N]	M [Nm]
0.3		222	72			365	118		
0.6		642	218			1238	420		

Size [m]	Freq [GHz]	Operational 35 m/s		Operational 40 m/s		Operational 45 m/s		Operational 50 m/s		Survival 56 m/s		Survival 70 m/s	
		F [N]	M [Nm]	F [N]	M [Nm]	F [N]	M [Nm]	F [N]	M [Nm]	F [N]	M [Nm]		
0.9	6-15							1519	629	2930	1213	2930	1213
0.9	18-23					1292	535			2930	1213	2930	1213
0.9	24-32			972	402					2930	1213	2930	1213
0.9	38	775	321							2930	1213	2930	1213
1.2								2419	797	4666	1538	4666	1538
1.8	4-5							6769	2419	7500	2970		
1.8	6-23							5379	2453			10377	4732
2.4								11580	4855	12831	5961		
3.0								17480	8337	19368	10236		
3.7								24978	13559	27676	16647		

Maximum force and torque due to wind from the most critical direction.

5.3.3

ANT C, HP and HPX

Size [m]	Frequency [GHz]	Operational 40 m/s		Operational 50 m/s		Survival 56 m/s		Survival 70 m/s	
		F [N]	M [Nm]	F [N]	M [Nm]	F [N]	M [Nm]	F [N]	M [Nm]
0.3						305	113		
0.6						830	249		
0.9	6-18					1510	645		
0.9	23-38	966	413						
1.2						3039	1335		
1.8						5368	1836		
								10522	3599

Maximum force and torque due to wind from the most critical direction.

5.3.4

ANT A, SHP and SHPX

Size [m]	Operational 50 m/s		Survival 70 m/s	
	F [N]	M [Nm]	F [N]	M [Nm]
0.1	64	11	126	23
0.3	227	73	446	144
0.6	660	205	1290	395
0.9	1508	633	2956	1242

Maximum force and torque due to wind from the most critical direction.



5.3.5

Dual band antenna

Size [m]	Operational 50 m/s		Survival 70 m/s	
	F [N]	M [Nm]	F [N]	M [Nm]
0.6	642	246	1238	474

Maximum force and torque due to wind from the most critical direction.

5.4

Endurance

The antennas are designed to withstand years of exposure to coastal and/or industrial atmosphere without noticeable performance degeneration or significant deterioration in finish, such as corrosion etc.



6 Mounting Data

6.1 Mounting Kit

6.1.1 ANT A, HP and HPX

The mounting kit (including side struts for stabilisation) must be fitted to the following tube diameters.

Size [m]	Mounting kit, tube diameter [mm]	Side strut, tube diameter [mm]	Number of side struts [qty]
0.1-0.6	50-120		
0.9	90-120		
1.2	90-115	48-120	1
1.8	115-120	48-120	1
2.4	115	100-115	1
3.0-3.7	115	100-115	2

6.1.2 ANT B and Dual band antenna, HP/HPX

The mounting kit (including side struts for stabilisation) must be fitted to the following tube diameters.

Size [m]	Mounting kit, tube diameter [mm]	Side strut, tube diameter [mm]	Number of side struts [qty]
0.3-0.6	48-120		
0.9	89-114		
1.2-1.8	114	60-114	1
2.4-3.7	114	60-114	1

6.1.3 ANT C, HP/HPX

The mounting kit (including side struts for stabilisation) must be fitted to the following tube diameters.

Size [m]	Frequency [GHz]	Mounting kit, tube diameter [mm]	Side strut, tube diameter [mm]	Number of side struts [qty]
0.3-0.6	7-42	50-120		
0.3-0.6	80	40-120		
0.9		90-114		
1.2		90-114	60-114	1
1.8		114	60-114	1



6.1.4

ANT A, SHP and SHPX

The mounting kit must be fitted to the following tube diameters.

Size [m]	Mounting kit, tube diameter [mm]
0.1-0.6	50-120
0.9	115

6.2

Alignment

6.2.1

ANT A, HP/HPX and SHP/SHPX

Size [m]	Azimuth [±°]	Elevation [±°]	Polarization ⁴⁸ [±°]
0.1	15	25	
0.2-1.2	15	15	5
1.8	15	5	5
2.4-3.7	5	5	6

Minimum alignment interval.

6.2.2

ANT B and Dual band antenna, HP/HPX

Size [m]	Azimuth [±°]	Elevation [±°]	Polarization ⁴⁹ [±°]
0.3-1.2	15	15	5
1.8	5	5	5
2.4-3.7	5	5	5

Minimum alignment interval.

6.2.3

ANT C, HP/HPX

Size [m]	Azimuth [±°]	Elevation [±°]	Polarization ⁵⁰ [±°]
0.3	15	25	5
0.6-0.9	15	15	5
1.2	15	10	5
1.8	5	5	5

Minimum alignment interval.

⁴⁸ Polarization alignment is valid for all sizes of HPX+SHPX.

⁴⁹ Polarization alignment is valid for all sizes of HPX.

⁵⁰ Polarization alignment is valid for all sizes of HPX.



6.3

Installation Instruction

A quick guide is enclosed with every antenna. A full version of the installation instruction is stored in CPI Store.



7

Packing Data

7.1 Dimensions

7.1.1 ANT A, HP and HPX

Product Name	Freq. [GHz]	Length [mm]	Width [mm]	Height [mm]	Volume [m ³]
ANT0 A 1.2 HPX		1360	378	1515	0.779
ANT0 A 1.8 HPX	4	1995	600	2107	2.522
ANT0 A 1.8 HPX	5-23	1895	450	2107	1.797
ANT0 A 2.4 HP/HPX		2375	1130	2250	6.038
ANT0 A 3.0 HP/HPX		3404	1168	1931	7.677
ANT0 A 3.7 HPX		3988	1524	2134	12.970
ANT2 A 0.1 HP		330	390	140	0.018
ANT2 A 0.2 HP		420	320	190	0.026
ANT2 A 0.3 HP		400	400	350	0.056
ANT2 A 0.3 HPX	13-42	400	400	450	0.072
ANT2 A 0.3 HPX	80	400	400	400	0.064
ANT2 A 0.6 HP		729	695	354	0.179
ANT2 A 0.6 HPX		800	800	400	0.256
ANT2 A 0.9 HP		1200	400	1107	0.531
ANT2 A 0.9 HPX		1200	400	1107	0.531
ANT2 A 1.2 HP		1360	378	1515	0.779
ANT2 A 1.2 HPX		1360	378	1515	0.779
ANT2 A 1.8 HP		1895	450	2107	1.797
ANT2 A 1.8 HPX		1895	450	2107	1.797
ANT3 A 0.3 HP		400	400	350	0.056
ANT3 A 0.3 HPX		600	400	460	0.110
ANT3 A 0.6 HP		729	695	354	0.179
ANT3 A 0.6 HPX		800	800	400	0.256
ANT3 A 0.9 HP		1200	400	1107	0.531
ANT3 A 0.9 HPX		1200	400	1107	0.531
ANT3 A 1.2 HP		1360	378	1515	0.779
ANT3 A 1.2 HPX		1360	378	1515	0.779
ANT3 A 1.8 HP		1895	450	2107	1.797
ANT3 A 1.8 HPX		1895	450	2107	1.797



7.1.2

ANT B, HP and HPX

Product Name	Freq. [GHz]	Length [mm]	Width [mm]	Height [mm]	Volume [m ³]
ANT0 B 1.2 HPX		1370	370	1430	0.72
ANT0 B 1.8 HPX	4-5	2050	2050	1050	4.41
ANT0 B 1.8 HPX	6-23	1980	520	2050	2.11
ANT0 B 2.4 HPX	4	3550	1800	1500	9.05
ANT0 B 2.4 HPX	5-15	2670	1040	1630	4.53
ANT0 B 3.0 HPX	4	3570	2250	1870	15.0
ANT0 B 3.0 HPX	5-13	3270	1150	2070	7.78
ANT0 B 3.7 HPX	4	4600	2250	1800	18.6
ANT0 B 3.7 HPX	5-7/8	3980	1800	2190	15.7
ANT3 B 0.3 HP	13-42	400	400	240	0.04
ANT3 B 0.3 HP	80	400	400	250	0.04
ANT3 B 0.3 HPX		400	400	280	0.04
ANT3 B 0.6 HP		680	790	340	0.18
ANT3 B 0.6 HPX		680	790	340	0.18
ANT3 B 0.9 HP & HPX		1050	1030	400	0.43
ANT3 B 1.2 HP & HPX		1370	370	1430	0.72
ANT3 B 1.8 HP & HPX		1980	520	2050	2.11

7.1.3

ANT C, HP and HPX

Product Name	Length [mm]	Width [mm]	Height [mm]	Volume [m ³]
ANT3 C 0.3 HP	435	460	235	0.05
ANT3 C 0.3 HPX	435	460	395	0.08
ANT3 C 0.6 HP	710	697	385	0.19
ANT3 C 0.6 HPX	710	697	520	0.26
ANT3 C 0.9 HP & HPX	1120	1090	640	0.78
ANT3 C 1.2 HP & HPX	1380	410	1560	0.88
ANT3 C 1.8 HP & HPX	2100	570	2220	2.66

7.1.4

ANT A, SHP and SHPX

Product Name	Freq. [GHz]	Length [mm]	Width [mm]	Height [mm]	Volume [m ³]
FPA3 A 0.1 SHP		274	200	112	0.006
ANT2 A 0.3 SHP		400	400	550	0.088
ANT2 A 0.3 SHPX		400	400	617	0.099
ANT2 A 0.6 SHP		730	730	575	0.306
ANT2 A 0.6 SHPX		910	755	595	0.399
ANT2 A 0.9 SHP/SHPX		1082	1082	1113	1.303
ANT3 A 0.3 SHP		400	400	550	0.088
ANT3 A 0.3 SHPX		600	400	460	0.110
ANT3 A 0.6 SHP		730	730	575	0.306
ANT3 A 0.6 SHPX		925	755	595	0.399
ANT3 A 0.9 SHP/SHPX		1082	1082	1113	1.303



7.1.5

Dual band antenna

Product Name	Freq. [GHz]	Length [mm]	Width [mm]	Height [mm]	Volume [m ³]
ANT2/2 B 0.6 HP/HP		730	680	480	0.239

7.2

Weight

7.2.1

ANT A, HP/HPX and SHP/SHPX

Size [m]	Freq. [GHz]	Type									
		ANT0 HP/HPX	ANT2 HP	ANT2 HPX	ANT3 HP	ANT3 HPX	ANT2 SHP	ANT2 SHPX	ANT3/FPA3 SHP	ANT3 SHP	ANT3 SHPX
0.1			5.1							2.6	
0.2			6.7								
0.3	13-42		7.2	10	7.2	11	9	12.4	9	12	
0.3	80		8.6	9.3	8.6	12.5					
0.6			13	17	13	17	18	23	16	22	
0.9			30	33	30	33	79	81	79	81	
1.2		62	60	62	60	62					
1.8	4	151									
1.8	5	126									
1.8	6-23	133	131	133	131	133					
2.4	4&15	329									
2.4	5-13	318									
3.0		520									
3.7		736									

Gross packing weight (in kg).

7.2.2

ANT B and Dual band antenna, HP/HPX

Size [m]	Freq. [GHz]	ANT0 HPX	ANT3 HP	Type ANT3 HPX	ANT2/2 HP/HP
0.3	13-42		7	10.5	
0.3	80		8	12	
0.6			9	12.5	18.5
0.9			22	26	
1.2		59	57	61	
1.8	4-5	270			
1.8	6-23	142	140	144	
2.4	4	590			
2.4	5-15	320			
3.0	4	860			
3.0	5-13	450			
3.7	4	1010			



3.7	5-7/8	770		
-----	-------	-----	--	--

Gross packing weight (in kg).

7.2.3 ANT C, HP/HPX

Size [m]	Type		
	ANT2/ANT3 HP	ANT2/ANT3 HPX	
0.3	5.8	8.8	
0.6	11	14.5	
0.9	39	42	
1.2	79	82	
1.8	150	162	

Gross packing weight (in kg).

7.3 Compliance with International Standards

7.3.1 HP and HPX

ANT A and ANT B 1.2-3.7 m antennas are packed in wooden crates. The wood is bark free (DB), heat treated (HT) and marked in accordance with: International standards for phytosanitary measures Guidelines for regulating wood packaging material in international trade ISPM publication No. 15, March 2002.

ANT A and ANT B 0.1-0.9 m antennas are packed in cardboard boxes and hence the material is considered sufficiently processed to be excluded from the requirements above.

ANT C 0.9-1.8 m are packed in crates made of plywood and hence the material is considered sufficiently processed to be excluded from the requirements above.

7.3.2 SHP and SHPX

0.9 m antennas are packed in wooden crates. The wood is bark free (DB), heat treated (HT) and marked in accordance with:
International standards for phytosanitary measures Guidelines for regulating wood packaging material in international trade ISPM publication No. 15, March 2002.

0.1-0.6 m antennas are packed in cardboard boxes and hence the material is considered sufficiently processed to be excluded from the requirements above.



8

Document Revision Records

- A-EZ See earlier revisions.
- FA 0.9 m 28-38 GHz operational wind data corrected.
- FB 0.3 m HPX 13-42 GHz dimensions added (missing in EZ-FA).
- FC 0.2 m updated (new design, ETSI class 3 compliant).
0.6 m 80 GHz updated (new design).
- FD 0.3 m 80 GHz updated (new design).
- FE ANT3 18-23 GHz and 0.1 m 60 GHz added and editorial changes.
- FF ANT3 13, 15 and 38 GHz added.
- FG ANT2 0.3 HP, 0.6 HP/HPX, 0.9 HP, 1.2 HP/HPX updated
- FH ANT3 7/8 added.
- FJ Modular ANT0 and ANT2 antennas added.
- FK Modular ANT2 0.3 80, ANT2 0.6 80 added and ANT3 10/11 added.
- FL 1.8 m HP+HPX 6-23 updated (new electrical & mechanical design).
ANT3 6, 24/26, 80 GHz added
- FM FPA3 0.1 38 SHP and ANT2 0.1 80 HP added
- FN 0.3 m new radome design (13-32 & 42 GHz),
- FS FPA3 A 28, 32, 42 GHz added, ANT3 A I/F HPX/SHPX new mechanical design
- FT Antenna name changed, antenna type B added
- FU ANT B delivered in one box instead of two
- FV ANT A delivered in one box, ANT0 B & ANT2/2 0.6 HP/HP added. RPE's moved to 2/1301-UKY 210 40+
- FX ANT C added
- FY ANT2 B 80 & ANT2/2 0.6 18/80 HP/HP added, ANT0 A 1.8 m 4-5 GHz & ANT0 A 2.4 m new design
- FZ Editorial changes
- GA ANT2 C 80 added