

VHF AIR BAND TRANSCEIVER

## 8.33/25 kHz Ground to Air Radio with Class Leading 1500 mW Powerful Audio



8.33 kHz and 25 kHz channel spacing

1500 mW loud audio provides clear communications

6 W (PEP) /1.8 W (carrier) RF output power

Built-in Bluetooth® for Hands-Free Operation\*

\* Bluetooth operation depending on the transceiver version.



Large capacity battery pack provides 17 hours\* of long battery life

\* With BP-280. Typical operation with TX : RX : Standby = 5:5:90. (Bluetooth OFF, backlight OFF)

Compact, waterproof durable body (IP67/54 and MIL-STD-810-G)


LCD and key backlight for night time operation

Compatible\* with third-party aviation headsets


\* Optional headset adapter OPC-2401 required.

### And More

- Auto Noise Limiter (ANL) for noise reduction
- Side Tone function
- Internal VOX capability
- 200 memory channels with 8 character names
- BNC type antenna connector



LCD and keypad backlight



IP67 waterproofing



1500 mW powerful audio



**SPECIFICATIONS**

		IC-A16E
<b>GENERAL</b>		
Frequency range	TX/RX : 118.000–136.992 MHz	
Number of memory channels	200 channels	
Channel spacing	8.33 kHz/25 kHz	
Type of emission	6K80A3E, 5K00A3E	
Power supply requirement	7.2 V DC	
Current drain (approximate)		
TX High	1.8 A	
RX Max. audio/Stand-by	650 mA/65 mA typical	
Antenna impedance	50 Ω (BNC type antenna connector)	
Operating temperature range	-20°C to +55°C	
Dimensions (WxHxD) (Projections not included)	52.2 × 111.8 × 34.1 mm (with BP-280)	
Weight (approximate)	257 g (with BP-280)	
<b>TRANSMITTER</b>		
Output power (at 7.2 V DC)	6.0 W (PEP), 1.8 W (carrier)	
Audio harmonic distortion	Less than 10% (at 85% + 3 dB modulation)	
Harmonics spurious emissions	Less than -36 dBm (Except for operating frequency ±1 MHz.)	
Frequency stability	±1 ppm	
<b>RECEIVER</b>		
Intermediate frequencies	46.35 MHz (1st), 450 kHz (2nd)	
Sensitivity	Less than 0 dBμ (at 12 dB SINAD with CCITT)	
Squelch sensitivity (Threshold)	Less than 0 dBμ	
Spurious response	More than 70 dB	
Hum and noise	More than 40 dB (at 90% modulation)	
Audio output power	INT SP EXT SP	1500 mW typical More than 350 mW (AM 8 Ω 60% modulation at 10% distortion)
External speaker connector	3 conductor 3.5 (d) mm	

Measurements made in accordance with EN300 676-2.  
All stated specifications are subject to change without notice or obligation.

**Applicable U.S. Military Specifications**

Standard	MIL 810G	
	Method	Procedure
Low Pressure	500.5	I, II
High Temperature	501.5	I, II
Low Temperature	502.5	I, II
Temperature Shock	503.5	I-C
Solar Radiation	505.5	I
Rain Blowing/Drip	506.5	I, III
Humidity	507.5	II
Salt Fog	509.5	-
Dust Blowing	510.5	I
Immersion	512.5	I
Vibration	514.6	I
Shock	516.6	I, IV

Also meets equivalent MIL-STD-810-C, -D, -E and -F.

**Ingress Protection Standard**

Dust and Water	IP67/54
----------------	---------

**Supplied accessories :** (\* Not supplied, depending on the transceiver version.)

- BP-280 battery pack ●BC-213 rapid charger\* ●BC-242 AC adapter\*
- FA-B02AR antenna ●MB-133 belt clip ●Hand strap

**OPTIONS**

**BATTERY PACKS**

- BP-278** Rechargeable Li-ion 7.2 V  
1190 mAh (typ.), 1130 mAh (min.).
- BP-279** Rechargeable Li-ion 7.2 V  
1570 mAh (typ.), 1485 mAh (min.).
- BP-280** Rechargeable Li-ion 7.2 V  
2400 mAh (typ.), 2280 mAh (min.).  
Same as supplied.



**DESKTOP CHARGER**

- BC-213** Charges the BP-278, BP-279 or BP-280.
- BC-242** AC adapter. Same as supplied.
- BC-123SE/SUK/SV\*** AC adapter.  
\* SE for Europe, SUK for UK, SV for Australia.



**MULTI-CHARGER**

- BC-214\*** Charges up to six transceivers  
and/or batteries at the same time.
- BC-157S** AC adapter.  
\* The AD-130 charger adapter is supplied with the  
BC-214, depending on the charger version.



**VEHICLE CHARGER CABLE**

- CP-23L** For use with the BC-213.



**DC POWER CABLES**

- OPC-515L** For use with the BC-213.
- OPC-656** For use with the BC-214.



**CHARGER BRACKET**

- MB-130** For use  
with the BC-213.



**SPEAKER-MICROPHONE**

- HM-240** Waterproof.



**Bluetooth® HEADSET**

- VS-3** With side tone function when  
connected to transceiver.



**HEADSET ADAPTER**

- OPC-2401**



**BELT CLIP**

- MB-133**  
Same as supplied.



**BELT HANGERS**

- MB-96N** Swivel type.
- MB-96F** Fixed type.
- MB-96FL** Longer type.



**ANTENNA**

- FA-B02AR**  
Same as supplied.

**SOFTWARE AND CABLE**

- CS-A16** Programming software for Windows® PC.
- OPC-478UC** USB type radio programming cable.

Icom, Icom Inc. and Icom logo are registered trademarks of Icom Incorporated (Japan) in Japan, the United States, the United Kingdom, Germany, France, Spain, Russia, Australia, New Zealand, and/or other countries. Windows is either a registered trademark or a trademark of Microsoft Corporation in the United States and/or other countries. The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by Icom Inc. is under license. All other trademarks are the properties of their respective holders.

**Icom Inc.**

1-1-32, Kamiminami, Hirano-Ku, Osaka 547-0003, Japan Phone: +81 (06) 6793 5302 Fax: +81 (06) 6793 0013

[www.icom.co.jp/world](http://www.icom.co.jp/world)

**Count on us!**

**Icom America Inc.**  
[www.icomamerica.com](http://www.icomamerica.com)

**Icom (Europe) GmbH**  
[www.icomeurope.com](http://www.icomeurope.com)

**Icom (Australia) Pty. Ltd.**  
[www.icom.net.au](http://www.icom.net.au)

Your local distributor/dealer:

**Icom Canada**  
[www.icomcanada.com](http://www.icomcanada.com)

**Icom Spain S.L.**  
[www.icomspain.com](http://www.icomspain.com)

**Shanghai Icom Ltd.**  
[www.bjicom.com](http://www.bjicom.com)

**Icom Brazil**  
E-mail: [sales@icombrasil.com](mailto:sales@icombrasil.com)

**Icom (UK) Ltd.**  
[www.icomuk.co.uk](http://www.icomuk.co.uk)

**Icom France s.a.s.**  
[www.icom-france.com](http://www.icom-france.com)