

**HCS-5100CHG/60
IR Receiver Charging Case****Features**

- Used for charging IR receivers (HCS-5100R)
- Charges 60 pcs of IR receivers per charging
- Uses universal power supply with automatic voltage

Controls and Indicators

- Power switch
- Charging indicator on the receiver
- booth supplying the same interpretation channel.
- A maximum of six interpreter units can be installed in each booth

Interconnections

- Power output interface
- Power input interface
- Charging lattices

Technical Specifications
Electrical

Power supply AC 100 V-120 V 60 Hz or AC 220 V-240 V 50 Hz
Power consumption 125 W (60 receivers charging)
Power consumption (standby) 7W no receiver in charging case

Mechanical

Dimensions h x w x d (mm) 260 x 610 x 405
Net weight 14.5 kg (w/o IR receiver)
Color Blue

**HCS-5100KS
IR Receiver Storage Case****Features**

- Used for storing and transporting IR receivers
- Every case can store up to 100 IR receivers

Technical Specifications**Mechanical**

Dimensions h x w x d (mm)	205x669x307
Net weight	6.0kg(w/oIRreceiver)
Gross weight	14.0 kg (w/100 pcs IR receivers, w/o battery)
Color	Blue

BNC Connector**Features**

- Used to connect HCS-5100M/N and HCS-5100T/S or between HCS-5100T/SEvery case can store up to 100 IR receivers
- Used with RG-59 Coaxial-cable

HCS-5100PA Headphone**Features**

- Used with the receiver or a conference unit
- Hi-Fi sound quality
- $32 \Omega \times 2$, Ø 3.5 mm stereo plug
- Frequency response: 20 Hz to 20 kHz
- Sensitivity: =108 dBA/1 mW

EP-820AS Single Earphone**Features**

- Used with the receiver or a conference unit
- Hi-Fi sound quality
- Ø 3.5 mm stereo plug
- 32Ω (Tip and Sleeve, Ring: NC)
- Frequency response: 50 Hz to 20 kHz
- Sensitivity: =102 dBA/1 mW

HCS-5100PB Headphone**Features**

- Used with the receiver or a conference unit
- Hi-Fi sound quality
- $32 \Omega \times 2$, Ø 3.5 mm stereo plug
- Frequency response: 20 Hz to 20 kHz
- Sensitivity: =108 dBA/1 mW

EP-828 Single Earphone**Features**

- Used with the receiver or a conference unit
- Hi-Fi sound quality
- Ø 3.5 mm stereo plug (TRS)
- 32Ω (Tip and Sleeve, Ring: NC)
- Frequency response: 20 Hz to 20 kHz
- Sensitivity: =108 dBA/1 mW

EP-829SW**Single Earphone with Switch****Features**

- Used with the receiver or a conference unit
- Excellent sound quality
- Built-in magnetic control switch
- Earshell is detachable and washable, convenient for cleaning
- Ø 3.5 mm stereo plug (TRS)
- 32 Ohm (Tip and Sleeve, Ring: NC)
- Frequency response: 20 Hz to 20 kHz
- Sensitivity: =108 dBA/1 mW

HCS-5100BAT-16**Ni-MH Rechargeable Battery Pack****Features**

- Ni-MH rechargeable battery pack
- Suitable for HCS-5100R series digital infrared receiver

Technical Specifications**Electrical**

Voltage	2.4 V
Capacity	1600 mAh

Mechanical

Dimensions h x w x d (mm)	51 x 27 x 15
Weight	50 g
Color	Green

Coaxial-cable**Features**

- Equivalent impedance: 75 Ohm
- Ø5mm(RG-59)
- Ø7mm(RG-6/U)
- Length of per roll:300 meter