



TEST NUMBER: 100527-6074

Time interval since previous test	min	-		
Operation	O			
Phase		C	B	A
Breaking current, phase value	kA	16,2	16,5	16,2
Average current, three phase	kA	16,3		
Breaking current, DC-component	%	15	61	50
Recovery voltage, phase value	kV	9,18	9,13	9,15
Recovery voltage, between phases	kV	15,9		
TRV, peak	kV	-17,4	23,8	17,2
Arc duration	ms	9,0	0,7	9,0
Opening time	ms	-		
Break time	ms	-	-	-
Voltage opening coil	- Vd.c.	Gas pressure at 20 °C		
		- MPa		
		Operating pressure		
		- MPa		

Remarks: Recloser cleared.





TEST NUMBER: 100527-6075


Time interval since previous test	min	-		
Time interval between operations	s	0,519		
Operation		CO		
Phase		C	B	A
Applied voltage, phase value	kV	9,46	9,46	9,39
Applied voltage, between phases	kV	16,3		
Making current, peak	kA	45,7	-34,8	-34,9
Breaking current, phase value	kA	16,1	16,3	16,3
Average current, three phase	kA	16,2		
Breaking current, DC-component	%	56	21	34
Recovery voltage, phase value	kV	9,05	9,07	9,04
Recovery voltage, between phases	kV	15,7		
TRV, peak	kV	-32,1	-18,3	-28,9
Make time	ms	-	-	-
Arc duration	ms	9,4	9,4	3,2
Opening time	ms	-		
Break time	ms	-	-	-

Voltage closing coil - Vd.c.
Voltage opening coil - Vd.c.

Gas pressure at 20 °C
Operating pressure





Remarks: Recloser closed and cleared.


TEST NUMBER: 100527-6076

Time interval since previous test	min	-		
Time interval between operations	s	1,03		
Operation		CO		
Phase		C	B	A
Applied voltage, phase value	kV	9,49	9,53	9,45
Applied voltage, between phases	kV	16,4		
Making current, peak	kA	-26,7	-40,7	43,8
Breaking current, phase value	kA	16,3	16,3	16,3
Average current, three phase	kA	16,3		
Breaking current, DC-component	%	3	20	23
Recovery voltage, phase value	kV	5,19	5,21	5,19
Recovery voltage, between phases	kV	9,00		
TRV, peak	kV	30,5	-11,2	-31,1
Make time	ms	-	-	-
Arc duration	ms	6,4	10,9	10,9
Opening time	ms	-		
Break time	ms	-	-	-
Voltage closing coil	- Vd.c.	Gas pressure at 20 °C		
Voltage opening coil	- Vd.c.	Operating pressure		

Remarks: Recloser closed and cleared.






TEST NUMBER: 100527-6077

Time interval since previous test	min	-		
Time interval between operations	s	1,02		
Operation		CO		
Phase		C	B	A
Applied voltage, phase value	kV	9,48	9,45	9,40
Applied voltage, between phases	kV	16,4		
Making current, peak	kA	44,8	-29,6	-39,2
Breaking current, phase value	kA	16,3	16,3	16,3
Average current, three phase	kA	16,3		
Breaking current, DC-component	%	24	5	19
Recovery voltage, phase value	kV	9,48	9,35	9,34
Recovery voltage, between phases	kV	16,3		
TRV, peak	kV	-30,9	-15,6	-46,2
Make time	ms	-	-	-
Arc duration	ms	9,4	9,5	4,4
Opening time	ms	-		
Break time	ms	-	-	-

Voltage closing coil	- Vd.c.	Gas pressure at 20 °C	- MPa
Voltage opening coil	- Vd.c.	Operating pressure	

Remarks: Recloser closed and cleared.



TDT 2108-10

DUTY: T50

Page 173

TEST NUMBERS

100527-6084	100527-6096	100527-6108	100527-6120	100527-6136
100527-6085	100527-6097	100527-6109	100527-6121	100527-6137
100527-6086	100527-6098	100527-6110	100527-6122	100527-6138
100527-6087	100527-6099	100527-6111	100527-6123	100527-6139
100527-6088	100527-6100	100527-6112	100527-6128	100527-6140
100527-6089	100527-6101	100527-6113	100527-6129	100527-6141
100527-6090	100527-6102	100527-6114	100527-6130	100527-6142
100527-6091	100527-6103	100527-6115	100527-6131	100527-6143
100527-6092	100527-6104	100527-6116	100527-6132	
100527-6093	100527-6105	100527-6117	100527-6133	
100527-6094	100527-6106	100527-6118	100527-6134	
100527-6095	100527-6107	100527-6119	100527-6135	

CONDITION BEFORE TESTS

Recloser in same condition.

Supply and load side connections interchanged.


Supply to fixed contacts.

Load on moving contacts.

Frame earthed via an earth fault current indicating CT.

Recovery voltage maintained for 1 sec after the final interruption.

TEST-CIRCUIT S08



G	= Generator	TO	= Test Object
MB	= Master Breaker	L	= Reactor
MS	= Make Switch	R	= Resistor
PT	= Power Transformer	C	= Capacitor

U = Voltage Measurement to earth
I = Current Measurement

Supply		
Power	MVA	752
Frequency	Hz	60
Phase(s)		3
Voltage	kV	15,5
Current	kA	28
Impedance	Ω	0,32
Power factor		< 0,1
Neutral		not earthed

TRV control elements added (supply)		
C ₁	μ F	0,008
R ₁ (in parallel)	Ω	-
R ₁ (in series)	Ω	-
L ₁	mH	-
C _d	nF	-
Neutral		not earthed


Load		
Impedance	Ω	0,8
X/R		4
Neutral		not earthed

TRV control elements added (load)		
C ₂	nF	15
R ₂ (in parallel)	Ω	-
Neutral		not earthed

Prospective TRV across TO		
E ₂	kV	31,9
T ₂	μ s	22,4
t _d	μ s	< 4
Rate of rise	kV/ μ s	1,68

Inductive load element		
X _L (L _L)	Ω	0,784

Remarks: -





TEST NUMBER: 100527-6084

Time interval since previous test	min	-		
Operation	O			
Phase			C	B
Breaking current, phase value	kA	8,14	8,12	8,17
Average current, three phase	kA	8,14		
Breaking current, DC-component	%	14	100	61
Recovery voltage, phase value	kV	9,34	9,30	9,20
Recovery voltage, between phases	kV	16,1		
TRV, peak	kV	18,6	-21,1	-18,0
Arc duration	ms	2,1	1,0	0,5
Opening time	ms	-		
Break time	ms	-	-	-

Voltage opening coil	- Vd.c.	Gas pressure at 20 °C	- MPa
		Operating pressure	

Remarks: Recloser cleared.






TEST NUMBER: 100527-6085

Time interval since previous test	min	-		
Time interval between operations	s	0,525		
Operation		CO		
Phase		C	B	A
Applied voltage, phase value	kV	9,44	9,41	9,33
Applied voltage, between phases	kV	16,3		
Making current, peak	kA	-16,4	-19,6	23,8
Breaking current, phase value	kA	8,15	8,16	8,13
Average current, three phase	kA	8,15		
Breaking current, DC-component	%	30	51	40
Recovery voltage, phase value	kV	9,36	9,24	9,24
Recovery voltage, between phases	kV	16,1		
TRV, peak	kV	16,4	-28,4	-15,4
Make time	ms	-	-	-
Arc duration	ms	10,0	0,2	10,0
Opening time	ms	-		
Break time	ms	-	-	-

Voltage closing coil - Vd.c. Gas pressure at 20 °C - MPa
 Voltage opening coil - Vd.c. Operating pressure

Remarks: Recloser closed and cleared.



**TEST NUMBER: 100527-6086**

Time interval since previous test	min	-	
Time interval between operations	s	1,02	
Operation	CO		
Phase	C	B	A
Applied voltage, phase value	kV	9,42	9,39
Applied voltage, between phases	kV	16,2	
Making current, peak	kA	-23,0	17,8
Breaking current, phase value	kA	8,04	8,04
Average current, three phase	kA	8,04	
Breaking current, DC-component	%	39	20
Recovery voltage, phase value	kV	9,34	9,29
Recovery voltage, between phases	kV	16,1	
TRV, peak	kV	18,2	-18,6
Make time	ms	-	-
Arc duration	ms	9,0	9,0
Opening time	ms	-	
Break time	ms	-	-

Voltage closing coil

- Vd.c.

Gas pressure at 20 °C


- MPa


Voltage opening coil

- Vd.c.

Operating pressure

Remarks: Recloser closed and cleared.







TEST NUMBER: 100527-6087

Time interval since previous test	min	-		
Time interval between operations	s	1,03		
Operation		CO		
Phase		C	B	A
Applied voltage, phase value	kV	9,43	9,41	9,32
Applied voltage, between phases	kV	16,3		
Making current, peak	kA	21,3	13,8	-22,5
Breaking current, phase value	kA	8,06	8,06	8,05
Average current, three phase	kA	8,06		
Breaking current, DC-component	%	32	5	38
Recovery voltage, phase value	kV	9,33	9,28	9,23
Recovery voltage, between phases	kV	16,1		
TRV, peak	kV	-18,4	33,0	17,4
Make time	ms	-	-	-
Arc duration	ms	10,7	5,4	10,7
Opening time	ms	-		
Break time	ms	-	-	-
Voltage closing coil	- Vd.c.	Gas pressure at 20 °C		
Voltage opening coil	- Vd.c.	Operating pressure		

Remarks: Recloser closed and cleared.







TEST NUMBER: 100527-6088

Time interval since previous test	min	-		
Operation		O		
Phase		C	B	A
Breaking current, phase value	kA	8,14	8,17	8,11
Average current, three phase	kA	8,14		
Breaking current, DC-component	%	10	73	65
Recovery voltage, phase value	kV	9,35	9,23	9,23
Recovery voltage, between phases	kV	16,1		
TRV, peak	kV	-19,1	21,7	17,9
Arc duration	ms	9,5	1,3	9,5
Opening time	ms	-		
Break time	ms	-	-	-

Voltage opening coil - Vd.c. Gas pressure at 20 °C - MPa
Operating pressure


Remarks: Recloser cleared.





TEST NUMBER: 100527-6089

Time interval since previous test	min	-		
Time interval between operations	s	0,520		
Operation		CO		
Phase		C	B	A
Applied voltage, phase value	kV	9,42	9,39	9,31
Applied voltage, between phases	kV	16,2		
Making current, peak	kA	23,2	-19,1	-16,3
Breaking current, phase value	kA	5,37	8,14	8,15
Average current, three phase	kA	7,22		
Breaking current, DC-component	%	27	49	27
Recovery voltage, phase value	kV	9,35	9,31	9,21
Recovery voltage, between phases	kV	16,1		
TRV, peak	kV	-14,5	14,7	-31,6
Make time	ms	-	-	-
Arc duration	ms	9,9	9,9	3,0
Opening time	ms	-		
Break time	ms	-	-	-
Voltage closing coil	- Vd.c.	Gas pressure at 20 °C		- MPa
Voltage opening coil	- Vd.c.	Operating pressure		

Remarks: Recloser closed and cleared.




TEST NUMBER: 100527-6090


Time interval since previous test	min	-	
Time interval between operations	s	1,03	
Operation		CO	
Phase	C	B	A
Applied voltage, phase value	kV	9,41	9,37
Applied voltage, between phases	kV	16,2	
Making current, peak	kA	12,6	-22,6
Breaking current, phase value	kA	8,04	8,00
Average current, three phase	kA	8,01	
Breaking current, DC-component	%	2	39
Recovery voltage, phase value	kV	9,31	9,15
Recovery voltage, between phases	kV	16,0	
TRV, peak	kV	19,3	-30,3
Make time	ms	-	-
Arc duration	ms	7,4	1,8
Opening time	ms	-	
Break time	ms	-	-


 Voltage closing coil
 - Vd.c.
 Voltage opening coil
 - Vd.c.

 Gas pressure at 20 °C
 Operating pressure

- MPa


Remarks: Recloser closed and cleared.





TEST NUMBER: 100527-6091

Time interval since previous test	min	-		
Time interval between operations	s	1,02		
Operation		CO		
Phase		C	B	A
Applied voltage, phase value	kV	9,39	9,33	9,27
Applied voltage, between phases	kV	16,2		
Making current, peak	kA	-15,7	-	-
Breaking current, phase value	kA	8,04	8,02	8,02
Average current, three phase	kA	8,03		
Breaking current, DC-component	%	13	41	28
Recovery voltage, phase value	kV	9,30	9,18	9,16
Recovery voltage, between phases	kV	16,0		
TRV, peak	kV	-19,5	-29,9	18,4
Make time	ms	-	-	-
Arc duration	ms	7,1	1,7	7,1
Opening time	ms	-		
Break time	ms	-	-	-
Voltage closing coil	- Vd.c.	Gas pressure at 20 °C		- MPa
Voltage opening coil	- Vd.c.	Operating pressure		


Remarks: Recloser closed and cleared.






TEST NUMBER: 100527-6092

Time interval since previous test	min	-		
Operation		O		
Phase		C	B	A
Breaking current, phase value	kA	8,14	8,17	8,11
Average current, three phase	kA	8,14		
Breaking current, DC-component	%	11	74	65
Recovery voltage, phase value	kV	9,34	9,24	9,25
Recovery voltage, between phases	kV	16,1		
TRV, peak	kV	-19,2	21,3	18,1
Arc duration	ms	8,3	0,2	8,3
Opening time	ms	-		
Break time	ms	-	-	-
Voltage opening coil	- Vd.c.	Gas pressure at 20 °C Operating pressure		
		- MPa		





Remarks: Recloser cleared.


TEST NUMBER: 100527-6093


Time interval since previous test	min	-		
Time interval between operations	s	0,521		
Operation	CO			
Phase		C	B	A
Applied voltage, phase value	kV	9,26	9,41	9,33
Applied voltage, between phases	kV	16,2		
Making current, peak	kA	22,6	-13,5	-21,1
Breaking current, phase value	kA	8,15	8,16	8,13
Average current, three phase	kA	8,15		
Breaking current, DC-component	%	72	10	64
Recovery voltage, phase value	kV	9,34	9,30	9,25
Recovery voltage, between phases	kV	16,1		
TRV, peak	kV	-14,0	33,2	13,6
Make time	ms	-	-	-
Arc duration	ms	12,0	6,1	12,0
Opening time	ms	-		
Break time	ms	-	-	-
Voltage closing coil	- Vd.c.	Gas pressure at 20 °C		- MPa
Voltage opening coil	- Vd.c.	Operating pressure		


Remarks: Recloser closed and cleared.




TEST NUMBER: 100527-6094

Time interval since previous test	min	-		
Time interval between operations	s	1,02		
Operation		CO		
Phase		C	B	A
Applied voltage, phase value	kV	9,45	9,42	9,34
Applied voltage, between phases	kV	16,3		
Making current, peak	kA	17,2	-23,3	18,3
Breaking current, phase value	kA	8,07	8,05	8,05
Average current, three phase	kA	8,06		
Breaking current, DC-component	%	19	41	22
Recovery voltage, phase value	kV	9,31	9,32	9,22
Recovery voltage, between phases	kV	16,1		
TRV, peak	kV	32,4	19,1	-17,4
Make time	ms	-	-	-
Arc duration	ms	4,4	9,9	9,9
Opening time	ms	-		
Break time	ms	-	-	-
Voltage closing coil	- Vd.c.	Gas pressure at 20 °C		- MPa
Voltage opening coil	- Vd.c.	Operating pressure		


Remarks: Recloser closed and cleared.





TEST NUMBER: 100527-6095

Time interval since previous test	min	-		
Time interval between operations	s	1,02		
Operation		CO		
Phase		C	B	A
Applied voltage, phase value	kV	9,45	9,41	9,34
Applied voltage, between phases	kV	16,3		
Making current, peak	kA	-19,3	23,0	-15,8
Breaking current, phase value	kA	8,09	8,09	8,08
Average current, three phase	kA	8,09		
Breaking current, DC-component	%	26	38	12
Recovery voltage, phase value	kV	9,33	9,35	9,25
Recovery voltage, between phases	kV	16,1		
TRV, peak	kV	-31,8	-19,7	17,5
Make time	ms	-	-	-
Arc duration	ms	2,8	8,4	8,4
Opening time	ms	-		
Break time	ms	-	-	-
Voltage closing coil	- Vd.c.	Gas pressure at 20 °C		- MPa
Voltage opening coil	- Vd.c.	Operating pressure		

Remarks: Recloser closed and cleared.







TEST NUMBER: 100527-6096

Time interval since previous test	min	-		
Operation		O		
Phase		C	B	A
Breaking current, phase value	kA	8,13	8,17	8,10
Average current, three phase	kA	8,13		
Breaking current, DC-component	%	13	75	63
Recovery voltage, phase value	kV	9,30	9,29	9,21
Recovery voltage, between phases	kV	16,1		
TRV, peak	kV	-32,7	-14,6	13,1
Arc duration	ms	7,1	13,7	13,7
Opening time	ms	-		
Break time	ms	-	-	-
Voltage opening coil	- Vd.c.	Gas pressure at 20 °C Operating pressure		
		- MPa		

Remarks: Recloser cleared.




TEST NUMBER: 100527-6097


Time interval since previous test	min	-		
Time interval between operations	s	0,516		
Operation		CO		
Phase		C	B	A
Applied voltage, phase value	kV	9,41	9,37	9,29
Applied voltage, between phases	kV	16,2		
Making current, peak	kA	23,1	-19,7	-15,7
Breaking current, phase value	kA	5,35	8,12	8,14
Average current, three phase	kA	7,2		
Breaking current, DC-component	%	39	52	24
Recovery voltage, phase value	kV	9,34	9,30	9,19
Recovery voltage, between phases	kV	16,1		
TRV, peak	kV	-14,4	14,7	-31,7
Make time	ms	-	-	-
Arc duration	ms	10,9	11,0	4,1
Opening time	ms	-		
Break time	ms	-	-	-


 Voltage closing coil - Vd.c.
 Voltage opening coil - Vd.c.

 Gas pressure at 20 °C
 Operating pressure

- MPa


Remarks: Recloser closed and cleared.





TEST NUMBER: 100527-6098

Time interval since previous test	min	-		
Time interval between operations	s	1,03		
Operation		CO		
Phase		C	B	A
Applied voltage, phase value	kV	9,40	9,36	9,29
Applied voltage, between phases	kV	16,2		
Making current, peak	kA	-13,4	-21,6	23,0
Breaking current, phase value	kA	8,02	8,00	7,99
Average current, three phase	kA	8,00		
Breaking current, DC-component	%	4	35	39
Recovery voltage, phase value	kV	9,29	9,21	9,18
Recovery voltage, between phases	kV	16,0		
TRV, peak	kV	19,2	-30,8	-18,0
Make time	ms	-	-	-
Arc duration	ms	8,3	2,6	8,2
Opening time	ms	-		
Break time	ms	-	-	-
Voltage closing coil	- Vd.c.	Gas pressure at 20 °C		
Voltage opening coil	- Vd.c.	Operating pressure		

Remarks: Recloser closed and cleared.





TEST NUMBER: 100527-6099


Time interval since previous test	min	-	
Time interval between operations	s	1,02	
Operation		CO	
Phase	C	B	A
Applied voltage, phase value	kV	9,38	9,33
Applied voltage, between phases	kV	16,1	
Making current, peak	kA	-13,1	22,6
Breaking current, phase value	kA	8,03	8,03
Average current, three phase	kA	8,03	
Breaking current, DC-component	%	3	38
Recovery voltage, phase value	kV	9,29	9,17
Recovery voltage, between phases	kV	15,8	
TRV, peak	kV	-19,2	30,1
Make time	ms	-	-
Arc duration	ms	7,0	-2,1
Opening time	ms	-	
Break time	ms	-	-

Voltage closing coil - Vd.c.
Voltage opening coil - Vd.c.


Gas pressure at 20 °C - MPa
Operating pressure


Remarks: Recloser closed and cleared.




TEST NUMBER: 100527-6100


Time interval since previous test	min	-		
Operation		O		
Phase		C	B	A
Breaking current, phase value	kA	8,11	8,14	8,08
Average current, three phase	kA	8,11		
Breaking current, DC-component	%	10	74	66
Recovery voltage, phase value	kV	9,32	9,22	9,21
Recovery voltage, between phases	kV	16,0		
TRV, peak	kV	-19,1	21,6	18,1
Arc duration	ms	10,8	2,6	10,8
Opening time	ms	-		
Break time	ms	-	-	-
Voltage opening coil	- Vd.c.	Gas pressure at 20 °C - MPa		
		Operating pressure		


Remarks: Recloser cleared.



TEST NUMBER: 100527-6101


Time interval since previous test	min	-		
Time interval between operations	s	0,519		
Operation		CO		
Phase	C	B	A	
Applied voltage, phase value	kV	9,40	9,39	9,31
Applied voltage, between phases	kV	16,2		
Making current, peak	kA	21,1	-21,6	12,4
Breaking current, phase value	kA	8,12	8,11	8,12
Average current, three phase	kA	8,12		
Breaking current, DC-component	%	64	65	3
Recovery voltage, phase value	kV	9,33	9,30	9,30
Recovery voltage, between phases	kV	16,1		
TRV, peak	kV	-14,2	14,8	-32,8
Make time	ms	-	-	-
Arc duration	ms	11,0	11,0	4,9
Opening time	ms	-		
Break time	ms	-	-	-
Voltage closing coil	- Vd.c.	Gas pressure at 20 °C		
Voltage opening coil	- Vd.c.	Operating pressure		


Remarks: Recloser closed and cleared.





TEST NUMBER: 100527-6102


Time interval since previous test	min	-		
Time interval between operations	s	1,02		
Operation	CO			
Phase	C	B	A	
Applied voltage, phase value	kV	9,41	9,38	9,30
Applied voltage, between phases	kV	16,2		
Making current, peak	kA	-17,7	6,67	22,3
Breaking current, phase value	kA	8,02	8,04	7,99
Average current, three phase	kA	8,02		
Breaking current, DC-component	%	21	18	40
Recovery voltage, phase value	kV	9,30	9,24	9,19
Recovery voltage, between phases	kV	16,0		
TRV, peak	kV	19,0	-32,2	-17,3
Make time	ms	-	-	-
Arc duration	ms	8,7	3,2	8,7
Opening time	ms	-		
Break time	ms	-	-	-
Voltage closing coil	- Vd.c.	Gas pressure at 20 °C		
Voltage opening coil	- Vd.c.	Operating pressure		

Remarks: Recloser closed and cleared.



TEST NUMBER: 100527-6103


Time interval since previous test	min	-		
Time interval between operations	s	1,02		
Operation		CO		
Phase		C	B	A
Applied voltage, phase value	kV	9,42	9,39	9,31
Applied voltage, between phases	kV	16,2		
Making current, peak	kA	11,7	21,3	-21,5
Breaking current, phase value	kA	8,06	8,04	8,03
Average current, three phase	kA	8,04		
Breaking current, DC-component	%	1	36	35
Recovery voltage, phase value	kV	9,28	9,30	9,20
Recovery voltage, between phases	kV	16,0		
TRV, peak	kV	-32,9	-18,6	17,2
Make time	ms	-	-	-
Arc duration	ms	5,2	10,4	10,4
Opening time	ms	-		
Break time	ms	-	-	-
Voltage closing coil	- Vd.c.	Gas pressure at 20 °C		- MPa
Voltage opening coil	- Vd.c.	Operating pressure		


Remarks: Recloser closed and cleared.



TEST NUMBER: 100527-6104

Time interval since previous test	min	-		
Operation		O		
Phase		C	B	A
Breaking current, phase value	kA	8,12	8,15	8,08
Average current, three phase	kA	8,12		
Breaking current, DC-component	%	14	75	63
Recovery voltage, phase value	kV	9,32	9,21	9,21
Recovery voltage, between phases	kV	16,0		
TRV, peak	kV	-19,3	21,3	17,9
Arc duration	ms	10,3	2,2	10,3
Opening time	ms	-		
Break time	ms	-	-	-

Voltage opening coil	- Vd.c.	Gas pressure at 20 °C	- MPa
		Operating pressure	

Remarks: Recloser cleared.






TEST NUMBER: 100527-6105

Time interval since previous test	min	-		
Time interval between operations	s	0,519		
Operation	CO			
Phase	C B A			
Applied voltage, phase value	kV	9,40	9,37	9,29
Applied voltage, between phases	kV	16,2		
Making current, peak	kA	22,5	-21,0	-14,0
Breaking current, phase value	kA	8,18	8,11	8,12
Average current, three phase	kA	8,14		
Breaking current, DC-component	%	73	63	12
Recovery voltage, phase value	kV	9,26	9,32	9,24
Recovery voltage, between phases	kV	16,1		
TRV, peak	kV	22,2	19,7	-17,9
Make time	ms	-	-	-
Arc duration	ms	2,3	10,5	10,5
Opening time	ms	-		
Break time	ms	-	-	-

Voltage closing coil - Vd.c. Gas pressure at 20 °C - MPa
 Voltage opening coil - Vd.c. Operating pressure

Remarks: Recloser closed and cleared.







TEST NUMBER: 100527-6106

Time interval since previous test	min	-		
Time interval between operations	s	1,02		
Operation	CO			
Phase	C	B	A	
Applied voltage, phase value	kV	9,41	9,38	9,29
Applied voltage, between phases	kV	16,2		
Making current, peak	kA	-23,2	19,6	16,0
Breaking current, phase value	kA	8,03	8,03	8,02
Average current, three phase	kA	8,03		
Breaking current, DC-component	%	40	26	14
Recovery voltage, phase value	kV	9,32	9,28	9,17
Recovery voltage, between phases	kV	16,0		
TRV, peak	kV	18,1	-18,1	32,1
Make time	ms	-	-	-
Arc duration	ms	9,6	9,6	4,1
Opening time	ms	-		
Break time	ms	-	-	-
Voltage closing coil	- Vd.c.	Gas pressure at 20 °C		- MPa
Voltage opening coil	- Vd.c.	Operating pressure		

Remarks: Recloser closed and cleared. NSDD in the S-fase after 115 ms.







TEST NUMBER: 100527-6107

Time interval since previous test	min	-		
Time interval between operations	s	1,02		
Operation		CO		
Phase	C	B	A	
Applied voltage, phase value	kV	9,44	9,42	9,33
Applied voltage, between phases	kV	16,3		
Making current, peak	kA	22,8	-13,9	-20,9
Breaking current, phase value	kA	8,07	8,06	8,06
Average current, three phase	kA	8,06		
Breaking current, DC-component	%	37	6	31
Recovery voltage, phase value	kV	9,34	9,31	9,21
Recovery voltage, between phases	kV	16,1		
TRV, peak	kV	-18,7	18,8	-31,1
Make time	ms	-	-	-
Arc duration	ms	8,2	8,3	2,6
Opening time	ms	-		
Break time	ms	-	-	-
Voltage closing coil	- Vd.c.	Gas pressure at 20 °C		- MPa
Voltage opening coil	- Vd.c.	Operating pressure		

Remarks: Recloser closed and cleared.







TEST NUMBER: 100527-6108

Time interval since previous test	min	-		
Operation	O			
Phase	C B A			
Breaking current, phase value	kA	8,12	8,09	8,09
Average current, three phase	kA	8,1		
Breaking current, DC-component	%	10	75	64
Recovery voltage, phase value	kV	9,29	9,30	9,21
Recovery voltage, between phases	kV	16,1		
TRV, peak	kV	-32,8	-14,5	12,8
Arc duration	ms	5,5	12,1	12,1
Opening time	ms	-		
Break time	ms	-	-	-

Voltage opening coil	- Vd.c.	Gas pressure at 20 °C	- MPa
		Operating pressure	


Remarks: Recloser cleared.




**TEST NUMBER: 100527-6109**


Time interval since previous test	min	-		
Time interval between operations	s	0,517		
Operation		CO		
Phase		C	B	A
Applied voltage, phase value	kV	9,42	9,40	9,32
Applied voltage, between phases	kV	16,2		
Making current, peak	kA	22,2	-12,6	-21,5
Breaking current, phase value	kA	8,13	8,15	8,12
Average current, three phase	kA	8,13		
Breaking current, DC-component	%	69	4	66
Recovery voltage, phase value	kV	9,33	9,28	9,24
Recovery voltage, between phases	kV	16,1		
TRV, peak	kV	-14,1	33,2	13,3
Make time	ms	-	-	-
Arc duration	ms	11,5	5,4	11,5
Opening time	ms	-		
Break time	ms	-	-	-
Voltage closing coil	- Vd.c.	Gas pressure at 20 °C		
Voltage opening coil	- Vd.c.	- MPa		


Remarks: Recloser closed and cleared.




TEST NUMBER: 100527-6110

Time interval since previous test	min	-		
Time interval between operations	s	1,02		
Operation	CO			
Phase	C	B	A	
Applied voltage, phase value	kV	9,45	9,42	9,34
Applied voltage, between phases	kV	16,3		
Making current, peak	kA	18,4	-23,3	17,0
Breaking current, phase value	kA	8,07	8,06	8,05
Average current, three phase	kA	8,06		
Breaking current, DC-component	%	23	40	17
Recovery voltage, phase value	kV	9,33	9,33	9,23
Recovery voltage, between phases	kV	16,1		
TRV, peak	kV	32,0	19,3	-17,5
Make time	ms	-	-	-
Arc duration	ms	3,7	9,2	9,2
Opening time	ms	-		
Break time	ms	-	-	-
Voltage closing coil	- Vd.c.	Gas pressure at 20 °C		- MPa
Voltage opening coil	- Vd.c.	Operating pressure		

Remarks: Recloser closed and cleared.






TEST NUMBER: 100527-6111

Time interval since previous test	min	-		
Time interval between operations	s	1,02		
Operation		CO		
Phase	C	B	A	
Applied voltage, phase value	kV	9,47	9,29	9,37
Applied voltage, between phases	kV	16,2		
Making current, peak	kA	-20,2	22,9	-14,9
Breaking current, phase value	kA	8,11	8,11	8,10
Average current, three phase	kA	8,11		
Breaking current, DC-component	%	28	37	9
Recovery voltage, phase value	kV	9,35	9,37	9,27
Recovery voltage, between phases	kV	16,2		
TRV, peak	kV	-31,6	-19,8	17,8
Make time	ms	-	-	-
Arc duration	ms	2,6	8,2	8,2
Opening time	ms	-		
Break time	ms	-	-	-


Voltage closing coil - Vd.c. Gas pressure at 20 °C - MPa
 Voltage opening coil - Vd.c. Operating pressure


Remarks: Recloser closed and cleared.





TEST NUMBER: 100527-6112


Time interval since previous test	min	-		
Operation	O			
Phase	C B A			
Breaking current, phase value	kA	8,11	8,08	8,08
Average current, three phase	kA	8,09		
Breaking current, DC-component	%	12	76	63
Recovery voltage, phase value	kV	9,26	9,26	9,20
Recovery voltage, between phases	kV	16,0		
TRV, peak	kV	-32,7	-12,4	25,8
Arc duration	ms	5,3	11,9	11,9
Opening time	ms	-		
Break time	ms	-	-	-
Voltage opening coil	- Vd.c.	Gas pressure at 20 °C		- MPa
		Operating pressure		

Remarks: Recloser cleared.



TEST NUMBER: 100527-6113


Time interval since previous test	min	-		
Time interval between operations	s	0,518		
Operation		CO		
Phase	C	B	A	
Applied voltage, phase value	kV	9,39	9,35	9,27
Applied voltage, between phases	kV	16,2		
Making current, peak	kA	20,5	14,8	-22,9
Breaking current, phase value	kA	8,11	8,12	8,13
Average current, three phase	kA	8,12		
Breaking current, DC-component	%	58	18	34
Recovery voltage, phase value	kV	9,31	9,25	9,20
Recovery voltage, between phases	kV	16,0		
TRV, peak	kV	-14,3	32,5	13,3
Make time	ms	-	-	-
Arc duration	ms	10,7	4,0	10,7
Opening time	ms	-		
Break time	ms	-	-	-
Voltage closing coil	- Vd.c.	Gas pressure at 20 °C		
Voltage opening coil	- Vd.c.	Operating pressure		


Remarks: Recloser closed and cleared.


**TEST NUMBER: 100527-6114**

Time interval since previous test	min	-		
Time interval between operations	s	1,02		
Operation		CO		
Phase		C	B	A
Applied voltage, phase value	kV	9,38	9,36	9,27
Applied voltage, between phases	kV	16,2		
Making current, peak	kA	20,2	-22,5	14,2
Breaking current, phase value	kA	8,01	8,00	7,99
Average current, three phase	kA	8,00		
Breaking current, DC-component	%	30	37	8
Recovery voltage, phase value	kV	9,28	9,22	9,13
Recovery voltage, between phases	kV	16,0		
TRV, peak	kV	-17,2	18,5	-32,6
Make time	ms	-	-	-
Arc duration	ms	10,8	10,9	5,9
Opening time	ms	-		
Break time	ms	-	-	-
Voltage closing coil	- Vd.c.	Gas pressure at 20 °C		
Voltage opening coil	- Vd.c.	- MPa		


Remarks: Recloser closed and cleared.





TEST NUMBER: 100527-6115

Time interval since previous test	min	-		
Time interval between operations	s	1,02		
Operation	CO			
Phase	C	B	A	
Applied voltage, phase value	kV	9,36	9,32	9,25
Applied voltage, between phases	kV	16,1		
Making current, peak	kA	-22,0	20,6	13,9
Breaking current, phase value	kA	8,01	8,01	8,00
Average current, three phase	kA	8,01		
Breaking current, DC-component	%	36	30	6
Recovery voltage, phase value	kV	9,27	9,23	9,13
Recovery voltage, between phases	kV	16,0		
TRV, peak	kV	18,1	-17,9	32,3
Make time	ms	-	-	-
Arc duration	ms	10,8	10,7	5,5
Opening time	ms	-		
Break time	ms	-	-	-
Voltage closing coil	- Vd.c.	Gas pressure at 20 °C		
Voltage opening coil	- Vd.c.	- MPa		

Remarks: Recloser closed and cleared.







TEST NUMBER: 100527-6116

Time interval since previous test	min	-		
Operation		O		
Phase		C	B	A
Breaking current, phase value	kA	8,11	8,09	8,08
Average current, three phase	kA	8,09		
Breaking current, DC-component	%	11	75	64
Recovery voltage, phase value	kV	9,33	9,21	9,21
Recovery voltage, between phases	kV	16,0		
TRV, peak	kV	-19,0	21,7	18,0
Arc duration	ms	7,9	-0,3	7,9
Opening time	ms	-		
Break time	ms	-	-	-
Voltage opening coil	- Vd.c.	Gas pressure at 20 °C		
		Operating pressure		

Remarks: Recloser cleared.







TEST NUMBER: 100527-6117

Time interval since previous test	min	-		
Time interval between operations	s	0,521		
Operation	CO			
Phase	C	B	A	
Applied voltage, phase value	kV	9,42	9,38	9,30
Applied voltage, between phases	kV	16,2		
Making current, peak	kA	20,6	14,9	-23,0
Breaking current, phase value	kA	8,13	8,15	8,16
Average current, three phase	kA	8,15		
Breaking current, DC-component	%	58	18	39
Recovery voltage, phase value	kV	9,33	9,28	9,24
Recovery voltage, between phases	kV	16,1		
TRV, peak	kV	-14,5	32,6	13,5
Make time	ms	-	-	-
Arc duration	ms	11,0	4,4	11,0
Opening time	ms	-		
Break time	ms	-	-	-
Voltage closing coil	- Vd.c.	Gas pressure at 20 °C		- MPa
Voltage opening coil	- Vd.c.	Operating pressure		

Remarks: Recloser closed and cleared.






TEST NUMBER: 100527-6118


Time interval since previous test	min	-		
Time interval between operations	s	1,02		
Operation		CO		
Phase		C	B	A
Applied voltage, phase value	kV	9,43	9,41	9,32
Applied voltage, between phases	kV	16,3		
Making current, peak	kA	20,6	-21,6	13,0
Breaking current, phase value	kA	8,06	8,04	8,04
Average current, three phase	kA	8,05		
Breaking current, DC-component	%	31	34	3
Recovery voltage, phase value	kV	9,32	9,32	9,21
Recovery voltage, between phases	kV	16,1		
TRV, peak	kV	31,4	19,9	-17,9
Make time	ms	-	-	-
Arc duration	ms	2,9	8,4	8,4
Opening time	ms	-		
Break time	ms	-	-	-

Voltage closing coil - Vd.c.
Voltage opening coil - Vd.c.

Gas pressure at 20 °C
Operating pressure



Remarks: Recloser closed and cleared.



TEST NUMBER: 100527-6119


Time interval since previous test	min	-		
Time interval between operations	s	1,02		
Operation		CO		
Phase		C	B	A
Applied voltage, phase value	kV	9,45	9,43	9,36
Applied voltage, between phases	kV	16,3		
Making current, peak	kA	-23,3	15,2	20,2
Breaking current, phase value	kA	8,09	8,08	8,08
Average current, three phase	kA	8,08		
Breaking current, DC-component	%	39	10	29
Recovery voltage, phase value	kV	9,36	9,32	9,21
Recovery voltage, between phases	kV	16,1		
TRV, peak	kV	18,6	-18,8	31,4
Make time	ms	-	-	-
Arc duration	ms	8,9	8,9	3,2
Opening time	ms	-		
Break time	ms	-	-	-

Voltage closing coil - Vd.c.
Voltage opening coil - Vd.c.

Gas pressure at 20 °C - MPa
Operating pressure

Remarks: Recloser closed and cleared.







TEST NUMBER: 100527-6120

Time interval since previous test	min	-		
Operation		O		
Phase		C	B	A
Breaking current, phase value	kA	8,10	8,08	8,07
Average current, three phase	kA	8,08		
Breaking current, DC-component	%	13	100	63
Recovery voltage, phase value	kV	9,32	9,21	9,22
Recovery voltage, between phases	kV	16,0		
TRV, peak	kV	-19,1	21,9	18,0
Arc duration	ms	9,0	1,0	9,0
Opening time	ms	-		
Break time	ms	-	-	-


Voltage opening coil	- Vd.c.	Gas pressure at 20 °C		
		- MPa		
		Operating pressure		


Remarks: Recloser cleared.




TEST NUMBER: 100527-6121

Time interval since previous test	min	-		
Time interval between operations	s	0,520		
Operation	CO			
Phase		C	B	A
Applied voltage, phase value	kV	9,41	9,37	9,30
Applied voltage, between phases	kV	16,2		
Making current, peak	kA	21,4	13,2	-22,2
Breaking current, phase value	kA	8,12	8,13	8,10
Average current, three phase	kA	8,12		
Breaking current, DC-component	%	64	6	71
Recovery voltage, phase value	kV	9,33	9,28	9,23
Recovery voltage, between phases	kV	16,1		
TRV, peak	kV	-14,4	33,0	13,3
Make time	ms	-	-	-
Arc duration	ms	11,2	4,9	11,2
Opening time	ms	-		
Break time	ms	-	-	-
Voltage closing coil	- Vd.c.	Gas pressure at 20 °C		
Voltage opening coil	- Vd.c.	- MPa Operating pressure		

Remarks: Recloser closed and cleared.




TEST NUMBER: 100527-6122


Time interval since previous test	min	-		
Time interval between operations	s	1,02		
Operation	CO			
Phase	C	B	A	
Applied voltage, phase value	kV	9,42	9,40	9,31
Applied voltage, between phases	kV	16,2		
Making current, peak	kA	23,3	-17,2	-18,3
Breaking current, phase value	kA	8,03	8,03	8,02
Average current, three phase	kA	8,03		
Breaking current, DC-component	%	39	18	22
Recovery voltage, phase value	kV	9,32	9,27	9,22
Recovery voltage, between phases	kV	16,1		
TRV, peak	kV	-18,9	32,4	17,0
Make time	ms	-	-	-
Arc duration	ms	8,3	3,7	8,3
Opening time	ms	-		
Break time	ms	-	-	-

 Voltage closing coil - Vd.c.
 Voltage opening coil - Vd.c.


 Gas pressure at 20 °C - MPa
 Operating pressure


Remarks: Recloser closed and cleared.




TEST NUMBER: 100527-6123

Time interval since previous test	min	-		
Time interval between operations	s	1,02		
Operation	CO			
Phase	C	B	A	
Applied voltage, phase value	kV	9,44	9,43	9,35
Applied voltage, between phases	kV	16,3		
Making current, peak	kA	22,3	-20,4	-14,5
Breaking current, phase value	kA	8,07	8,06	8,06
Average current, three phase	kA	8,06		
Breaking current, DC-component	%	36	28	8
Recovery voltage, phase value	kV	9,31	9,26	9,23
Recovery voltage, between phases	kV	16,1		
TRV, peak	kV	-18,8	32,0	18,2
Make time	ms	-	-	-
Arc duration	ms	9,2	5,2	9,2
Opening time	ms	-		
Break time	ms	-	-	-
Voltage closing coil	- Vd.c.	Gas pressure at 20 °C		
Voltage opening coil	- Vd.c.	- MPa		


Remarks: Recloser closed and cleared.





TEST NUMBER: 100527-6128

Time interval since previous test	min	-		
Operation		O		
Phase	C	B	A	
Breaking current, phase value	kA	8,12	8,14	8,08
Average current, three phase	kA	8,11		
Breaking current, DC-component	%	13	75	64
Recovery voltage, phase value	kV	9,31	9,18	9,19
Recovery voltage, between phases	kV	16,0		
TRV, peak	kV	-19,0	21,2	17,9
Arc duration	ms	10,0	2,0	10,0
Opening time	ms	-		
Break time	ms	-	-	-
Voltage opening coil	- Vd.c.	Gas pressure at 20 °C	- MPa	
		Operating pressure		

Remarks: Recloser cleared.






TEST NUMBER: 100527-6129


Time interval since previous test	min	-		
Time interval between operations	s	0,521		
Operation		CO		
Phase	C	B	A	
Applied voltage, phase value	kV	9,40	9,35	9,26
Applied voltage, between phases	kV	16,2		
Making current, peak	kA	22,9	-20,2	-15,0
Breaking current, phase value	kA	8,11	8,10	8,12
Average current, three phase	kA	8,11		
Breaking current, DC-component	%	46	57	19
Recovery voltage, phase value	kV	9,33	9,27	9,16
Recovery voltage, between phases	kV	16,0		
TRV, peak	kV	-14,6	13,8	-32,1
Make time	ms	-	-	-
Arc duration	ms	11,6	11,7	4,9
Opening time	ms	-		
Break time	ms	-	-	-

Voltage closing coil - Vd.c.
Voltage opening coil - Vd.c.

Gas pressure at 20 °C - MPa
Operating pressure

Remarks: Recloser closed and cleared.




TEST NUMBER: 100527-6130


Time interval since previous test	min	-		
Time interval between operations	s	1,03		
Operation	CO			
Phase	C	B	A	
Applied voltage, phase value	kV	9,38	9,33	9,26
Applied voltage, between phases	kV	16,1		
Making current, peak	kA	-14,8	-19,6	22,4
Breaking current, phase value	kA	8,01	7,97	7,97
Average current, three phase	kA	7,98		
Breaking current, DC-component	%	9	28	37
Recovery voltage, phase value	kV	9,28	9,18	9,14
Recovery voltage, between phases	kV	15,9		
TRV, peak	kV	19,3	-31,3	-17,8
Make time	ms	-	-	-
Arc duration	ms	7,5	2,0	7,5
Opening time	ms	-		
Break time	ms	-	-	-


 Voltage closing coil - Vd.c.
 Voltage opening coil - Vd.c.

Gas pressure at 20 °C

- MPa

Operating pressure

Remarks: Recloser closed and cleared.






TEST NUMBER: 100527-6131

Time interval since previous test	min	-		
Time interval between operations	s	1,02		
Operation	CO			
Phase	C	B	A	
Applied voltage, phase value	kV	9,38	9,31	9,25
Applied voltage, between phases	kV	16,1		
Making current, peak	kA	-14,5	23,1	-21,2
Breaking current, phase value	kA	8,02	8,02	8,01
Average current, three phase	kA	8,02		
Breaking current, DC-component	%	9	40	31
Recovery voltage, phase value	kV	9,28	9,16	9,14
Recovery voltage, between phases	kV	15,9		
TRV, peak	kV	-19,4	30,0	18,4
Make time	ms	-	-	-
Arc duration	ms	7,5	1,4	7,5
Opening time	ms	-		
Break time	ms	-	-	-

Voltage closing coil	- Vd.c.	Gas pressure at 20 °C	- MPa
Voltage opening coil	- Vd.c.	Operating pressure	

Remarks: Recloser closed and cleared.







TEST NUMBER: 100527-6132


Time interval since previous test	min	-		
Operation	O			
Phase			C	B
Breaking current, phase value	kA	8,11	8,14	8,08
Average current, three phase	kA	8,11		
Breaking current, DC-component	%	12	73	63
Recovery voltage, phase value	kV	9,31	9,20	9,21
Recovery voltage, between phases	kV	16,0		
TRV, peak	kV	-19,1	21,3	18,0
Arc duration	ms	8,0	0,8	8,0
Opening time	ms	-		
Break time	ms	-	-	-
Voltage opening coil	- Vd.c.	Gas pressure at 20 °C		- MPa
		Operating pressure		


Remarks: Recloser cleared.




TEST NUMBER: 100527-6133

Time interval since previous test	min	-		
Time interval between operations	s	0,521		
Operation		CO		
Phase		C	B	A
Applied voltage, phase value	kV	9,42	9,37	9,27
Applied voltage, between phases	kV	16,2		
Making current, peak	kA	22,4	-13,2	-20,4
Breaking current, phase value	kA	8,12	8,12	8,13
Average current, three phase	kA	8,12		
Breaking current, DC-component	%	72	9	64
Recovery voltage, phase value	kV	9,31	9,25	9,20
Recovery voltage, between phases	kV	16,0		
TRV, peak	kV	-13,9	33,0	13,4
Make time	ms	-	-	-
Arc duration	ms	11,6	5,6	11,6
Opening time	ms	-		
Break time	ms	-	-	-
Voltage closing coil	- Vd.c.	Gas pressure at 20 °C		
Voltage opening coil	- Vd.c.	- MPa Operating pressure		


Remarks: Recloser closed and cleared.





TEST NUMBER: 100527-6134

Time interval since previous test	min	-	
Time interval between operations	s	1,02	
Operation		CO	
Phase		C	B
Applied voltage, phase value	kV	9,37	9,35
Applied voltage, between phases	kV	16,2	
Making current, peak	kA	-5,58	-9,46
Breaking current, phase value	kA	8,03	7,97
Average current, three phase	kA	7,99	
Breaking current, DC-component	%	22	40
Recovery voltage, phase value	kV	9,28	9,15
Recovery voltage, between phases	kV	15,9	
TRV, peak	kV	19,6	-29,9
Make time	ms	-	-
Arc duration	ms	6,2	2,4
Opening time	ms	-	
Break time	ms	-	-
Voltage closing coil	- Vd.c.	Gas pressure at 20 °C	
Voltage opening coil	- Vd.c.	- MPa	

Remarks: Recloser closed and cleared.







TEST NUMBER: 100527-6135

Time interval since previous test	min	-		
Time interval between operations	s	1,02		
Operation		CO		
Phase	C	B	A	
Applied voltage, phase value	kV	9,38	9,34	9,26
Applied voltage, between phases	kV	16,2		
Making current, peak	kA	-20,7	21,4	-12,3
Breaking current, phase value	kA	8,00	8,00	8,01
Average current, three phase	kA	8,00		
Breaking current, DC-component	%	33	35	2
Recovery voltage, phase value	kV	9,28	9,25	9,35
Recovery voltage, between phases	kV	16,1		
TRV, peak	kV	17,6	-18,0	32,4
Make time	ms	-	-	-
Arc duration	ms	7,5	7,4	2,3
Opening time	ms	-		
Break time	ms	-	-	-
Voltage closing coil	- Vd.c.	Gas pressure at 20 °C		- MPa
Voltage opening coil	- Vd.c.	Operating pressure		

Remarks: Recloser closed and cleared.







TEST NUMBER: 100527-6136

Time interval since previous test	min	-		
Operation	O			
Phase	C	B	A	
Breaking current, phase value	kA	8,11	8,14	8,08
Average current, three phase	kA	8,11		
Breaking current, DC-component	%	12	74	65
Recovery voltage, phase value	kV	9,31	9,21	9,22
Recovery voltage, between phases	kV	16,0		
TRV, peak	kV	-19,0	21,3	18,0
Arc duration	ms	9,2	1,1	9,2
Opening time	ms	-		
Break time	ms	-	-	-


Voltage opening coil	- Vd.c.	Gas pressure at 20 °C	- MPa
		Operating pressure	


Remarks: Recloser cleared.




TEST NUMBER: 100527-6137

Time interval since previous test	min	-		
Time interval between operations	s	0,520		
Operation		CO		
Phase		C	B	A
Applied voltage, phase value	kV	9,39	9,37	9,29
Applied voltage, between phases	kV	16,2		
Making current, peak	kA	23,2	-15,5	4,21
Breaking current, phase value	kA	8,01	7,97	8,00
Average current, three phase	kA	7,99		
Breaking current, DC-component	%	33	28	49
Recovery voltage, phase value	kV	9,25	9,30	9,14
Recovery voltage, between phases	kV	16,0		
TRV, peak	kV	-16,0	16,8	-28,3
Make time	ms	-	-	-
Arc duration	ms	9,9	10,0	0,1
Opening time	ms	-		
Break time	ms	-	-	-
Voltage closing coil	- Vd.c.	Gas pressure at 20 °C		
Voltage opening coil	- Vd.c.	- MPa		

Remarks: Recloser closed and cleared.





TEST NUMBER: 100527-6138

Time interval since previous test	min	-		
Time interval between operations	s	1,03		
Operation		CO		
Phase	C	B	A	
Applied voltage, phase value	kV	9,38	9,36	9,29
Applied voltage, between phases	kV	16,2		
Making current, peak	kA	-9,07	-22,4	20,1
Breaking current, phase value	kA	8,02	7,98	7,98
Average current, three phase	kA	7,99		
Breaking current, DC-component	%	10	41	31
Recovery voltage, phase value	kV	9,28	9,14	9,14
Recovery voltage, between phases	kV	15,9		
TRV, peak	kV	19,7	-30,0	-18,3
Make time	ms	-	-	-
Arc duration	ms	6,7	2,2	6,7
Opening time	ms	-		
Break time	ms	-	-	-


Voltage closing coil - Vd.c.
Voltage opening coil - Vd.c.

Gas pressure at 20 °C
Operating pressure

6138



Remarks: Recloser closed and cleared.




TEST NUMBER: 100527-6139


Time interval since previous test	min	-		
Time interval between operations	s	1,02		
Operation		CO		
Phase		C	B	A
Applied voltage, phase value	kV	9,36	9,32	9,24
Applied voltage, between phases	kV	16,1		
Making current, peak	kA	5,52	22,4	-16,6
Breaking current, phase value	kA	8,04	7,99	8,00
Average current, three phase	kA	8,01		
Breaking current, DC-component	%	22	40	18
Recovery voltage, phase value	kV	9,28	9,16	9,14
Recovery voltage, between phases	kV	15,9		
TRV, peak	kV	-19,5	30,0	18,3
Make time	ms	-	-	-
Arc duration	ms	6,5	2,0	6,5
Opening time	ms	-		
Break time	ms	-	-	-

Voltage closing coil - Vd.c.
Voltage opening coil - Vd.c.

Gas pressure at 20 °C - MPa
Operating pressure

Remarks: Recloser closed and cleared.







TEST NUMBER: 100527-6140

Time interval since previous test	min	-		
Operation	O			
Phase	C	B	A	
Breaking current, phase value	kA	8,11	8,14	8,07
Average current, three phase	kA	8,11		
Breaking current, DC-component	%	11	73	64
Recovery voltage, phase value	kV	9,31	9,20	9,21
Recovery voltage, between phases	kV	16,0		
TRV, peak	kV	-19,1	21,3	18,0
Arc duration	ms	9,0	0,8	9,0
Opening time	ms	-		
Break time	ms	-	-	-

Voltage opening coil	- Vd.c.	Gas pressure at 20 °C	- MPa
		Operating pressure	


Remarks: Recloser cleared.





TEST NUMBER: 100527-6141

Time interval since previous test	min	-		
Time interval between operations	s	0,520		
Operation	CO			
Phase	C	B	A	
Applied voltage, phase value	kV	9,39	9,36	9,28
Applied voltage, between phases	kV	16,2		
Making current, peak	kA	23,0	-15,2	-19,7
Breaking current, phase value	kA	5,31	8,07	8,03
Average current, three phase	kA	7,14		
Breaking current, DC-component	%	14	23	55
Recovery voltage, phase value	kV	9,18	9,15	9,02
Recovery voltage, between phases	kV	15,8		
TRV, peak	kV	-16,1	16,6	-27,2
Make time	ms	-	-	-
Arc duration	ms	8,4	8,5	1,2
Opening time	ms	-		
Break time	ms	-	-	-
Voltage closing coil	- Vd.c.	Gas pressure at 20 °C		
Voltage opening coil	- Vd.c.	Operating pressure		


Remarks: Recloser closed and cleared.





TEST NUMBER: 100527-6142

Time interval since previous test	min	-		
Time interval between operations	s	1,03		
Operation	CO			
Phase	C	B	A	
Applied voltage, phase value	kV	9,27	9,24	9,16
Applied voltage, between phases	kV	16,0		
Making current, peak	kA	15,9	-23,0	19,4
Breaking current, phase value	kA	7,92	7,90	7,90
Average current, three phase	kA	7,91		
Breaking current, DC-component	%	14	41	27
Recovery voltage, phase value	kV	9,16	9,14	9,05
Recovery voltage, between phases	kV	15,8		
TRV, peak	kV	31,9	18,7	-16,8
Make time	ms	-	-	-
Arc duration	ms	5,1	10,5	10,6
Opening time	ms	-		
Break time	ms	-	-	-
Voltage closing coil	- Vd.c.	Gas pressure at 20 °C		
Voltage opening coil	- Vd.c.	Operating pressure		

Remarks: Recloser closed and cleared.






TEST NUMBER: 100527-6143

Time interval since previous test	min	-		
Time interval between operations	s	1,02		
Operation	CO			
Phase	C	B	A	
Applied voltage, phase value	kV	9,30	9,25	9,17
Applied voltage, between phases	kV	16,0		
Making current, peak	kA	-20,4	22,0	-13,4
Breaking current, phase value	kA	7,67	7,67	7,65
Average current, three phase	kA	7,66		
Breaking current, DC-component	%	32	36	4
Recovery voltage, phase value	kV	8,78	8,75	8,74
Recovery voltage, between phases	kV	15,2		
TRV, peak	kV	16,7	-17,1	30,9
Make time	ms	-	-	-
Arc duration	ms	7,4	7,3	2,3
Opening time	ms	-		
Break time	ms	-	-	-
Voltage closing coil	- Vd.c.	Gas pressure at 20 °C		- MPa
Voltage opening coil	- Vd.c.	Operating pressure		

Remarks: Recloser closed and cleared.





TDT 2108-10

DUTY: No-load test


Page 231

TEST NUMBER

100527-6144

CONDITION BEFORE TEST

Recloser in same condition.



TEST NUMBER: 100527-6144

Operation		CO		
Phase		C	B	A
Current closing coil	A		-	
Closing time	ms	-	-	-
Current opening coil	A		-	
Opening time	ms	-	-	-

Voltage closing coil	- Vd.c.	Gas pressure at 20 °C	- MPa
Voltage opening coil	- Vd.c.	Operating pressure	

Remarks: -



TDT 2108-10


CONDITION AFTER TEST

Page 233

CONDITION AFTER TEST

Externally no visible change.

ELECTROCON SRL



DIELECTRIC VERIFICATION AND CONTACT RESISTANCE MEASUREMENT


Vacuum interrupter type: VG5

Manufactured by: ABB AG,
Ratingen, Germany*Dielectric test (state of vacuum) and measurement of contact resistance:*

Recloser withstood a 1 min power-frequency voltage across open vacuum interrupters.

POLE	INTERRUPTER SERIAL No.	Contact resistance (measured with 100 A d.c.)	
		100526-6001 Before	100527-6144 After
A	786015	58,8 $\mu\Omega$	57,6 $\mu\Omega$
B	785993	56,1 $\mu\Omega$	58,2 $\mu\Omega$
C	786004	45,4 $\mu\Omega$	52,4 $\mu\Omega$
Test voltage		50 kV	40 kV

The results of the contact resistance measurements indicate that the interrupters are capable of carrying the rated normal current without exceeding the prescribed temperature-rise limits.





TDT 2108-10

FINGERPRINT MEASUREMENT OF ELECTRONIC CONTROL CIRCUIT

Annex I

Fingerprint measurement of the electronic control circuit was performed at KEMA High-Voltage Laboratory.
See enclosed record of tests on the following pages.

ELECTROCON SPU

RECORD OF TESTS

TDT 1486-10

OBJECT	Electronic control circuit for control of a three -phase solid insulated metal-enclosed automatic vacuum circuit recloser	
TYPE	Recloser: EPR-1 Controller: EVRC2A	SERIAL No. 1002 0001 0906 0001
Fn = 50/60 Hz; Vaux = 220 VAC / 24 VDC Recloser: Ur = 15,5 kV, Ir = 630 A		
MANUFACTURER	ENTEC Eelectric & Electronic Co., Ltd. Gyungki-Do, Korea-South	
CLIENT	ENTEC Eelectric & Electronic Co., Ltd. Gyungki-Do, Korea-South	
TESTED BY	KEMA HIGH-VOLTAGE LABORATORY Utrechtseweg 310 - 6812 AR Arnhem - the Netherlands	
DATE OF TESTS	31 May 2010	
TEST PROGRAMME	Fingerprint measurement of electronic control circuit.	
SUMMARY AND CONCLUSION	As far as specified by the manufacturer, the measuring results are conforming the specifications.	

This Record of Tests applies only to the object tested. The responsibility for conformity of any object having the same designations with that tested rests with the Manufacturer.

This report consists of 14 pages in total.

© Copyright: Only integral reproduction of this report is permitted without written permission from KEMA. Electronic copies in e.g. PDF-format or scanned version of this report may be available and have the status "for information only". The sealed and bound version of the report is the only valid version.

KEMA Nederland B.V.

P.G.A. Bus
KEMA T&D Testing Services
Managing Director

Arnhem, 16 August 2010

TABLE OF CONTENTS

TABLE OF CONTENTS	2
1 Identification of the test object.....	3
1.1 Ratings assigned by the manufacturer	3
1.2 Description of the test object.....	3
2 General information.....	4
2.1 The tests were partly witnessed by	4
2.2 The tests were carried out by.....	4
2.3 Purpose of the test	4
2.4 Applicable standards	4
3 Correct operation and charging of main capacitor.....	5
4 Correct operation at power supply interruption	9
5 Power consumption.....	10
APPENDIX A PHOTOGRAHPS OF THE TEST OBJECT	11
APPENDIX B LIST OF INSTRUMENTS USED	13
APPENDIX C CONNECTION DIAGRAM EPR-KE016	14

1 IDENTIFICATION OF THE TEST OBJECT

1.1 Ratings assigned by the manufacturer

Vacuum recloser

Serial number	10020001
Number of phases	3
Insulation material	Solid
Rated maximum voltage	15,5 kV
Rated current	630 A
Rated lightning impulse voltage	110 kV
Power frequency insulation level	50 kV
Short-circuit current	16 kA

Recloser-M Controller

Serial number	09060001
Software revision	V5.09
Power supply	220 / 24 VAC / VDC
Rated frequency	50 / 60 Hz
Rated voltage measuring input	4 V
Rated current measuring input	1 A
Main capacitor	

Voltage level main capacitor	125 VDC
Power supply charging circuit	220 VAC
Battery voltage	24 VDC
Closing coil resistance (20°C)	4 Ω
number of turns	720
wire material	coated copper, 1,2 mm Ø
Opening coil resistance (20°C)	2 Ω
number of turns	400
wire material	coated copper, 1,3 mm Ø

1.2 Description of the test object

Manufacturer	ENTEC Eelectric & Electronic Co., Ltd.
Type	Recloser: EPR-1 Controller: EVCR2A-n
Year of manufacture	2009/2010

2 GENERAL INFORMATION

2.1 The tests were partly witnessed by

Name	Company
Kim, Y.	ENTEC Eelectric & Electronic Co., Ltd.
Choi, M.	Gyungki-Do, Korea-South

2.2 The tests were carried out by

Name	Company
Achterkamp, M.	KEMA Nederland B.V., Arnhem, the Netherlands

2.3 Purpose of the test

Purpose of the test was to verify whether the material complies with the manufacturer specifications.

2.4 Applicable standards

When reference is made to a standard and the date of issue is not stated, this applies to the latest issue, including amendments, which have been officially published prior to the date of the tests.

3 CORRECT OPERATION AND CHARGING OF MAIN CAPACITOR

Standard and date

Standard -
Test dates 31 May 2010

Environmental conditions


Ambient temperature 22 °C Ambient air pressure 1016 hPa
Temperature of test object 22 °C Humidity 35 %

Characteristic test data

Power supply charging circuit 187...242 VAC
Frequency 50 Hz
Capacitor supervision level 113 VDC
Battery voltage 24 VDC

The correct operation of the magnetic actuator and the charging of the main capacitor is measured for different values of the auxiliary power supply voltage.

power supply voltage (VAC)	battery voltage (VDC)	charge main capacitor	
		current (ADC)	time (s)
220	24	18 Apeak see plot below	1,49




Charging main capacitor with battery voltage

The recloser can be operated local by means of push buttons. The push buttons are connect to binary inputs of the recloser controller.


Remote operation is only possible with communication interface.

Uaux	close operation				open operation				Uc (VDC)
	td (ms)	Id (Ap)	tr (s)	Ir (Ap)	td (ms)	Id (Ap)	tr (ms)	Ir (Ap)	
(VAC)									
187	57,3	6,5	671,8	8,4	19,8	6,9	465,2	11,0	125,0
220	47,3	13,5	286,8	14,2	27,4	15,4	164,3	17,5	125,0
242	52,0	7,1	178,5	7,5	21,9	6,7	123,1	8,3	125,0


td = discharge time; Id = discharge current, tr = recharge time; Ir = recharge current




Open operation at Uaux = 187 VAC




Close operation at Uaux = 187 VAC




Open operation at $U_{aux} = 220$ VAC



Close operation at $U_{aux} = 220$ VAC



Open operation at $U_{aux} = 242$ VAC



Close operation at $U_{aux} = 242$ VAC

4 CORRECT OPERATION AT POWER SUPPLY INTERRUPTION

Standard and date

Standard -
Test dates 31 May 2010

Environmental conditions

Ambient temperature	22 °C	Ambient air pressure	1016 hPa
Temperature of test object	22 °C	Humidity	35 %

Characteristic test data

Power supply charging circuit	187...242 VAC
Frequency	50 Hz
Capacitor supervision level	113 VDC
Battery voltage	24 VDC

The correct operation of the magnetic actuator is measured during an interruption of the power supply voltage. Because the main capacitor is charged by the 24 VDC battery the test is performed without 220 VAC power supply voltage.

test description	observation
manual close / open / close operation without 220 VAC power supply after: 1 minute	correct operation
5 minutes	correct operation

5 POWER CONSUMPTION

Standard and date

Standard -
Test dates 31 May 2010

Environmental conditions


Ambient temperature 22 °C Ambient air pressure 1016 hPa
Temperature of test object 22 °C Humidity 35 %

Characteristic test data

Power supply charging circuit 187...242 VAC
Frequency 50 Hz
Capacitor supervision level 113 VDC
Battery voltage 24 VDC

The power consumption of the control circuit at a close and open operation is measured.

test description	observation / value
recloser in closed position, quiescent state	28 VA
open operation	125 VA (see plot below)
close operation	100 VAp



Battery voltage, current and power consumption during open operation

APPENDIX A PHOTOGRAPHS OF THE TEST OBJECT



ELECTROCON SRU

APPENDIX B LIST OF INSTRUMENTS USED

no	description	manufacturer	type	KEMA ID
1	Oscilloscope	Yokogawa	DL1640	105217
2	Current probe	Tektronix	A6303	105335
3	Current probe amplifier	Tektronix	AM503	67241
4	Digital Multi Meter	Hewlett Packard	34401A	105257
5	100:1 resistive divider	KEMA	100:1	no.1

APPENDIX C CONNECTION DIAGRAM EPR-KE016

