

# DC/AC True RMS Clamp Meter

**Model:BM803A+**



## Specifications:

- 3 1/4 Digit , Maximum Display:3999
- Over Load Protection
- Auto Range
- Measured frequency AC voltage profile
- Inrush Current
- Auto power off
- Battery power is insufficient
- DCA Automatic Zero
- MAX expand of the pincers:52mm
- DC Voltage: 400mV/4V/40V/400V±0.8%±2, 1000V±1%±3
- AC Voltage: 400mV/4V/40V/400V±1.2%±5, 700V±1.5%±3
- DC Current: 400/1000A±2%±10
- AC Current: 400/1000A±2%±10
- Resistance: 400/4k/40k/400k/4MΩ±0.8%±5 ; 40MΩ±1.5%±5
- Capacitance: 10n/100n/1u/10 u/100u/1000uF±3%±5, 10mF±5%±5
- Frequency: 10 /100 /1k /10k/100k/1M/10M/30MHz±0.5%±3
- Duty Test : 1%~99.9%±0.5%±3
- Temperature : -50~400°C±1.2%±4, 400~1000°C±1.9%±15  
-58~400oF ±1.2%±6, 400~1832oF ±1.9%±25
- Continuity Test: BUZZER , DIODE , NCV
- Power Supply: 9V×1 6F22
- Size : 249×89×38mm



*Made in China*